# Kickbase 0.4 – what's new and test list

**Format:** Do this → expected result. Tick the box when it matches. Report anything that does not. Tested in Lemon.

## What's in 0.4

### Effects and mixer

- **FX send matrix.** Old SEND links move to the matrix automatically when a project loads; INS shows as its own row.
- **Remove FX channel.** The FX popup has "- remove FXn" on the last channel. If it has effects or sends it asks first; Ctrl+Z restores effects, EQ, compressor, level and sends.
- **PATTERN rows.** The FX knob is gone, VOL is larger and the FX button shows "N x FX".
- **MIX tab.** The combined wave has the full width on top with the knobs below; WIDE/NARROW is gone.
- **SIDECHAIN now lives in MASTER.** MASTER has the sub-tabs MIXER, SIDECHAIN and MAXIMIZER (the FX version: SIDECHAIN and MAXIMIZER). SIDECHAIN is no longer a main tab.

### KICK tab

- **New SYNTH tab layout.** The MIX control sits in the tab row (SYNTH / SAMPLE / ENVELOPE). KEY moved into TUNING, the envelope curves are above the knobs, and the knobs use the 48 px size.
- **SYNTH / SAMPLE buttons are gone.** MIX alone controls the blend: left = synth only, middle = both, right = sample only. Old presets are migrated.
- **SAMPLE tab.** Split into three boxes: PITCH, AMP and REVERSE.

### Instrument: timing, phase and length

- **TIMING diagram.** All seven lanes on one time axis with the volume contour. Drag the left edge (POS DELAY) and the right edge (LENGTH). FOCUS / OVERVIEW.
- **Small timing diagram on INSTR.** Read-only; a click opens TIMING. It is now larger, split 50/50 with the envelope graph, shows NUDGE, START and POLARITY, and you pick which engine to show.
- **Own start phase per source.** Each source (including SUB alone) has its own START phase, visible in the timing diagram.
- **MAX LENGTH per group.** A MAX time per instrument, set as a multiple (up to x10). MAX also raises the FM ENV TIME. Automating the MAX time shows a warning.
- **SYNC lists** go down to 1/64 (at the end of the list, sorted menu). TIMING OVERVIEW fits on one row.
- **WARP ENV curve** over time in the WARP ENV group: source, AMOUNT, DIRECT DEC and a playhead.
- **EDIT HARMONICS button** visible in the OSC tabs. Narrower PHASE group; PRESET and HELP laid out more clearly.

### Oscillators, FM and filter

- **OSC OUTPUT.** Click the MODE label until it says OUTPUT to see the real output (phase, warp and unison with detune/blend).
- **WARP FM on OSC 1.** You choose the modulator (OSC 2 or OSC 3); the diagram explains it and warns when the chosen source is off.
- **FM diagram.** Waveform and index over time (drawn dry, without the filter).
- **Harmonic editor.** Tooltips on every field and a HELP tab.
- **FILTER.** The allpass knobs use the same size as the rest; the FILTER on/off switch is in the tab button; the FILTER 2 power button is 22 px.
- **New starting values** for a fresh instrument: filter cutoff 10 kHz and SUB 0. Existing presets keep their own values.

### Look and feel

- **Hover everywhere.** Chips, tabs, pill buttons and dropdowns brighten under the mouse; popup menus have a rounded background and a cyan highlight.
- Shared edge glow, clearer menu levels, glass buttons and glass PREVIEWS; more air in menus.
- **Glow strength** Off / Weak / Strong in SETTINGS (off by default).
- Large OUT knob; knob and label form one block; SWING / HUMAN / DELAY have one knob per row.
- **Tabs and breadcrumb.** INSTRUMENT sub-tabs are ordered INSTR | OSC 1, OSC 2, OSC 3, SAMPLE, FM | FILTER, MIX, TIMING with dividers. The breadcrumb at the top right shows the path (no "KICKBASE" in it); the MASTER tab row has none, since its buttons already show where you are.

### Preview and JOG

- **One preview at a time.** PREVIEW switches off when you audition locally (speaker, LISTEN, key, slice, JOG).
- **JOG TEST BPM.** Own knob for the tempo of the JOG test.

## Before you start

Click inside the plugin window first so it has keyboard focus (otherwise the DAW may take Ctrl+Z and similar shortcuts). Older presets and projects should sound as before; the exceptions are listed under "Older projects".

## Test list

### KICK tab

☐ Open KICK > SYNTH → the MIX control is in the tab row, KEY is in TUNING, the envelope curves sit above the knobs, nothing overlaps or is clipped. Make the window narrower → the preset selector and the help button stay usable, the MIX label is readable.
☐ Look for the old SYNTH / SAMPLE buttons → they are gone.
☐ MIX fully left → only the synthesised kick. Middle → both. Fully right → only the sample.
☐ Open an old preset that had SYNTH off, and one that had SAMPLE off → they sound as before. If a preset sounds different, note its name.
☐ KICK > SAMPLE → three boxes PITCH, AMP and REVERSE; each control responds.
☐ HELP button on the KICK tab → opens help and does not cover the tab row.

### Hover and menus

☐ Move the mouse over chips, tabs, pill buttons and dropdowns → each brightens while hovered.
☐ Open a dropdown or context menu → rounded dark background, the hovered item has a cyan highlight.
☐ Open menus in several tabs → the levels are easy to tell apart and there is air around the items.

### Look and feel

☐ SETTINGS > Glow strength: Off, Weak, Strong → the edge glow follows; Off is the default.
☐ PREVIEW buttons → glass look. OUT knob → large. SWING / HUMAN / DELAY → one knob per row.
☐ FILTER tab → the allpass knobs are the same size as the others. Slide FILTER 1 and FILTER 2 on/off → the tab button and the diagrams follow; the FILTER 2 power button is easy to hit.
☐ Knobs and labels on INSTR, FILTER, SAMPLE and TIMING → knob and label read as one block. Note anything that is hard to use; row 2 knobs are about 12 % narrower than before, and FILTER 2 contents sit 6 px lower than FILTER 1.

### FX and mixer

- ☐ Open an old project with an FX link in SEND mode → one normal FX row in the popup (no double row). An INS link shows as “INS FXn”.
- ☐ FX popup, last channel, “- remove FXn” → asks first if the channel has effects or sends; Ctrl+Z restores effects, EQ, compressor, level and sends.
- ☐ PATTERN rows → one larger VOL knob, no FX knob. The FX button shows None / FX / “2 x FX”; hovering lists the channels.
- ☐ MIX tab → the wave has the full width on top, knobs below, WIDE/NARROW is gone.

### MASTER and SIDECHAIN

- ☐ MASTER (instrument) → three sub-tabs MIXER, SIDECHAIN, MAXIMIZER; there is no SIDECHAIN main tab. In the FX plugin: SIDECHAIN and MAXIMIZER.
- ☐ Switch between the sub-tabs → the content changes; no breadcrumb is shown in the MASTER tab row.
- ☐ SIDECHAIN inside MASTER → everything fits without clipping; knob, curve, presets and help button work as before (instrument and FX plugin). Ducking is audible on the sources that have SC on.
- ☐ MAXIMIZER → drive, clip, ceiling and release work; the “through the maximizer” switches per source at the bottom decide what goes through it.

### INSTRUMENT, OSC and timing

- ☐ INSTRUMENT sub-tabs → INSTR | OSC 1, OSC 2, OSC 3, SAMPLE, FM | FILTER, MIX, TIMING with dividers. The FM on/off icon controls FM.
- ☐ Breadcrumb → INSTRUMENT > instrument name > OSC 2, follows tab and instrument changes; no KICKBASE in it. Also KICK, and ANALYZER > SPECTRUM.
- ☐ The row above the instrument tabs → taller, nothing clipped.
- ☐ OSC 1, click the MODE label until it says OUTPUT → Phase shifts the wave sideways, Warp changes the shape. Unison 1 shows two periods; Unison 3+ shows many periods with beating; Detune and Blend change the beating. Push Position, Warp and Phase to their extremes with Unison 1 and 8 → the picture never goes empty and nothing crashes.
- ☐ OSC 1 WARP FM → choose OSC 2, then OSC 3 as modulator; the text and diagram follow, and a warning appears if the chosen source is off.
- ☐ WARP ENV group → the curve over time follows source, AMOUNT and DIRECT DEC; the playhead moves with a note.
- ☐ EDIT HARMONICS button in an OSC tab → opens the harmonic editor.
- ☐ TIMING opens in FOCUS → drag the left edge of the tall lane: POS DELAY follows; drag the right edge: LENGTH follows. Click another lane → it becomes tall and the knobs switch motor. With SYNC on, dragging does nothing.
- ☐ Play a note → playhead and release line move in the lanes. NUDGE and POLARITY → lanes shift / contour flips. NUDGE ≠ 0 and drag the left edge → no jump on the first drag.
- ☐ Give a source its own START phase (SUB alone too) → the timing diagram shows it and the sound starts at that phase.
- ☐ LENGTH 0 without SYNC → dragging right of the left edge pulls LENGTH out from 0.
- ☐ MAX LENGTH → set it per group (x1 … x10): the envelopes stretch with it, FM ENV TIME follows. Automate the MAX time → a warning is shown.
- ☐ SYNC menus → the lists go down to 1/64 and are sorted; an old project with a sync value still sounds the same.
- ☐ OVERVIEW shows all boxes, FOCUS goes back; close and reopen the tab → the choice is kept.
- ☐ INSTR tab → a larger time diagram next to the envelope graph (50/50); the playhead moves with a note; dragging changes nothing; a click opens TIMING.
- ☐ FM tab → the FM diagram shows and follows the FM settings.
- ☐ Harmonic editor → hover the fields (tooltips); HELP opens the HARMONICS tab.

## Preview and JOG

- ☐ Start PREVIEW, then press a speaker button / LISTEN / a key / a slice / JOG → PREVIEW switches off and no sound hangs.
- ☐ JOG panel → the JOG TEST BPM knob sets the tempo of the JOG test.

## Older projects

- ☐ Open a project and a preset made in 0.3 → loads and sounds as before.
- ☐ Open an old preset where a source was switched off and MIX was not in the middle → it may sound different (the MIX control now does what the old switches did). Note the preset name.
- ☐ Create a new instrument → filter cutoff starts at 10 kHz and SUB at 0 %. These are new starting values; old presets keep theirs.