

#ADR <Absolute store address> RET Prints block name and offset

#ADR <Block Name> <Offset> RET Prints absolute store address

#ALO <Block Name> <size in octal> RET
Allocate a block - no zero size block allowed

#BLK <Key characters><LP (Optional)> RET
Outputs directory details of blocks starting with the key characters.
1-4 Key characters are allowed, a "?" indicating a don't care.
If LP then O/P is to line printer.

#CMD <Command Name> <Command enter block name> RET
Adds additional commands to the system.

#CON <Dumpstack name> <WDT Time Value> RET
Continue running a process.

#COP <Old Block Name> <New Block Name>
<New size if larger than old (optional)> RET
Copy old block into new created block. If OLD and NEW block names are the same the block is adjusted in size without changing its offset in the system capability table.

#DCA <block><start offset><(optional) no. of words> RET
Display capability block, giving block names.

#DEL <Block Name> RET Delete a block

#DIS <Block Name><offset in block><No. of words (optional-default 1)>
Display block starting at specified offset.

#EDI <Block Name><starting offset in Block><data><data> etc. RET
Edit locations; there is a limit to number of consecutive edits which can be carried out, by the size of input buffer area and should therefore be limited to 64 characters; both offset and data numerics are in octal.

#FST RET Prints free space in each store module

#GIV <Block name><base><size> RET Allocates Capability Table entry

#HOL <block offset> RET
Replace instruction with invalid instruction, saving old inst.

#LOI RET/load assembler output via data break.

#LOO RET/load assembler output from serial medium reader.

#LOP

#MON <block offset> RET
Continuous monitor of location e.g. Device status registers etc.

NAM <set offset> RET Prints name of block.

OFL <CPU><Number> RET Remove module from system.

OFS RET Complementary to # ONS

ONL <Store or CPU><Number> RET Online module to system

ONS <Process name> RET
Routes teletype input to another process

PRO RET Details of running process
T = Waiting for timeout
F = Waiting for flag
P = Printing on teletype
S = Suspended
R = Ready to run or running

REB <Key characters><No. of key chars. (optional)> RET
Delete all blocks starting with key character/s

REG <dumpstack> RET Prints all registers of process

REL <block offset> RET Replace original instruction

REN <old block name><new block name> RET Renames block

RES <Process name><IAR><Time WDT> RET Will restart process with PD
pointer reset to 8R21

RSP <Block name><Pointer Block name><offset in Pointer Block>
<Access code*> RET
Creates a pointer and stores it away.
*Access code in same format as most sig. 8 bits of pointer

RUN <Dumpstack name><Pointer Block name>
<Code Block name><WDT (time value)>
<i.a.r. value> RET Start a process (WDT value in mS)

STA <dumpstack> RET Prints process call stack

STO <Dumpstack name> RET Stop a process

SUS <Dumpstack name> RET Suspend a process from running

TEX <Name of Block for Text to be inserted> RET
<'Text *" (Text terminator)> RET
Return and line feed can be input and treated as normal characters.
The input is limited to 64 characters between 'returns', characters
are packed 3 characters to a word the first word of the Block
(offset 0) holds the number of characters inserted.

N.B. RETURN (RET) can be replaced by LINE FEED (LF) at the end of each command.

