

TB EQ

DETAILED ENGLISH USER MANUAL

A 24-band parametric equalizer that combines static EQ, Dynamic EQ, spectral resonance reduction, channel modes, auditioning, and detailed analysis.



Catalog version: 2.0.0

Documentation edition: 2026-08-04

Host-visible endpoints documented: 438

1. Product purpose

A 24-band parametric equalizer that combines static EQ, Dynamic EQ, spectral resonance reduction, channel modes, auditioning, and detailed analysis.

Static EQ solves stable tonal problems but cannot follow level-dependent harshness. Broadband compression reacts to level but often affects more spectrum than necessary. TB EQ places static shape, dynamic movement, and spectral resonance control inside the same per-band workflow so tonal balance and problem control remain localized.

What result it creates

- Precise static shaping across as many as 24 bands
- Level-dependent cuts or boosts
- Narrow spectral resonance reduction
- Channel-selective and delta monitoring workflows

Signal flow

**Input Gain -> 24 ordered bands, each with static EQ plus optional Dynamic or Spectral processing
-> Output Gain -> analyzer and audition paths**

2. Complete feature guide

Band creation and selection

Create, select, enable, or delete bands from the analyzer and band selector. Node dragging edits frequency and gain; the mouse wheel changes Q. The full host appendix lists every per-band endpoint.

Static filter types

Each band supports Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, and All Pass where the deployed build exposes them. Frequency, Gain, Q, and channel mode define the basic response.

Dynamic EQ

Dynamic mode adds Threshold, Range, Ratio, Attack, and Release behavior to the static band. Range determines the maximum direction and amount of movement.

Spectral processing

Spectral mode uses short-time spectral analysis to detect narrow components around the selected band. Sensitivity, depth/range, attenuation, and related controls determine what is reduced and by how much.

Mutual processing modes

Dynamic and Spectral layers are intended as distinct per-band processes. Use the mode that matches the problem instead of stacking two detectors on one band.

Channel and delta tools

Channel Mode targets the relevant stereo component. Delta Band, Delta Mode, and monitor/audition behavior isolate what a band or processing layer is changing.

Analyzer

The display combines the live spectrum, static curve, expected dynamic/spectral range, and real-time movement. Visuals confirm behavior but do not replace listening.

3. Quick start

1. Start at 0 dB Input and Output Gain.
2. Create or select a band and choose the static filter type.
3. Set Frequency, Gain, and Q while listening in context.
4. Enable Dynamic for level-dependent movement or Spectral for narrow resonance control.
5. Use delta/audition to verify the target.
6. Repeat only as needed and level-match the output.

4. Practical workflows

Harsh vocal resonance

1. Create a narrow Bell at the harsh frequency.
2. Keep static Gain near neutral if the harshness is intermittent.
3. Enable Spectral mode and lower Sensitivity until only the resonance reacts.
4. Set a conservative reduction range and audition the removed component.

Expected result: Harsh peaks are controlled while surrounding vocal tone remains open.

Dynamic low-mid cleanup

1. Create a broad Bell in the buildup region.
2. Enable Dynamic mode with a negative Range.
3. Set Threshold for loud phrases and tune Attack/Release to follow the phrase envelope.

Expected result: Low-mid density is reduced only when it becomes excessive.

Mastering tone

1. Use very broad Q values and small gains.
2. Work in channel modes only when the imbalance is clearly localized.
3. Use Output Gain for matched comparison.

Expected result: The balance changes subtly without unnecessary phase or dynamics movement.

5. Automation, gain staging, and session use

- Automate only controls that serve a clear musical transition. Fast movement of frequency, time, pitch, mode, oversampling, or algorithm selectors may intentionally create artifacts or require a host-safe transition.
- Match perceived loudness before judging quality. A louder setting will often appear better even when the processing decision is not better.
- Use the plug-in bypass endpoint for comparison and preserve an unprocessed source or earlier project version.
- Factory programs are starting points. Loading a program changes multiple parameters; save a new DAW preset after adapting it to the source.

- The parameter appendix is captured from the installed VST3 host contract. It lists every host-visible endpoint, its displayed range/options, default, automation status, and identifier.

6. Limits, cautions, and troubleshooting

- Twenty-four active dynamic or spectral bands can be CPU intensive.
- Narrow boosts can create large peaks.
- Delta monitoring is diagnostic and should be returned to normal before export.
- No audible change: confirm the plug-in and relevant sub-block are enabled, Mix/Amount is not at a neutral value, and the source contains energy in the processed region.
- Unexpected level: return input, output, send, feedback, and parallel-mix controls to conservative values, then rebuild the setting one block at a time.
- Automation does not match the panel: reload the project, confirm the DAW is addressing the current plug-in version, and check whether a factory program or state recall replaced values.
- Clicks or transitions: avoid sample-instant changes to algorithm, time, pitch, mode, or oversampling selectors unless the sound is intentional.

7. Complete host parameter reference

This appendix contains all 438 parameters exposed by the current installed VST3 to a host. Repeated EQ-band endpoints are intentionally listed rather than collapsed. Discrete options are printed in full when the host contract exposes them.

Parameter	Range / options	Default	Host status	Function
Band 1 Attenuation VST3 ID 1494252441	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 1 Channel Mode VST3 ID 231707632	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 1 Dynamic VST3 ID 2110033166	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 1 Dynamic Attack VST3 ID 1526674335	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 1 Dynamic Range VST3 ID 1380575462	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 1 Dynamic Ratio VST3 ID 1380581300	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 1 Dynamic Release VST3 ID 1848216944	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 1 Dynamic Threshold VST3 ID 679907220	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 1 Enabled VST3 ID 523155472	Off, On	On	Automatable	Enables this EQ band.
Band 1 Frequency VST3 ID 2057284585	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 1 Gain VST3 ID 2057298160	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 1 Q VST3 ID 2015360	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 1 Spectral VST3 ID 1705673301	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 1 Spectral Depth VST3 ID 924135888	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 1 Spectral Niddle VST3 ID 1020538023	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 1 Spectral Range VST3 ID 936943690	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 1 Spectral Sensitivity VST3 ID 1361263596	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 1 Type VST3 ID 2057708715	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 2 Attenuation VST3 ID 234272474	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 2 Channel Mode VST3 ID 1873632655	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 2 Dynamic VST3 ID 302578703	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 2 Dynamic Attack VST3 ID 1655757054	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.

Parameter	Range / options	Default	Host status	Function
Band 2 Dynamic Range VST3 ID 1731107751	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 2 Dynamic Ratio VST3 ID 1731113589	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 2 Dynamic Release VST3 ID 1554813937	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 2 Dynamic Threshold VST3 ID 39975381	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 2 Enabled VST3 ID 863184657	Off, On	Off	Automatable	Enables this EQ band.
Band 2 Frequency VST3 ID 2085913736	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 2 Gain VST3 ID 2085927311	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 2 Q VST3 ID 2016321	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 2 Spectral VST3 ID 1509159796	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 2 Spectral Depth VST3 ID 1053218607	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 2 Spectral Niddle VST3 ID 727135016	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 2 Spectral Range VST3 ID 1066026409	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 2 Spectral Sensitivity VST3 ID 364191243	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 2 Type VST3 ID 2086337866	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 3 Attenuation VST3 ID 1121776155	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 3 Channel Mode VST3 ID 1368074030	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 3 Dynamic VST3 ID 642607888	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 3 Dynamic Attack VST3 ID 1784839773	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 3 Dynamic Range VST3 ID 2081640040	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 3 Dynamic Ratio VST3 ID 2081645878	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 3 Dynamic Release VST3 ID 1261410930	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 3 Dynamic Threshold VST3 ID 1547527190	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 3 Enabled VST3 ID 1203213842	Off, On	Off	Automatable	Enables this EQ band.
Band 3 Frequency VST3 ID 2114542887	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 3 Gain VST3 ID 2114556462	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.

Parameter	Range / options	Default	Host status	Function
Band 3 Q VST3 ID 2017282	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 3 Spectral VST3 ID 1312646291	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 3 Spectral Depth VST3 ID 1182301326	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 3 Spectral Niddle VST3 ID 433732009	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 3 Spectral Range VST3 ID 1195109128	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 3 Spectral Sensitivity VST3 ID 1514602538	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 3 Type VST3 ID 2114967017	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 4 Attenuation VST3 ID 2009279836	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 4 Channel Mode VST3 ID 862515405	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 4 Dynamic VST3 ID 982637073	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 4 Dynamic Attack VST3 ID 1913922492	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 4 Dynamic Range VST3 ID 284688681	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 4 Dynamic Ratio VST3 ID 284694519	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 4 Dynamic Release VST3 ID 968007923	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 4 Dynamic Threshold VST3 ID 907595351	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 4 Enabled VST3 ID 1543243027	Off, On	Off	Automatable	Enables this EQ band.
Band 4 Frequency VST3 ID 2143172038	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 4 Gain VST3 ID 2143185613	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 4 Q VST3 ID 2018243	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 4 Spectral VST3 ID 1116132786	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 4 Spectral Depth VST3 ID 1311384045	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 4 Spectral Niddle VST3 ID 140329002	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 4 Spectral Range VST3 ID 1324191847	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 4 Spectral Sensitivity VST3 ID 517530185	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 4 Type VST3 ID 2143596168	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.

Parameter	Range / options	Default	Host status	Function
Band 5 Attenuation VST3 ID 749299869	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 5 Channel Mode VST3 ID 356956780	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 5 Dynamic VST3 ID 1322666258	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 5 Dynamic Attack VST3 ID 2043005211	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 5 Dynamic Range VST3 ID 635220970	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 5 Dynamic Ratio VST3 ID 635226808	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 5 Dynamic Release VST3 ID 674604916	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 5 Dynamic Threshold VST3 ID 267663512	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 5 Enabled VST3 ID 1883272212	Off, On	Off	Automatable	Enables this EQ band.
Band 5 Frequency VST3 ID 24317541	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 5 Gain VST3 ID 24331116	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 5 Q VST3 ID 2019204	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 5 Spectral VST3 ID 919619281	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 5 Spectral Depth VST3 ID 1440466764	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 5 Spectral Niddle VST3 ID 1994409643	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 5 Spectral Range VST3 ID 1453274566	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 5 Spectral Sensitivity VST3 ID 1667941480	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 5 Type VST3 ID 24741671	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 6 Attenuation VST3 ID 1636803550	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 6 Channel Mode VST3 ID 1998881803	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 6 Dynamic VST3 ID 1662695443	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 6 Dynamic Attack VST3 ID 24604282	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 6 Dynamic Range VST3 ID 985753259	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 6 Dynamic Ratio VST3 ID 985759097	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 6 Dynamic Release VST3 ID 381201909	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.

Parameter	Range / options	Default	Host status	Function
Band 6 Dynamic Threshold VST3 ID 1775215321	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 6 Enabled VST3 ID 75817749	Off, On	Off	Automatable	Enables this EQ band.
Band 6 Frequency VST3 ID 52946692	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 6 Gain VST3 ID 52960267	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 6 Q VST3 ID 2020165	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 6 Spectral VST3 ID 723105776	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 6 Spectral Depth VST3 ID 1569549483	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 6 Spectral Niddle VST3 ID 1701006636	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 6 Spectral Range VST3 ID 1582357285	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 6 Spectral Sensitivity VST3 ID 670869127	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 6 Type VST3 ID 53370822	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 7 Attenuation VST3 ID 376823583	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 7 Channel Mode VST3 ID 1493323178	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 7 Dynamic VST3 ID 2002724628	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 7 Dynamic Attack VST3 ID 153687001	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 7 Dynamic Range VST3 ID 1336285548	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 7 Dynamic Ratio VST3 ID 1336291386	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 7 Dynamic Release VST3 ID 87798902	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 7 Dynamic Threshold VST3 ID 1135283482	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 7 Enabled VST3 ID 415846934	Off, On	Off	Automatable	Enables this EQ band.
Band 7 Frequency VST3 ID 81575843	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 7 Gain VST3 ID 81589418	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 7 Q VST3 ID 2021126	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 7 Spectral VST3 ID 526592271	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 7 Spectral Depth VST3 ID 1698632202	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.

Parameter	Range / options	Default	Host status	Function
Band 7 Spectral Niddle VST3 ID 1407603629	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 7 Spectral Range VST3 ID 1711440004	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 7 Spectral Sensitivity VST3 ID 1821280422	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 7 Type VST3 ID 81999973	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 8 Attenuation VST3 ID 1264327264	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 8 Channel Mode VST3 ID 987764553	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 8 Dynamic VST3 ID 195270165	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 8 Dynamic Attack VST3 ID 282769720	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 8 Dynamic Range VST3 ID 1686817837	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 8 Dynamic Ratio VST3 ID 1686823675	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 8 Dynamic Release VST3 ID 1941879543	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 8 Dynamic Threshold VST3 ID 495351643	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 8 Enabled VST3 ID 755876119	Off, On	Off	Automatable	Enables this EQ band.
Band 8 Frequency VST3 ID 110204994	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 8 Gain VST3 ID 110218569	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 8 Q VST3 ID 2022087	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 8 Spectral VST3 ID 330078766	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 8 Spectral Depth VST3 ID 1827714921	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 8 Spectral Niddle VST3 ID 1114200622	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 8 Spectral Range VST3 ID 1840522723	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 8 Spectral Sensitivity VST3 ID 824208069	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 8 Type VST3 ID 110629124	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 9 Attenuation VST3 ID 4347297	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 9 Channel Mode VST3 ID 482205928	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 9 Dynamic VST3 ID 535299350	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.

Parameter	Range / options	Default	Host status	Function
Band 9 Dynamic Attack VST3 ID 411852439	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 9 Dynamic Range VST3 ID 2037355964	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 9 Dynamic Ratio VST3 ID 2037355964	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 9 Dynamic Release VST3 ID 1648476536	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 9 Dynamic Threshold VST3 ID 2002903452	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 9 Enabled VST3 ID 1095905304	Off, On	Off	Automatable	Enables this EQ band.
Band 9 Frequency VST3 ID 138834145	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 9 Gain VST3 ID 138847720	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 9 Q VST3 ID 2023048	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 9 Spectral VST3 ID 133565261	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 9 Spectral Depth VST3 ID 1956797640	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 9 Spectral Niddle VST3 ID 820797615	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 9 Spectral Range VST3 ID 1969605442	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 9 Spectral Sensitivity VST3 ID 1974619364	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 9 Type VST3 ID 139258275	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 10 Attenuation VST3 ID 891850978	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 10 Channel Mode VST3 ID 2124130951	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 10 Dynamic VST3 ID 875328535	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 10 Dynamic Attack VST3 ID 540935158	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 10 Dynamic Range VST3 ID 240398767	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 10 Dynamic Ratio VST3 ID 240404605	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 10 Dynamic Release VST3 ID 1355073529	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 10 Dynamic Threshold VST3 ID 1362971613	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 10 Enabled VST3 ID 1435934489	Off, On	Off	Automatable	Enables this EQ band.

Parameter	Range / options	Default	Host status	Function
Band 10 Frequency VST3 ID 167463296	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 10 Gain VST3 ID 167476871	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 10 Q VST3 ID 2024009	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 10 Spectral VST3 ID 2084535404	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 10 Spectral Depth VST3 ID 2085880359	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 10 Spectral Niddle VST3 ID 527394608	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 10 Spectral Range VST3 ID 2098688161	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 10 Spectral Sensitivity VST3 ID 977547011	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 10 Type VST3 ID 167887426	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 11 Attenuation VST3 ID 750853900	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 11 Channel Mode VST3 ID 1037613341	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 11 Dynamic VST3 ID 668606401	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 11 Dynamic Attack VST3 ID 1064943628	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 11 Dynamic Range VST3 ID 1296407257	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 11 Dynamic Ratio VST3 ID 1296413095	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 11 Dynamic Release VST3 ID 419466915	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 11 Dynamic Threshold VST3 ID 2040664071	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 11 Enabled VST3 ID 1229212355	Off, On	Off	Automatable	Enables this EQ band.
Band 11 Frequency VST3 ID 1063472662	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 11 Gain VST3 ID 1063486237	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 11 Q VST3 ID 62461299	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 11 Spectral VST3 ID 2118600194	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 11 Spectral Depth VST3 ID 462405181	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 11 Spectral Niddle VST3 ID 1739271642	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.

Parameter	Range / options	Default	Host status	Function
Band 11 Spectral Range VST3 ID 475212983	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 11 Spectral Sensitivity VST3 ID 1619788441	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 11 Type VST3 ID 1063896792	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 12 Attenuation VST3 ID 1638357581	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 12 Channel Mode VST3 ID 532054716	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 12 Dynamic VST3 ID 1008635586	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 12 Dynamic Attack VST3 ID 1194026347	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 12 Dynamic Range VST3 ID 1646939546	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 12 Dynamic Ratio VST3 ID 1646945384	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 12 Dynamic Release VST3 ID 126063908	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 12 Dynamic Threshold VST3 ID 1400732232	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 12 Enabled VST3 ID 1569241540	Off, On	Off	Automatable	Enables this EQ band.
Band 12 Frequency VST3 ID 1092101813	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 12 Gain VST3 ID 1092115388	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 12 Q VST3 ID 62462260	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 12 Spectral VST3 ID 1922086689	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 12 Spectral Depth VST3 ID 591487900	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 12 Spectral Niddle VST3 ID 1445868635	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 12 Spectral Range VST3 ID 604295702	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 12 Spectral Sensitivity VST3 ID 622716088	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 12 Type VST3 ID 1092525943	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 13 Attenuation VST3 ID 378377614	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 13 Channel Mode VST3 ID 26496091	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.

Parameter	Range / options	Default	Host status	Function
Band 13 Dynamic VST3 ID 1348664771	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 13 Dynamic Attack VST3 ID 1323109066	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 13 Dynamic Range VST3 ID 1997471835	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 13 Dynamic Ratio VST3 ID 1997477673	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 13 Dynamic Release VST3 ID 1980144549	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 13 Dynamic Threshold VST3 ID 760800393	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 13 Enabled VST3 ID 1909270725	Off, On	Off	Automatable	Enables this EQ band.
Band 13 Frequency VST3 ID 1120730964	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 13 Gain VST3 ID 1120744539	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 13 Q VST3 ID 62463221	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 13 Spectral VST3 ID 1725573184	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 13 Spectral Depth VST3 ID 720570619	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 13 Spectral Niddle VST3 ID 1152465628	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 13 Spectral Range VST3 ID 733378421	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 13 Spectral Sensitivity VST3 ID 1773127383	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 13 Type VST3 ID 1121155094	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 14 Attenuation VST3 ID 1265881295	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 14 Channel Mode VST3 ID 1668421114	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 14 Dynamic VST3 ID 1688693956	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 14 Dynamic Attack VST3 ID 1452191785	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 14 Dynamic Range VST3 ID 200520476	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 14 Dynamic Ratio VST3 ID 200526314	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 14 Dynamic Release VST3 ID 1686741542	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.

Parameter	Range / options	Default	Host status	Function
Band 14 Dynamic Threshold VST3 ID 120868554	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 14 Enabled VST3 ID 101816262	Off, On	Off	Automatable	Enables this EQ band.
Band 14 Frequency VST3 ID 1149360115	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 14 Gain VST3 ID 1149373690	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 14 Q VST3 ID 62464182	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 14 Spectral VST3 ID 1529059679	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 14 Spectral Depth VST3 ID 849653338	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 14 Spectral Niddle VST3 ID 859062621	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 14 Spectral Range VST3 ID 862461140	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 14 Spectral Sensitivity VST3 ID 776055030	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 14 Type VST3 ID 1149784245	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 15 Attenuation VST3 ID 5901328	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 15 Channel Mode VST3 ID 1162862489	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 15 Dynamic VST3 ID 2028723141	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 15 Dynamic Attack VST3 ID 1581274504	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 15 Dynamic Range VST3 ID 551052765	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 15 Dynamic Ratio VST3 ID 551058603	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 15 Dynamic Release VST3 ID 1393338535	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 15 Dynamic Threshold VST3 ID 1628420363	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 15 Enabled VST3 ID 441845447	Off, On	Off	Automatable	Enables this EQ band.
Band 15 Frequency VST3 ID 1177989266	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 15 Gain VST3 ID 1178002841	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 15 Q VST3 ID 62465143	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 15 Spectral VST3 ID 1332546174	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.

Parameter	Range / options	Default	Host status	Function
Band 15 Spectral Depth VST3 ID 978736057	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 15 Spectral Niddle VST3 ID 565659614	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 15 Spectral Range VST3 ID 991543859	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 15 Spectral Sensitivity VST3 ID 1926466325	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 15 Type VST3 ID 1178413396	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 16 Attenuation VST3 ID 893405009	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 16 Channel Mode VST3 ID 657303864	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 16 Dynamic VST3 ID 221268678	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 16 Dynamic Attack VST3 ID 1710357223	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 16 Dynamic Range VST3 ID 901585054	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 16 Dynamic Ratio VST3 ID 901590892	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 16 Dynamic Release VST3 ID 1099935528	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 16 Dynamic Threshold VST3 ID 988488524	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 16 Enabled VST3 ID 781874632	Off, On	Off	Automatable	Enables this EQ band.
Band 16 Frequency VST3 ID 1206618417	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 16 Gain VST3 ID 1206631992	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 16 Q VST3 ID 62466104	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 16 Spectral VST3 ID 1136032669	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 16 Spectral Depth VST3 ID 1107818776	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 16 Spectral Niddle VST3 ID 272256607	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 16 Spectral Range VST3 ID 1120626578	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 16 Spectral Sensitivity VST3 ID 929393972	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 16 Type VST3 ID 1207042547	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.

Parameter	Range / options	Default	Host status	Function
Band 17 Attenuation VST3 ID 1780908690	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 17 Channel Mode VST3 ID 151745239	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 17 Dynamic VST3 ID 561297863	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 17 Dynamic Attack VST3 ID 1839439942	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 17 Dynamic Range VST3 ID 1252117343	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 17 Dynamic Ratio VST3 ID 1252123181	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 17 Dynamic Release VST3 ID 806532521	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 17 Dynamic Threshold VST3 ID 348556685	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 17 Enabled VST3 ID 1121903817	Off, On	Off	Automatable	Enables this EQ band.
Band 17 Frequency VST3 ID 1235247568	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 17 Gain VST3 ID 1235261143	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 17 Q VST3 ID 62467065	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 17 Spectral VST3 ID 939519164	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 17 Spectral Depth VST3 ID 1236901495	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 17 Spectral Niddle VST3 ID 2126337248	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 17 Spectral Range VST3 ID 1249709297	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 17 Spectral Sensitivity VST3 ID 2079805267	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 17 Type VST3 ID 1235671698	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 18 Attenuation VST3 ID 520928723	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 18 Channel Mode VST3 ID 1793670262	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 18 Dynamic VST3 ID 901327048	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 18 Dynamic Attack VST3 ID 1968522661	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 18 Dynamic Range VST3 ID 1602649632	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.

Parameter	Range / options	Default	Host status	Function
Band 18 Dynamic Ratio VST3 ID 1602655470	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 18 Dynamic Release VST3 ID 513129514	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 18 Dynamic Threshold VST3 ID 1856108494	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 18 Enabled VST3 ID 1461933002	Off, On	Off	Automatable	Enables this EQ band.
Band 18 Frequency VST3 ID 1263876719	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 18 Gain VST3 ID 1263890294	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 18 Q VST3 ID 62468026	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 18 Spectral VST3 ID 743005659	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 18 Spectral Depth VST3 ID 1365984214	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 18 Spectral Niddle VST3 ID 1832934241	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 18 Spectral Range VST3 ID 1378792016	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 18 Spectral Sensitivity VST3 ID 1082732914	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 18 Type VST3 ID 1264300849	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 19 Attenuation VST3 ID 1408432404	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 19 Channel Mode VST3 ID 1288111637	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 19 Dynamic VST3 ID 1241356233	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 19 Dynamic Attack VST3 ID 2097605380	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 19 Dynamic Range VST3 ID 1953181921	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 19 Dynamic Ratio VST3 ID 1953187759	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 19 Dynamic Release VST3 ID 219726507	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 19 Dynamic Threshold VST3 ID 1216176655	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 19 Enabled VST3 ID 1801962187	Off, On	Off	Automatable	Enables this EQ band.
Band 19 Frequency VST3 ID 1292505870	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 19 Gain VST3 ID 1292519445	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.

Parameter	Range / options	Default	Host status	Function
Band 19 Q VST3 ID 62468987	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 19 Spectral VST3 ID 546492154	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 19 Spectral Depth VST3 ID 1495066933	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 19 Spectral Niddle VST3 ID 1539531234	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 19 Spectral Range VST3 ID 1507874735	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 19 Spectral Sensitivity VST3 ID 85660561	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 19 Type VST3 ID 1292930000	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 20 Attenuation VST3 ID 148452437	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 20 Channel Mode VST3 ID 782553012	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 20 Dynamic VST3 ID 1581385418	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 20 Dynamic Attack VST3 ID 79204451	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 20 Dynamic Range VST3 ID 156230562	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 20 Dynamic Ratio VST3 ID 156236400	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 20 Dynamic Release VST3 ID 2073807148	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 20 Dynamic Threshold VST3 ID 576244816	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 20 Enabled VST3 ID 2141991372	Off, On	Off	Automatable	Enables this EQ band.
Band 20 Frequency VST3 ID 1321135021	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 20 Gain VST3 ID 1321148596	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 20 Q VST3 ID 62469948	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 20 Spectral VST3 ID 349978649	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 20 Spectral Depth VST3 ID 1624149652	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 20 Spectral Niddle VST3 ID 1246128227	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 20 Spectral Range VST3 ID 1636957454	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.

Parameter	Range / options	Default	Host status	Function
Band 20 Spectral Sensitivity VST3 ID 1236071856	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 20 Type VST3 ID 1321559151	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 21 Attenuation VST3 ID 346180587	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 21 Channel Mode VST3 ID 397681502	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 21 Dynamic VST3 ID 472092896	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 21 Dynamic Attack VST3 ID 771540621	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 21 Dynamic Range VST3 ID 1425489976	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 21 Dynamic Ratio VST3 ID 1425495814	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 21 Dynamic Release VST3 ID 2061391938	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 21 Dynamic Threshold VST3 ID 1530129894	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 21 Enabled VST3 ID 1032698850	Off, On	Off	Automatable	Enables this EQ band.
Band 21 Frequency VST3 ID 1950976343	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 21 Gain VST3 ID 1950989918	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 21 Q VST3 ID 62491090	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 21 Spectral VST3 ID 321648835	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 21 Spectral Depth VST3 ID 169002174	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 21 Spectral Niddle VST3 ID 1233713017	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 21 Spectral Range VST3 ID 181809976	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 21 Spectral Sensitivity VST3 ID 775316570	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 21 Type VST3 ID 1951400473	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 22 Attenuation VST3 ID 1233684268	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 22 Channel Mode VST3 ID 2039606525	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 22 Dynamic VST3 ID 812122081	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.

Parameter	Range / options	Default	Host status	Function
Band 22 Dynamic Attack VST3 ID 900623340	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 22 Dynamic Range VST3 ID 1776022265	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 22 Dynamic Ratio VST3 ID 1776028103	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 22 Dynamic Release VST3 ID 1767988931	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 22 Dynamic Threshold VST3 ID 890198055	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 22 Enabled VST3 ID 1372728035	Off, On	Off	Automatable	Enables this EQ band.
Band 22 Frequency VST3 ID 1979605494	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 22 Gain VST3 ID 1979619069	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 22 Q VST3 ID 62492051	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 22 Spectral VST3 ID 125135330	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 22 Spectral Depth VST3 ID 298084893	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 22 Spectral Niddle VST3 ID 940310010	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 22 Spectral Range VST3 ID 310892695	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 22 Spectral Sensitivity VST3 ID 1925727865	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 22 Type VST3 ID 1980029624	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 23 Attenuation VST3 ID 2121187949	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 23 Channel Mode VST3 ID 1534047900	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 23 Dynamic VST3 ID 1152151266	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 23 Dynamic Attack VST3 ID 1029706059	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 23 Dynamic Range VST3 ID 2126554554	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 23 Dynamic Ratio VST3 ID 2126560392	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 23 Dynamic Release VST3 ID 1474585924	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 23 Dynamic Threshold VST3 ID 250266216	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.

Parameter	Range / options	Default	Host status	Function
Band 23 Enabled VST3 ID 1712757220	Off, On	Off	Automatable	Enables this EQ band.
Band 23 Frequency VST3 ID 2008234645	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 23 Gain VST3 ID 2008248220	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 23 Q VST3 ID 62493012	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 23 Spectral VST3 ID 2076105473	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 23 Spectral Depth VST3 ID 427167612	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.
Band 23 Spectral Niddle VST3 ID 646907003	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 23 Spectral Range VST3 ID 439975414	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 23 Spectral Sensitivity VST3 ID 928655512	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 23 Type VST3 ID 2008658775	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Band 24 Attenuation VST3 ID 861207982	-96 to -3	-96	Automatable	Sets attenuation used by the spectral or delta path.
Band 24 Channel Mode VST3 ID 1028489275	Stereo, Mid, Side	Stereo	Automatable	Chooses which stereo component or channel this band processes.
Band 24 Dynamic VST3 ID 1492180451	Off, On	Off	Automatable	Enables the level-dependent Dynamic EQ layer.
Band 24 Dynamic Attack VST3 ID 1158788778	0.1000000 to 200.0000000	15.0000000	Automatable	Sets how quickly Dynamic EQ reacts.
Band 24 Dynamic Range VST3 ID 329603195	-24.0000000 to 24.0000000	-6.0000000	Automatable	Limits Dynamic EQ boost or cut movement.
Band 24 Dynamic Ratio VST3 ID 329609033	1.0000000 to 20.0000000	2.0000000	Automatable	Sets the strength of level-dependent movement above threshold.
Band 24 Dynamic Release VST3 ID 1181182917	1.0000000 to 2000.0000000	150.0000000	Automatable	Sets how quickly Dynamic EQ returns.
Band 24 Dynamic Threshold VST3 ID 1757818025	-60.0000000 to 0.0000000	-24.0000000	Automatable	Sets the level where Dynamic EQ movement begins.
Band 24 Enabled VST3 ID 2052786405	Off, On	Off	Automatable	Enables this EQ band.
Band 24 Frequency VST3 ID 2036863796	20.0000000 to 20000.0000000	999.9999390	Automatable	Sets the band center, cutoff, or reference frequency.
Band 24 Gain VST3 ID 2036877371	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets static boost or cut for filter types that use gain.
Band 24 Q VST3 ID 62493973	0.1000000 to 30.0000000	0.9999999	Automatable	Sets bandwidth or transition sharpness.
Band 24 Spectral VST3 ID 1879591968	Off, On	Off	Automatable	Enables narrow STFT spectral processing for this band.
Band 24 Spectral Depth VST3 ID 556250331	0.0000000 to 24.0000000	24.0000000	Automatable	Sets the depth of spectral treatment.

Parameter	Range / options	Default	Host status	Function
Band 24 Spectral Niddle VST3 ID 353503996	0 to 100	0	Automatable	Controls the deployed spectral detector's focused/narrow behavior.
Band 24 Spectral Range VST3 ID 569058133	0.0500000 to 8.0000000	1.0000000	Automatable	Limits spectral movement or reduction.
Band 24 Spectral Sensitivity VST3 ID 2079066807	0.00 to 1.00	0.50	Automatable	Sets how readily narrow spectral components are detected.
Band 24 Type VST3 ID 2037287926	Bell, Low Shelf, High Shelf, Low Cut, High Cut, Notch, Band Pass, All Pass	Bell	Automatable	Selects the static filter shape.
Bypass VST3 ID 1652125811	Off, On	Off	Automatable; Bypass	Turns the complete plug-in processing path off or on through the host-visible bypass endpoint.
Delta Band VST3 ID 10318460	0 to 23	0	Automatable	Selects the band used for band-delta monitoring.
Delta Mode VST3 ID 10659306	Off, All bands, Selected band	Off	Automatable	Selects the diagnostic delta-monitoring mode.
Input Gain VST3 ID 1900926708	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets the level entering the processor and therefore changes downstream drive or detection.
Output Gain VST3 ID 1357703165	-24.0000000 to 24.0000000	0.0000000	Automatable	Sets or limits the final output level after the plug-in's main processing.
Program VST3 ID 1886548852	Init / Flat, Vocal Resonance Guard, Mix Bus Polish, Drum Punch & Bite, Master De-Harsh, M/S Clarity	Init / Flat	Automatable	Selects a factory program. Loading a program recalls a coordinated set of plug-in parameters.

Documentation basis

Prepared from the current public catalog, current local product brief and implementation notes where available, existing English manuals where available, and a direct scan of the installed VST3 host contract. Internal implementation details that are not user-facing are intentionally excluded; all user-facing features and host-visible controls are documented.