




AC DIGITAL CLAMP METER KEW SNAP 200

Compact in Size &

Simple in Operation



- Oval jaws shape facilitates the clamping of conductors in cramped areas as connection boxes and switchboards
- 040A/400A AC
- 0400V/600V AC, 400V/600V DC
- Ω/Continuity Beeper with Electronic Protection
- Designed to meet IEC 61010-1
- Sleep function to save battery
- Data hold function

AC A	40A/400A
	±2.0%rdg±6dgt [50/60Hz] (0~39.99A)(0~399.9A)
AC V	400V/600V (Auto-ranging) ±2.0%rdg±5dgt [50/60Hz] (0~399.9V)(150~599V)
DC V	400V/600V (Auto-ranging) ±1.5%rdg±5dgt (0~399.9V)(150~599V)
Ω	$400\Omega/4000\Omega$ (Auto-ranging) ±2.0%rdg±5dgt (0~399.9Ω)(150~3999Ω)
Continuity buzzer	Buzzer sounds at 50Ω±35Ω
Conductor Size	Approx . ϕ 30mm
Applicable Standards	IEC 61010-1 CAT. III 300V, CAT. II 600V Pollution Degree 2 IEC 61010-031, IEC 61010-2-032, IEC 61326-1
Power source	R03(1.5V)x2 *Continuous measuring time: approx. 200 hours (Auto sleep function: approx. 10 minutes)
Dimensions / Weight	184(L) x 68.6(W) x 38.5(D)mm / Approx. 190g (including batteries)
Accessories Included	Test leads, R03×2, Instruction manual

d 30

MAX AC 400A Resolution





600 V

40Ã

Please read the "Safety Warnings" in the instruction manual supplied with the instrument thoroughly and completely for correct use. Failure to follow the safety rules can cause fire, trouble, electrical shock, etc. Therefore, make sure to operate the instrument on a correct power supply and voltage rating marked on each instrument.

For inquires or orders:



KYORITSU ELECTRICAL INSTRUMENTS WORKS, LTD.

No.5-20, Nakane 2-chome, Meguro-ku, Tokyo, 152-0031 Japan Phone:81-3-3723-0131 Fax:81-3-3723-0152

E-mail:info@kew-ltd.co.jp Factory: Ehime, Japan

http://www.kew-ltd.co.jp



