



ANENG PN103 Clamp Digital Meter Multimeter
600A AC Current AC/DC Voltage Tester



Description

ANENG PN103 AC/DC Current Clamp Meter

6000 Counts True RMS Digital Multimeter 600A Clamp Meter

A. Feature:

- 1-1. This series of clamp meters can automatically recognize the measurement range of AC current from 0.2 to 600A.
- 1-2. Overload protection throughout the range.
- 1-3. Max. voltage between measurement terminal and ground:700V DC or 600V AC
- 1-4. Max.display value:6000 digit.
- 1-5. Overrange display: The highest position shows"OL";
- 1-6. Low voltage display:"Low voltage symbol "symbol appears;
- 1-7. Power: AAA 1.5V battery(not include);

B. Function:

Function	Range	Accuracy
AC/DC Current	60A/600A	±(2.5%+10)
DC voltage	600mV/6V/60V/600V	±(0.8%+5)
AC voltage	6V/60V/600V	±1.0%+5)
Resistance	600Ω/6kΩ/60kΩ/600kΩ/6MΩ/60MΩ	±(0.8%+3)
Capacitor	10nF/100nF/1uF/10uF/100uF/1mF/60mF	±(2.5%+20)
Temperature	(0~250)°C	-
Frequency	10Hz/100Hz/1kHz/20kHz	±(1%+5)
Diode:yes	NCV:yes	Line on/off:yes
date:yes	Auto:yes	

