

Sales Tracking (STS) SMS Format and Working Principle

For GDL Mobile (Smart Phone), here we are considering **keyword GDLS**

GDLS<space>MODEL_NAME<space>**IMEI1;IMEI2:0:LOC**Latitude:Longitude

Example: GDLS NOTEAIR 123456789098765;230987654123428:0:49.862850:18.147800

Note for SMS format:

1. The keyword **GDLS** shall be fixed.
2. Here in the example for location tracking, **Latitude =49.862850** and **Longitude =18.147800**

Server number will be For Grameenphone 16272, and for ROBI, AIRTEL, BANGLALINK, TELETALK will be 16303

Note: Please follow the below logic

1. SMS will be triggered directly from handset and send SMS to For Grameenphone 16272, and for ROBI, AIRTEL, BANGLALINK, TELETALK will be 16303
2. SMS will send from handset **after 2nd incoming call or after 4 hours from the turn on time with sim card.**
3. The application will stop after **one successful** sending of the SMS.
4. The STS application will check **SIM 1** first and then **SIM 2** to send the SMS.
5. No pop-up notification while sending SMS to 16272 for GrameenPhone, and 16303 for ROBI, AIRTEL, BANGLALINK, TELETALK from handset.
6. If the application of STS finds **SIM 1** and successfully send the SMS, the STS application will stop forever. But for any other reason, if the SMS failed to send from **SIM1**, it will find **SIM 2** to send the SMS. If **SIM 2** successfully send the SMS, the STS application will **stop forever**.
For any other reason, if SMS failed to send from **SIM 1 and SIM2**, then it will make **SIM 1** to retry again after **6 hours** to send the SMS. If this time, the SMS is successful, the STS application will **stop forever**. If failed to send from **SIM 1**, it will try from **SIM 2** again.
Application will try total **22 Times**. The process will try after **6 hours** to sends the SMS successfully to 16272 for GrameenPhone, and 16303 for ROBI, AIRTEL, BANGLALINK, TELETALK.
7. **A single** SMS will generate from every handset. **No multiple** SMS will generate from the handsets. After successfully SMS sent from the handset, STS application will **stop forever** the device taken flash or reset.
8. Please keep an Sales Tracker Status (STS) statistics feature so that it can be verified directly from the mobile whether an STS has been generated from the application or not, by dialing a **specific code**.

Operator	MCC	MNC	HNI	Server Code
Grameenphone	470	01	47001	16272
Robi Axiata	470	02	47002	16303
Airtel	470	07	47007	16303
Banglalink	470	03	47003	16303
Teletalk	470	04	47004	16303