Class 750

České dráhy

Reverser
Speedbrake lever

Forward
Engine only
Off
Engine (rev.)
Backward

Vigilance
Gear lever

2 Head reduced
LO White lamps
3 Head full
BTV Off
HI + rear red
0

Lights
AUTO BRK rotary

Controller
Left throttle

8 7 6 5 4 3 2 1 0

Sand
Left throttle button

Engine start
ENG 1

Brake valve BS2
Right throttle

Quick release
Release
Neutral
Cutout
Emergency

Horn
Right throttle button

Brake release
ENG 2

Train protection
Left aux

off ◀ ▶ on

Wiper
Mode switch

not assigned
Right aux

Independent BP1
Flap lever

Release
Full

Whistle
Round aux

Doors L / R
RUD TRIM
PARK BRK

PARK BRK

Reverser handle + BS2 key
flat = out · rotate up = in

● recommended starting position

Cab setup

- PARK BRK up: reverser handle in, BS2 key unlocked (the loco loads with both out and the valve in Cutout)
- Reverser to Engine only, ENG 1 up for about 8 s until the engine runs, then ENG 1 down
- Train protection on (left aux lit); it loads in Banking
- Lights to Head full
- Independent at Full; brake valve from Cutout to Neutral

Cleared to depart

- Check the signal; reverser to Forward
- Brake valve to Release (Quick release at the far end), independent to Release
- Controller away from you: 1 … 8 (it only moves with the reverser out of Off)
- Acknowledge vigilance with the gear lever
- Brake: controller back to 0, brake valve into the apply zone; Emergency nearest you



© TheJAG