

-
-
-
-
-

Chapter 4

Workshop Operations Maintenance



Engineer Master File Maintenance



1/WOM

Use this option to maintain the details of all engineers employed within the workshop.

Workshop Management uses the engineer details to:

- Link an engineer with a stock location, so you can generate inventory movements against that stock location when the engineer uses parts to effect a repair.
- Link an engineer with a region, for reporting purposes.
- Record an engineer's absence status, and optionally prevent Workshop Management assigning this engineer new jobs.
- Calculate the cost of an engineer's time on each service job.
- Distinguish between grades of engineer, who may cost different amounts.

Engineer Maintenance Selection Screen

-  Select the Engineer Master File option to display the Engineer Maintenance Selection Screen.

Use this screen to enter or select the engineer you want to define or maintain.

SS045	Demonstration Company CENTRAL BRANCH	USER BRERETM	22/11/93 12:29:40
Engineer Maintenance			
Engineer.....?..		<u>E0001</u>	
F3=Exit F4=Prompt			

Fields:

Engineer

To define a new engineer, enter an engineer code, using up to five alphanumeric characters.

To maintain an existing engineer, select a code.

-  Press **Enter** to display the Engineer Maintenance Screen.

Engineer Maintenance Screen



To display this screen, on the Engineer Maintenance Selection Screen, select or enter an engineer and press **Enter**.

Use this screen to enter the location and grade details for the selected engineer.

SS045	Z1 - Demonstration Company	USER GBJBATD0	12/12/97
	WORKSHOP BRANCH		14:12:06
Engineer Maintenance			
Engineer.....	1005	UPDATE	
Name.....	ASTRE TEST TECH		
Address Line 1	32 ACACIA BOULEVARD		
2	BEDDITCH		
3			
4			
5			
Telephone.....	01527 58865	Ext.	Radio Page Code...
Supply Stockroom...	EQ		
Engineer Stockroom...	01	TP.. 0	Team Code....?.. IML Team 1
Vehicle Reg.No.....		Absent Code...?..	
Manager's Code.....			
Grading Code....?..	WE Workshop Engineer		
Cost Per Hour.....	85.00	Region...?..	CI Central
Workshop Engineer....	0	(1=yes 0=no)	
Include Engineer in Automatic Call Assignment....	0		
Engineer Account...	AC001	000	
F3=Exit F4=Prompt F8=Update F11=Delete F12=Previous F14=Skills Matrix			

Fields:

Name

Enter the full name of the engineer.

Address Lines 1 to 5

Enter the engineer's address.

Geo Code

Enter up to 10 alphanumeric characters in the two fields, to identify the engineer's home location geocode.



Tip: The engineer's geocode is for information only. Workshop Management uses the engineer's team, with its link to a territory or patch, in engineer allocation, not the geocode.

Post Code

Enter the engineer's postcode, in a format that complies with the Post Office regulations.

Telephone

Enter a telephone number for the engineer.

Ext

Enter a telephone extension number for the engineer.

Radio Page Code

If the remote communications link is active, enter the engineer's designated terminal code.

Supply Stockroom

This field only displays if you include the DRP libraries in the Workshop Management library list.

Enter a supply stockroom. You must have set up the stockroom in Inventory Management (company profile) with item and stockroom details.

The stockroom is the source of spare parts for replenishing the engineer's stock location. It is the default supply stockroom for the engineer used in DRP parts orders originated during technical reporting.

Engineer Stockroom

Enter the engineer's stock location. You must have defined this stockroom in Inventory company profile and set up physical stocks.

Where you use DRP orders, set up an Accounts Receivable account with delivery code 001. In DRP maintenance, attach the account to the stock location as the sole customer for all Distribution orders to the location.

Technical reporting debits the parts used by the engineer from this stock location code.

TP

Enter one of the following:

0 - If the engineer is not a third party engineer

1 - If the engineer is a third party engineer.



Note: If you set this field to 1, you do not need to enter the Engineer and Supply stockrooms.

Team Code

Enter the team for the engineer. Workshop Management uses the teams in engineer allocation if you set the Assign By Territory field on, in Company Profile Maintenance.

Vehicle Reg No

Enter the registration number of the engineer's vehicle.

Absent Code

Enter a reason for the engineer to be absent.

If this field is anything other than blank, 0 or 1, automatic allocation ignores this engineer for calls.

If you create a non-job activity in the engineer's diary, and give it an absent code, that code appears here. Workshop Management does not allocate the engineer any work. You set up absent codes using parameter type ABSC in the Codes/Parameter File option.



Note: You must reset the field manually; Workshop Management does not remove the absent code.

Manager's Code

Enter the manager's code.

Grading Code

Select the grade of the engineer. You define the grades on the codes file using code type EGRD.

Cost Per Hour

Enter the hourly rate, in base currency, to charge to the job cost database, for work done and travel time expended by the engineer.

Region

Select the service region in which the engineer works. You define the regions on the codes file under code type REGN.

Workshop Engineer

Enter one of the following:

0 - To use either the contract or non-contract rate from the price list, depending on the job.

1 - To use the workshop rate from the labour rate price list when you charge for the engineer's time.

Include Engineer In Auto Call Assignment

Enter one of the following:

0 - To exclude the engineer from ACA.

1 - To include the engineer in automatic call assignment (ACA) for his team; make sure the absent code is blank.



Note: System parameter, model and job category settings may also limit ACA operation.

Engineer Account

Enter the account number and address for the engineer.



Note: You must set up the account in Accounts Receivable. Workshop Management uses the account number as the customer for non-job activities, which you set up for the engineer using the diary function.

Functions:

F14

Skills Matrix. Use this function to maintain the engineer skills matrix.

F16

Alternate Engineer Maintenance. Use this function to maintain alternative engineers. This function is only available if you set the Assign By Territory Or Alternative Engineer field to 0, on the Company Profile Maintenance Screen 1.



To save any changes made, select **F8=Update**.

Engineer Maintenance Skills Matrix (F14)



To display this screen, select **F14=Skills Matrix**, from the Engineer Maintenance Screen.

Use this screen to enter the models, groups or divisions on which the engineer has trained.

SS045	Demonstration Company	BRERETM	22/11/93
	CENTRAL BRANCH		12:30:03
Engineer Maintenance			
Engineer.....	E0001	JOHN SMITH	
Model	Division	Model Group	Model Subgroup Job Cat
_____	10	_____	_____
	Environmental	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
			+
F3=Exit F4=Prompt F8=Update F12=Previous F13=Fold/Truncate			

Fields:

Model

Enter the models the engineer can work on. If the engineer can work on all the models in the model sub-group, you can leave this field blank.

Division

Enter the division the engineer can work on. If you only enter a division, the engineer can work on all products within the division.

Model Group

Enter the model group the engineer can work on. If you only enter a model group, the engineer can work on all products within the model group.

Model Sub-Group

Enter the model sub-group the engineer can work on. If you only enter a model sub-group, the engineer can work on all products within the sub-group.

Job Cat

Enter the job the engineer can do. This restricts the selection of the engineer to the jobs defined within the job category.

If the engineer can do all jobs, leave this field blank.

Functions:

F13

Fold/Truncate. Use this function to toggle the display to show more or fewer details.



To save any changes, select **F8=Update**.

Alternative Engineer Maintenance Screen (F16)



To display this screen, on the Engineer Maintenance Screen, select **F16=Alternative Engineer Maintenance**.

Use this screen to enter all the engineers you can consider as alternatives to the selected engineer.



Note: You can only access this screen if you set the Assign By Territory Or Alternative Engineer field to 0, on the Company Profile Maintenance Screen 1.

Fields:

Opt

Enter 4 against an engineer to delete it from the list of alternative engineers.

Engineer

Enter the engineer you want to define as an alternative to the specified engineer. Press **Enter** to add the engineer. The engineer displays in the list near the top of the screen.

Functions:

F9

Next. Use this function to return to the Engineer Maintenance Selection Screen so you can select a different engineer.



To return to the Engineer Maintenance Screen, select **F12=Previous**.

Geocode/Territory Maintenance



2/WOM

Use this option to define the geographical territories for service operations, using full or partial geographical or postal codes.

A service territory is a geographical area, defined as a number of full or partial postcodes. Workshop Management uses it to assign an engineer team to a service job automatically. Workshop Management uses the customer geocode to establish the territory in which the installation falls, and then selects the most suitable engineer covering this territory.

A geocode cannot exist in more than one territory, but you can assign a territory to more than one team.

You must enter all the geocodes which fall within a territory. These can be full (district, area and road), or partial (district only, or district and area) geocodes. It depends on how precisely you need to define the territory and how far the format of the local postcode allows this definition.

Geocode/Territory Maintenance Selection Screen



To display this screen, select the Geocode/Territory option.

Use this screen to enter or select the territory you want to create or maintain.

SS064	Demonstration Company	BRERETM	22/11/93
	CENTRAL BRANCH		12:31:26
Geocode/Territory Maintenance			
Territory..?. ?__			
F3=Exit F4=Prompt			

Fields:

Territory

To define a new territory, enter a territory code, using up to three alphanumeric characters.

To maintain an existing territory, select a code.



To display the Geocode/Territory Maintenance Screen, press **Enter**.

Geocode/Territory Maintenance Screen

- To display this screen, on the Geocode/Territory Maintenance Selection Screen, select a territory, and press **Enter**.

Use this screen to define the geocodes that are in the selected area.

SS064

Demonstration Company
CENTRAL BRANCH

BRERETM

14/02/94
10:09:22

Geocode/Territory Maintenance

Territory.... T01

Territory 1

Geocode	Geocode	Geocode	Geocode
CT1			

F3=Exit F8=Update F12=Previous

Fields:

Territory Description

Enter a territory description.

Geocode

Enter the geographic code (usually the postcode) to include in this territory.

- Enter all the geocodes in this territory, and select **F8=Update** to save any changes.

Job Category Maintenance

1... **2...** 4/WOM

Use this option to define and maintain all your job categories.

A job category code defines the type of activity the engineer performed when repairing or maintaining the equipment, (service, fit part).

Together with the contract type, you use the job category as the basis for deciding if you charge for the task. You set up the details of whether to charge, and how much to charge, in the cover type/job category charge matrix.

Implications

You use job categories to log jobs and create planned maintenance schedules for contracts. The engineers also require job categories when they enter the technical reports.

Workshop Management uses the information associated with a job category:

- To determine the default values for nine frequently used job categories. You use this when logging calls.
- With contract type data, to make up the charge matrix, to determine if you charge for cost elements in a call. Cost elements are labour hours, mileage charges, travel hours, miscellaneous costs and parts used, by four, user defined types (major, minor, consumables and supply items).

Job Category Maintenance Selection Screen



To display this screen, select the Job Category Maintenance option.

Use this screen to select, or enter, a job category to maintain, or create.

Fields:

Job Category

Enter the job category you wish to set up or maintain. You can use up to three alphanumeric characters.



Enter a new or existing job category on the Job Category Maintenance Selection Screen, then press **Enter** to display the Job Category Maintenance Screen.

Job Category Maintenance Screen



To display this screen, enter a new or existing job category on the Job Category Maintenance Selection Screen and press **Enter**.

Use this screen to define the details for the selected job category.

SS031	Z1 - Demonstration Company	USER GBJBATDO	12/12/97
	WORKSHOP BRANCH		14:14:24
Job Category Maintenance UPDATE			
Job Category.....	INS	<u>Installation</u>	
Category Type.....	4	(1-Breakdown 2-Planned 3-Non Job 4-Warranty)	
Default category.....	2	(0 Not a default)	
		(1 Breakdown category default)	
		(2 Installation category default)	
		(3 Withdrawal category default)	
		(4 Return job category default)	
		(5 Repeat call default)	
		(6 Specialist call default)	
		(7 Return for Knowledge)	
		(8 Return for Other Reasons)	
		(9 Warranty Call)	
		(A Workshop category default) (B Workshop Warranty) (C Warranty Claim)	
		Include category in repeat call calculation.... 1 (0/1)	
		Include category in automatic call assignment.. 1 (0/1)	
		Average hours factor....	
F3=Exit F11=Delete F12=Previous			

Fields:

Description

Enter the description for the job category.

Category Type

Enter one of the following:

- 1 - Breakdown.
- 2 - Planned.
- 3 - Non-job.
- 4 - Warranty.

Default Category

Each category type should have a default job category, which Workshop Management retrieves automatically and displays on the call logging screen. You can only define one default job category for each type.

Enter a single character, in the range 1 to 9, or A, B or C, if this job category is the default for a particular type.

If it is not, enter 0.

Include Category In Repeat Call Calculation

Enter one of the following:

0 - To exclude the category from the repeat call calculation.

1 - To include the category in the repeat call calculation.

When you log a call, Workshop Management checks repeat calls. They depend on the number of days, or the copies or vends produced or both, since the last reported service call to the equipment.

You define the days and copies between calls on the volume segment, linked directly to a specific model.

Include Category In Automatic Call Assignment

Enter one of the following:

0 - To exclude calls of this job category from the automatic call assignment (ACA) of engineers to calls.

1 - To include calls of this job category in the ACA of engineers to calls.



Note: System Parameters File Maintenance settings, and settings for the model and engineer, also limit ACA operation.

Average Hours Factor

This field is for future development.



To update, press **Enter**, then select **F8=Update**.

Cover Type/Job Category Maintenance



5/WOM

Use this option to define and maintain a charge matrix for all job categories. The charge matrix specifies the invoicing rules relating to each combination of job category and cover type. It determines which elements are chargeable, whether overrides apply and which elements are not chargeable.

Concepts

You must set up a list of all the job categories allowed for each cover type (including *NO - no cover type). This makes sure you do not book the wrong type of work against a contract; and tells Workshop Management whether to charge the labour, travel parts or miscellaneous costs to the customer.

Implications

You must define the matrix of cover types and job categories before you can despatch an engineer to a call, or log technical reports. You can only enter the labour and travel hours, parts used and miscellaneous costs against job categories set up in a matrix with the contract type covering the piece of equipment on the technical report.



*Note: You must define a set of job categories allowed for non-contract work against the special cover type code *NO, to allow technical report entries for non-contract work.*

The matrix is also important for the job invoicing routines. Workshop Management processes each completed job line, and accesses the indicators for the appropriate cover type and job category combination, to decide whether to charge labour hours, miscellaneous costs and parts used to the customer.



Note: If a cover type/job category charge matrix does not exist when you log a job, a warning message displays on the job line details screen. You can still log the call, but you should correct the error condition before attempting to process the technical report.

Cover Type/Job Category Maintenance Selection Screen



To display this screen, select the Cover Type/Job Category option

Use this screen to select the Cover Type for which you want to define the matrix.

```
W0033          Z1 - Demonstration Company      USER GBJBANB4   17/02/98
                  CENTRAL WORKSHOP                               09:48:00
Cover Type/Job Category Maint.

Cover Type .....?..  █
Currency Code.....?..  _

Based on:-

Cover Type .....?..  _
Currency Code.....?..  _

F3=Exit F4=Prompt
```

Fields:

Cover Type

Enter a new or existing cover type.

Currency Code

Enter an existing currency.

Based On

To base a new matrix on an existing one, complete the following fields:

Based On Cover Type

Enter the existing contract type.

Based On Currency Code

Enter the existing currency code.



Note: If you are using a different currency, you need to revise all fixed charge overrides for labour and travel labour.



To display the Cover Type/Job Category Maintenance Detail Screen, press **Enter**.

Cover Type/Job Category Maintenance Detail Screen



To display this screen, enter the selection details and press **Enter** on the Cover Type/Job Category Selection Screen.

This screen lists all job categories linked to the cover type. Use the line of invoice fields above the list of job categories to enter the matrix information.



Tip: In the Job Category matrix, Workshop Management highlights invoice field values with a fixed charge attached.

```

W0033          Z1 - Demonstration Company          USER GBJBANB4      17/02/98
                  CENTRAL WORKSHOP                      09:48:37
Cover Type/Job Category Maint.

Cover Type ..... B01  S&R Adv: Basic cover
Currency Code..... GBP
Job Category.....?.. █
Invoice? Labour  Mileage  Travel  Misc.  Major      Minor      Consume  Supplies
(1/0)      -      -      -      -      -      -      -      -

Job Category.....      LBR  MLG  TRV  MSC  MAJ  MIN  CON  SUP
- ARR Arrival at door      1    1    1    1    1    1    1    1
- CAL calibration          0    0    0    1    1    0    0    1
- CSR Customer Service Request  1    1    1    1    1    0    0    1
- MIS Misuse              1    1    1    1    1    1    1    1
- PSV Planned service visit  0    0    0    1    1    0    0    1
- RCC Repeat call - chargeable  1    1    1    1    1    0    0    1
- RCN Repeat call - no charge  0    0    0    0    1    0    0    1
- WTY Warranty call        0    0    0    0    0    0    0    1

1=Select  4=Delete
F3=Exit   F4=Prompt  F8=Update  F12=Previous
F14=Pos.Cur. Changing Overrides  F16=Changing Overrides
  
```

Fields:



Note: To enter a charge matrix, enter a job category in the Job Category field, and enter 1 in the appropriate invoice fields.



Note: To amend an existing line, enter 1 against the line in the job category list. The category displays in the Job Category field, and all the invoice fields display in the input fields so you can amend them.

Job Category

Enter a job category.



Warning: Do not enter a job category and immediately select an existing job category using option 1. This results in unnecessary record-locking of the first job category.



Note: You set up item types to Invoice in System Parameters Maintenance; you must classify a service part in the field Product Type on Item Master.



Note: If you have made a copy, based on another currency, you must convert any override charges into the new currency.

Labour

Enter one of the following:

- 0 - To not invoice for the labour hours; no fixed charge applies.
- 1 - To invoice the labour hours. You can set up fixed charge overrides using **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

Mileage

Enter one of the following:

- 0 - To not charge for distance travelled.
- 1 - To charge for miles or kilometres.

This displays on the technical report screen, where you can change it.

Travel

Enter one of the following:

- 0 - To not invoice for travel hours, no fixed charge applies.
- 1 - To invoice for travel hours. You can set up fixed charge overrides using **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

This displays on the technical report screen, where you can change it.

Misc

Enter one of the following:

- 0 - To not invoice for miscellaneous charges.
- 1 - To invoice miscellaneous charges.

This displays on the technical report screen, where you can change it.

Major

Enter one of the following:

- 0 - To not charge for the parts, unless you enter an override charge % in Technical Reporting - Parts Used.
- 1 - To invoice for major parts. To specify which parts to charge for, use **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

Minor

Enter one of the following:

- 0 - To not charge for the parts used, unless you enter an override charge % in Technical Reporting - Parts Used.

1 - To invoice for minor parts. To specify which parts to charge for, use **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

Consume

Enter one of the following:

0 - To not invoice for consumable parts used, unless you enter an override charge % in Technical Reporting - Parts Used.

1 - To invoice for a consumable. To specify which parts to charge for, use **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

Supplies

Enter one of the following:

0 - To not invoice for the supply parts used, unless you enter an override charge % in Technical Reporting - Parts Used.

1 - To invoice for supply parts. To specify which parts to charge for, use **F14=Pos.Cur. Charging Overrides** or **F16=Charging Overrides**.

Unnamed (Option)

Enter one of the following:

1 - To select a job category for maintenance. The job category charge details display for amendment in the invoice fields.

4 - To delete a category from this matrix.

Functions:

F14

Pos. Cur. Charging Overrides. Use this function to display the override entry window for the highlighted item.

F16

Charging Overrides. Use this function to display the override entry window for labour, travel, major, minor, consume and supplies, one after the other.



To save the information, and return to the selection screen, select **F8=Update**.

Charging Overrides Window (F14/F16)



To display a charging overrides window, select
F14=Pos.Cur. Charging Overrides or
F16=Charging Overrides.

Use this window to enter the fixed charges for the charging overrides.



Note: The window displayed varies depending on the charge you are entering. Only a selection of the documented fields display.

```

SS033          Z1 - GB Demonstration Company      USER GBJBATD0      24/09/97
               "BRUM" TRAINING & SERVICE BRANCH    15:26:04
Cover Type/Job Category Maint. (Detail)

Cover Type ..... *NO No user contract
Currency Code..... GBP
Job Category..... CAL Calibration
Invoice? Labour  Mileage  Travel  Misc.  Major  Minor  Consume  Supplies
(1/0)           1       1       1       1       1       1       1       1

Job Category..... LBR MLG TRV MSC MAJ MIN CON SUP
- AAI Annual Ammunition Inspection 1 1 1 0 0
- CAL Calibration
- CID Customer Inflicted Damage
- CSR Customer Service Request
- FOC Free-Of-Charge Call
- INS Installation
- PCV Pending Contract Visit
- RCC Repeat call - chargeable
- RCN Repeat Call - No Charge
- RTN Return Call : Standard

F12=Previous F14=Pos.Cur. Chrgi F7=Accept F12=Previous

21-40  SR  MW  KS  CL  IM  DM  II  EDN400A  KB  PKH317S1
  
```

LABOUR HOURS FIXED CHARGES

The first 'n' Hours for a Min. Charge Eff.Date
 1:00 100.00 1/05/96

0:00

Fields:

The First 'N' Hours

Enter the number of hours this charge applies for.

For A Min Charge

Enter the value to charge.

Eff Date

Enter the date to make this charge from.

Select Parts To Include

Enter one of the following:

0 - To not display a list of parts, for you to select the parts to override.

1 - To display a list of parts, for you to select the parts to override.

Select Parts To Exclude

Enter one of the following:

0 - To not display a list of parts.

1 - To display a list of parts for you to select the parts to exclude from the override.

Select All Parts

Enter one of the following:

0 - If you do not want to select all parts for the override.

1 - To select all parts for the override.



Enter the override and select **F7=Accept** to update. If you accessed this screen using **F16=Charging Overrides**, the next override displays, otherwise the Cover Type/Job Category Maintenance Detail Screen displays.

District File Maintenance



7/WOM

Use this option to authorise groups of teams to a user, for the purpose of work control.

Whereas most users can log a call, it is only those authorised to control specific teams who can progress calls through Engineer Work Allocation.

District Maintenance Selection Screen



To display this screen, select the District File Maintenance option.

Use this screen to enter, or select, the district you want to create, or maintain.

SS057	Demonstration Company	USER BRERETM	22/11/93
	CENTRAL BRANCH		12:33:09
District Maintenance			
District Number....?.. <u>D1</u>			
F3=Exit F4=Prompt			

Fields:

District Number

To create a new district, enter a code using up to two alphanumeric characters.

To maintain a district, select a district.



To display the District File Maintenance Detail Screen, press **Enter**.

District File Maintenance Detail Screen

 To display this screen, enter a district on the District File Maintenance Selection Screen, and press **Enter**.

Use this screen to enter the team and user details for the selected district.

SS057

Demonstration Company
CENTRAL BRANCH

USER BRERETM

22/11/93
12:33:13

District Maintenance

UPDATE

District Number..... D1

District 1

User ID.....

Team Number.....?

X	Team	Description	User Id
-	TM1	Team 1	BRERETM
-	TM1	Team 1	QSECOFR

4-Delete

F3=Exit

F4=Prompt

F8=Update

F12=Previous

Fields:

Untitled

Enter a district description of up to 36 alphanumeric characters.

User ID

Enter a user ID of up to 10 alphanumeric characters.

Team Number

To give the user access to a team's work allocation details, enter the team.

 *Note: If you do not enter a team, the user can log calls for that team, but cannot progress them.*

X

Enter 4 to delete the team.

 To save the information, select **F8=Update**.

Team File Maintenance



8/WOM

Use this option to assign the service territories an engineer team covers. You assign the engineer team by field service group. This is by the skills required for servicing equipment within the specified division, model group, model sub-group, or model.

Concepts

A team is a group of engineers who cover the same geographical area and product set. This provides a pool of labour to meet the call target time, so you can automatically assign an available member of the team to a task.

If you want a team to carry out service jobs in more than one territory, then assign it to a list of the appropriate territories. A team can cover any combination of all types of work in a territory, or only specific model groups or sub-groups or divisions, according to the field service groups defined.

Team Maintenance Selection Screen



To display this screen, select the Team Maintenance option.

Use this screen to define, or select, the team number you want to create or maintain.

SS058	Demonstration Company CENTRAL BRANCH	USER BRERETM	22/11/93 12:35:14
Team Maintenance			
Team Number.....?... <u>TM1</u>			
F3=Exit F4=Prompt			

Fields:

Team Number

To create a new team, enter a new team number using up to three alphanumeric characters.

To maintain a team, enter an existing team number.



To display the Team Maintenance Detail Screen, press **Enter**.

Team Maintenance Detail Screen



To display the Team Maintenance Detail Screen, on the Team Maintenance Selection Screen, enter a team and press **Enter**.

Use this screen to define the field service group, territories and job categories covered by each team.

SS058	Demonstration Company CENTRAL BRANCH	BRERETM	22/11/93 12:35:16
Team Maintenance		UPDATE	
Team Number.....	TM1 Team 1		
Field Service Group ...?..	—		
Territory.....?	—		
Job Category.....?..	—		
X Field Service Group	Territory	Job Category	
— G1 Group 1	T01 Territory 1	** ALL CATEGORIES **	
4-Delete			
F3=Exit F4=Prompt F8=Update F11=Delete F12=Previous			

Fields:

Untitled

Enter a team description of up to 30 alphanumeric characters.

Field Service Group

Enter a field service group.

Territory

Enter a territory.



Note: You can only allocate a field service group and territory code combination to one team.

Job Category

Enter a job category. To set up all job categories for the selected combination of field service group and territory, leave this field blank.

X

Enter 4 to delete a line.



Select **F8=Update** to update.

Field Service Group Maintenance



9/WOM

A field service group defines the service division and the model families for which a team of engineers is responsible.

Implications

Workshop Management uses the engineer team and territory definitions when it tries to automatically assign an engineer from a team to a service job.

The customer geocode establishes the territory in which the installation falls; Workshop Management then selects the most lightly loaded engineer covering this territory and field service group.

Field Service Group Maintenance Selection Screen



To display this screen, select the Field Service Group Maintenance option.

Use this screen to enter, or select, the Field Service Group you want to create, or maintain.

SS059	Demonstration Company CENTRAL BRANCH	USER BRERETM	22/11/93 12:35:46
Field Service Group Maint.			
Field Service Group...?... <u>G1</u>			
F3=Exit F4=Prompt			

Fields:

Field Service Group

To define a new field service group, enter a code using two alphanumeric characters.

To maintain a field service group, select a code.



To display the Field Service Group Maintenance Screen, enter a field service group and press **Enter**.

Field Service Group Maintenance Screen



To display this screen, on the Field Service Group Maintenance Selection Screen, enter a field service group and press **Enter**.

Use this screen to define the models, divisions and model groups or sub-groups this Field Service Engineer can maintain.

SS059	Demonstration Company CENTRAL BRANCH	BRERETM	22/11/93 12:35:49
Field Service Group Maint.		UPDATE	
Field Service Group..... G1 <u>Group 1</u>			
Model	Division	Model Group	Model Subgroup
_____	10	_____	_____
_____	Environmental	_____	_____
_____	—	_____	_____
_____	—	_____	_____
_____	—	_____	_____
_____	—	_____	_____
_____	—	_____	_____
_____	—	_____	_____

F3=Exit F4=Prompt F8=Update F11=Delete F12=Previous F13=Fold/Truncate

Fields:

Untitled

Enter the field service group description, using up to 36 alphanumeric characters.

Model

Enter the models this field service group can maintain.



Tip: If the field service group can service all the models in the model sub-group, you do not need to enter the models.



Note: If you enter a model code, you must also enter a division code, but you do not need to enter a model group or model sub-group.

Division

Enter the product divisions covered by the field service group.



Tip: If you do not enter a model, model group or model sub-group, the field service group can service all products within the division.

Model Group

Enter the specific model groups covered by the field service group. Leave this field blank if the field service group covers all model groups in the division.



Tip: If you do not enter a model or model sub-group, the field service group can service all products within the model group.

Model Sub-Group

Enter the specific model sub-groups within a model group, covered by the field service group. Leave this field blank if the field service group covers all model sub-groups in the model group.



Tip: If you do not enter a model, this means the field service group can service all products within the model sub-group.

Functions:

F13

Fold/Truncate. Use this function to display more details.



Select **F8=Update** to save the information and return to the Field Service Group Maintenance Selection Screen.

3-D Matrix Maintenance



10/WOM

Workshop Management uses the 3-D matrix to reduce the response time, retrieved from the contract header, line, or type, by a percentage.

The percentage depends on:

- The importance of the customer placing the call.
- The volume segment set at model level.
- The seriousness of the problem, for example: is the machine up and working, but in need of attention, or is it down and completely out of action.

Description

When you select the 3-D Matrix option, you display a list of the volume segments with a percentage reduction in response time by customer importance, and whether the machine is up (working, but in need of attention), or down (out of action).

3-D Matrix Maintenance Screen



To display the 3-D Matrix Maintenance Screen, select the 3-D Matrix Maintenance option.

Use this screen to enter the percentage change on specified priority machines, for all volume segment codes.



Tip: Workshop Management sets the target time by applying the percentage reduction for the volume segment (by model) and the customer priority (by site's additional service details) to the response hours, according to the value in Machine Up And Running, on the Call Logging Job Line Detail Screen.

W0055		Z1 - GB Demonstration Company				USER GBJBANB1		23/04/98	
		CENTRAL WORKSHOP						14:29:52	
3-D Matrix Maintenance									
		PRIORITY 1		PRIORITY 2		PRIORITY 3		PRIORITY 4	
		MACHINE		MACHINE		MACHINE		MACHINE	
Vol	Seg	UP	DOWN	UP	DOWN	UP	DOWN	UP	DOWN
10		—	—	—	—	—	20	25	33
20		—	—	—	—	20	30	40	50
21		—	—	—	—	—	—	—	—
30		—	—	—	—	50	66	75	100
F3=Exit F8=Update									

Fields:

Machine Up: Priorities 1 to 4

Enter the percentage reduction to make to the response time for this volume segment. You must enter a whole number between 0 and 100.

Machine Down: Priorities 1 to 4

Enter the percentage reduction to make to the response time for this volume segment. You must enter a whole number between 0 and 100.

Calculating the response time

The Response Time hierarchy looks for the response hours in the following order:

1. The special serial numbers file, but does not apply the 3-D matrix reduction to this figure.
2. Contract line.

3. Contract header.
4. Contract type (incl *NO).
5. Default branch response time, set on the escalation control file.

Workshop Management uses the first response time that it finds and applies the 3-D matrix reduction to them all, except 1, to establish the call response.

Call target time = (Call received date and time + Call response)



To save any changes, select **F8=Update**.

Special Serial Numbers Maintenance



11/WOM

Use this option to set up an actual response time, in hours and minutes, for a specified item of equipment. Workshop Management normally uses this as an exception, to provide a short-term, special service to an item of equipment.



Tip: The response time you enter here is at the top of the response times hierarchy, and so overrides any model, contract or other response times set up elsewhere.

Special Serial Numbers Selection Screen



To display this screen, select the Special Serial Numbers option.

Use this screen to select the serial number and model you want to enter a specific response time for.

```
SS054          Z1 - Demonstration Company      USER GBJBATD0  12/12/97
                  WORKSHOP BRANCH                               14:32:20

Special Serial Number Maint.

Serial Number..... █ Model.....?...

F3=Exit  F4=Prompt  F6=List of Serial Numbers
```

Fields:

Serial Number

Enter the serial number to maintain.

Model

Enter the model to maintain.



Tip: Leave the serial number field blank to display a screen showing all the serial numbers for this model. Select the serial number you require by entering 1 alongside it.

Functions:

F6

List of Serial Numbers. Use this function to display a list of the serial numbers for which you have entered a response time.



Enter a serial number and model, then press **Enter** to display the Special Serial Numbers Maintenance Screen.

Special Serial Numbers Maintenance Screen



To display this screen, select a serial number and model combination, then press **Enter**.

Use this screen to enter the response time for the selected serial number and model.

SS054	Demonstration Company CENTRAL BRANCH	USER BRERETM	14/01/94 16:42:20
-------	---	--------------	----------------------

Special Serial Numbers Maint.	
Serial Number.....	22581039
Account Number.....	C03 / 001
Model.....	WA10
	Jones & Crossland (Northern) Ltd
Response time	<u>4:00</u>

F3=Exit	F8=Update	F12=Previous
---------	-----------	--------------

Fields:

Response Time

Enter the response time, hhh:mm, to apply to the model and serial number.

This response time takes priority when calculating the target time for a call to this machine.

The Response Time hierarchy looks for the response hours in:

1. Special serial number, then:
2. Contract line, then:
3. Contract header, then:
4. Contract type (incl *NO), then:
5. Default branch response time, set on the escalation control file.

Workshop Management goes through each in turn, and takes the first that it finds. Workshop Management applies the 3-D matrix reduction, to all but the special serial number response time, to establish the call response.



Select **F8=Update** to save any changes.

Condition Code Maintenance



12/WOM

Use this function to define condition and symptom relationships. These apply to the equipment and you can enter them when you create a job and when you complete a technical report.



Tip: You enter the condition and symptoms themselves on the Workshop Codes file.



Note: You can enter up to three symptoms for each condition. However if you need to enter more symptoms, you can enter the same condition and enter three more symptoms.

Workshop Management holds the first two levels of symptom codes on the codes file under parameter type SYM#, where # is either 1 or 2. Workshop Management holds the third level of symptom code on the symptom file (SSP96).



Tip: You can also access this function by selecting **F14=Condition Maint.** on the Model Group Maintenance Details Screen.

Condition/Symptom Code Maintenance Selection Screen



To display this screen, select the Condition Code option.

Use this screen to select the model group and division for which you want to maintain symptoms and conditions relationships.

W0096	Z1 - Demonstration Company	User: GBJBATD0	12/12/97
	WORKSHOP BRANCH		14:33:04
Condition/Symptom code maintenance			
Division.....?..: █			
Model group.....?..: ____			
F3=Exit F4=Prompt			

Fields:

Division

Select the division.

Model Group

Select the model group.



Enter a division and model group then press **Enter** to display the Condition/Symptom Code Maintenance Screen.

Condition/Symptom Code Maintenance Screen



To display this screen, on the Condition/Symptom Code Maintenance Selection Screen, select a division and model group and press **Enter**.

Use this screen to maintain the relationships between conditions and symptoms.

```

W0096          Z1 - Demonstration Company      User GBJBATD0  12/12/97
                WORKSHOP BRANCH                14:33:20
Condition/Symptom code maintenance

Division.....: 10      Environmental Monitoring
Model group.....: 100    Analysers
Condition Code....?: █

Symptom Code 1....?: _
Symptom Code 2....?: _
Symptom Code 3....?: _
Default (0/1).....: 0

  n  Cond Description      Symptom 1      Symptom 2      Symptom 3      Def
  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -  -
  -  A  Code A            1 Symptom Code 1 Code 1      1 Code 1      1
  -  A  Code A            1 Symptom Code 2 Code 2      2 Code 2      0
  -  A  Code A            3 Code 3          3 Code 3      3 Code 3      0
  -  A  Code A            4 Code 4          4 Code 4      4 Code 4      0 +

1=Select    4=Delete

F3=Exit    F4=Prompt    F8=Update    F12=Previous
  
```

Fields:

Condition Code

Select the condition you want to enter symptoms for.

Symptom Code 1 and 2

Select the symptoms for this condition. Workshop Management holds these symptoms in the codes file under parameter types SYM1 and SYM2

Symptom Code 3

Select the third symptom for this condition, and enter a description. Workshop Management holds this symptom in the symptom code file (SSP96).



Note: You can enter up to three symptoms, on each row, for each condition. However if you need to enter more symptoms, you can enter the same condition and enter three more symptoms. This displays on another row.

Default

Enter one of the following:

0 - If this is not the default condition code for this model.

1 - To specify that this is the default condition code for this model.



Tip: To change the default relationship, you must set the old default to 0 before you set the new default to 1.



Tip: To save the new condition and symptoms relationship, press **Enter**. This then displays in the bottom half of the screen.

N

Enter one of the following:

1 - To select the condition to maintain.

4 - To delete the condition and symptoms relationship.



To save all the changes and return to the Condition/Symptom Code Maintenance Selection Screen, select **F8=Update**.

Defect Code Maintenance



13/WOM

You use this function to define defect and repair relationships. These apply to the parts the engineer fits to equipment during a repair. You enter them when you complete a technical report to show the condition of the part removed.



Tip: You enter the defects and repair codes themselves on the Workshop Codes file.



Note: You can enter more than one repair code for each defect.

Workshop Management holds the defects in the codes file under parameter type DEFC, and the repair codes in the codes file under parameter type REPC.

Defect Code Maintenance Selection Screen



To display this screen, select the Defect Code option.

Use this screen to select the defect code for which you want to enter the associated repair codes.

Fields:

Defect Code

Select the defect code for which you want to enter the associated repair codes.



Select the defect code and press **Enter** to display the Defect Code Maintenance Screen.

Defect Code Maintenance Screen



To display this screen, on the Defect Code Maintenance Selection Screen, select the defect code and press **Enter**.

Use this screen to maintain the defect and repair code relationships.

```

W0097          Z1 - Demonstration Company      User GBJBATD0  12/12/97
                WORKSHOP BRANCH                14:35:53

Defect Code Maintenance

Defect Code.....: A    Air-pipe split

Repair Code.....?: 
Default (0/1).....: 0
Add/Replace (0/1)....: 0

  n  Repair code  Description                Dft  Add/Replace
  -  -  -  -  -
  -   A      test8                        1    0
  -   B    Both Speakers                  0    1
  -   C      Clean                        0    0
  -   I    R/H Speaker                    0    0
  -   L    L/H Speaker                    0    0
  -   R      Replace                      0    0
  -   1    Use sealing tape                0    1
  -   2    Replace with new                0    1
  -   3    Fit a spare part                0    1
  -   4    Can't touch this                0    1    +

1=Select  4=Delete
F3=Exit   F4=Prompt  F8=Update  F12=Previous
  
```

Fields:

Repair Code

Select the repair code to associate with this defect code.

Default

Enter one of the following:

0 - If this is not the default repair code for this defect.

1 - To specify that this is the default repair code for this defect.



Tip: You can only have one repair code with the default set to 1. Therefore if you want to change the default, you must set the old default to 0 before you can set the new default to 1.

Add/Replace

Enter one of the following:

0 - If you do not need to add or replace a part for this repair. The part is not flagged for payment on a Warranty Claim, and therefore does not appear on a credit note.

1 - If you have to either add or replace a part for this repair.



Tip: To save the new repair code relationship,

press **Enter**. This then displays in the bottom half of the screen.

N

Enter one of the following:

1 - To select the repair code relationship to maintain.

4 - To delete the repair code relationship.



To save all the changes and return to the Defect Code Maintenance Selection Screen, select **F8=Update**.

Engineer Master File Enquiry



21/WOM

Use this enquiry to display the details of a specified engineer.

Engineer Enquiry Selection Screen



To display this screen, select the Engineer File Enquiry option.

Use this screen to select the engineer for whom you want to display the details.

Fields:

Engineer

Select an engineer.



Select an engineer and press **Enter** to display the Engineer Enquiry Detail Screen.

Engineer Enquiry Detail Screen

-  To display this screen, on the Engineer Enquiry Selection Screen, select an engineer and press **Enter**.

```
SS545          61 - 61 - Demonstration Company  USER SSV3  11/12/95
                  CENTRAL BRANCH                      14:47:41

Engineer Enquiry

Engineer..... E0001
Name..... ARCHIE ABLETT
Address Line 1 32 ACACIA BOULEVARD
                2 GREENLANDS
                3 REDDITCH
                4 WORCS
                5
Telephone..... 01527 500665   Ext.      Radio Page Code...
Supply Stockroom.
Stock Location... 01          Team Code..... TM1   Team 1
Vehicle Reg.No...           Absent Code.....
Manager's Code...
Grading Code..... FE   Field engineer
Cost Per Hour.... 25.00000   Region..... CT   Central
Workshop Engineer..... 0   (1=yes 0=no)
Include Engineer in automatic call assignment..... 1
Engineer Account. EAC01   000

F3=Exit  F12=Previous  F14=Skills Matrix

07-24  SF  MK  KS  IM  II  KENB20A  PET113S1
```

This screen displays for the selected engineer:

- Name and address.
- Stock location and supply details.
- Team and area information.
- Manager.
- Grade and cost.
- Absent reason.
- Whether you include the engineer in automatic call assignment.

Functions:

F14

Skills matrix. Use this function to display the skills matrix for the selected engineer.

F16

Alternative engineer. Use this function to display any alternative engineers defined for this engineer. This function only displays if you have set the Assign By Territory Or Alternative Engineer field to 0, on Company Profiles Maintenance Screen 1.

-  Select **F3=Exit** to leave the enquiry.

Engineer Enquiry Skills Matrix Screen (F14)



Select **F14=Skills Matrix** on the Engineer Detail Screen, to display the skills matrix.

SS545	Demonstration Company	BRERETM	25/11/93
	CENTRAL BRANCH		14:49:19
Engineer Enquiry			
Engineer.....	E0001	JOHN SMITH	
Model	Division	Model Group	Model Subgroup Job Cat
	10	100	
	Environmental	Analysers	
			+
F3=Exit F12=Previous F13=Fold/Truncate			

This screen displays the models, divisions, model group and model sub-group this engineer can maintain. It also displays which type of job the engineer can carry out on each category.

Functions:

F13

Fold/Truncate. Use this function to toggle the display between showing just the codes and the full descriptions.



Select **F3=Exit** to leave the enquiry.

Geocode/Territory Enquiry



22/WOM

Use this enquiry to display the geographical territories defined for service operations.

Description

You define geographical territories by grouping together one or more geographical codes (usually postcodes).

Geocode/Territory Enquiry Selection Screen



To display this screen, select the
Geocode/Territory Enquiry option.

Use this screen to select the territory, for which you want to display the details.

Fields:

Territory code

Select a territory.



Select a territory and press **Enter** to display the
Geocode/Territory Enquiry Detail Screen.

Geocode/Territory Enquiry Detail Screen



To display this screen, on the Geocode/Territory Enquiry Selection Screen, select a territory code and press **Enter**.

```

SS564                Demonstration Company          BRERETM          25/11/93
                     CENTRAL BRANCH                14:50:38

Geocode/Territory Enquiry

Territory..... T01 Territory 1

    Geocode          Geocode          Geocode          Geocode
    CT1

F3=Exit  F12=Previous

```

This screen shows the geocodes included within the selected territory.



Select **F3=Exit** to return to the menu.

Job Category Enquiry



24/WOM

Use this enquiry to display job category codes and associated data.

Workshop Management uses job category codes to define different types of service work to undertake; for example, in job maintenance, and scheduled service visit maintenance.

The technical reporting module also uses job categories to identify how to cost or charge the work undertaken.

Description

To access a job category record for enquiry, select a category code.

Job Category Enquiry Selection Screen



To display this screen, select the Job Category Enquiry option.

Fields:

Job Category

Select a job category.



Select a job category and press **Enter** to display the Job Category Enquiry Detail Screen.

Job Category Enquiry Detail Screen



To display this screen, on the Job Category Enquiry Selection Screen, select a job category and press **Enter**.

```
SS531          Z1 - Demonstration Company      USER GBJBATD0  12/12/97
                  WORKSHOP BRANCH                14:40:04

Job Category Enquiry

Job Category..... INS  Installation

Category type.....: 4      (1-Breakdown 2-Planned 3-Non Job 4-Warranty)
Default category.....: 2      (0 Not a default)
                              (1 Breakdown category default)
                              (2 Installation category default)
                              (3 Withdrawal category default)
                              (4 Return job category default)
                              (5 Repeat call default)
                              (6 Specialist call default)
                              (7 Return on knowledge)
                              (8 Return for other reasons)
                              (9 Warranty Call)
(A Workshop category default) (B Workshop Warranty) (C Warranty Claim)
Include category in repeat call calculation..... 1
Include category in automatic call assignment... 1
Average hours factor

F3=Exit  F12=Previous
```

This screen displays, for the selected job category, the category type, default category, and whether to include the category in call calculation and automatic call assignment.



Select **F3=Exit** to return to the menu.

Cover Type/Job Category Enquiry



25/WOM

Use this enquiry to display the job categories allowed for a cover type within a currency. It also displays the invoicing rules relating to each combination.



Note: Workshop Management uses the combination of Cover Type and Job Category, when pricing completed jobs, to determine whether to invoice for Hours or Parts or Miscellaneous Charges.

Cover Type/Job Category Enquiry Screen



To display this screen, on the Cover Type/Job Category Enquiry Selection Screen, select a cover type and currency and press **Enter**.

This screen displays which element is chargeable for each job on the cover type.

```

W0533          Z1 - UK Demonstration Company      USER GBJBANB4      17/02/98
                  CENTRAL WORKSHOP                  09:52:04
Cover Type/Job Category Enq'y

Cover Type..... B01   S&R Adv: Basic cover
Currency Code..... GBP
Job Category.....
Invoice? Labour  Mileage  Travel  Misc.  Major    Minor    Consume  Supplies
(1/0)

Job Category.....      LBR  MLG  TRV  MSC  MAJ    MIN    CON    SUP
■ ARR Arrival at door      1    1    1    1    1    1    1    1
- CAL calibration          0    0    0    1    1    0    0    1
- CSR Customer Service Request  1    1    1    1    1    0    0    1
- MIS Misuse              1    1    1    1    1    1    1    1
- PSV Planned service visit    0    0    0    1    1    0    0    1
- RCC Repeat call - chargeable  1    1    1    1    1    0    0    1
- RCN Repeat call - no charge    0    0    0    0    1    0    0    1
- WTY Warranty call          0    0    0    0    0    0    0    1

1=Select
F3=Exit  F12=Previous
  
```

Fields:

(Untitled)

Selection. Enter 1 alongside a Job Category. This displays the details in the Invoice Field. You can then use the **F14=Pos Cur. Charging Overrides** and **F16=Charging Overrides** functions.

Functions:

F14

Pos. Cur. Charging Overrides. Use this function to display the override entry window for the highlighted item.

F16

Charging Overrides. Use this function to display the override entry window for labour, travel, major, minor, consume and supplies, one after the other.



Select **F3=Exit** to leave the enquiry.

Charging Overrides Enquiry Window (F14, F16)



To display this window, on the Cover Type/Job Category Enquiry Screen, select a job category with 1, and select **F16=Charging Overrides**, or **F14=Pos Cur. Charging Overrides**.

This window displays the charging overrides details for the selected charge. These details include minimum and maximum charges for the specified number of hours, effective dates, and the parts excluded, and included, in this override.



Note: The information displayed varies depending upon the charge selected.

```
SS533          Z1 - GB DEMO. SERVICE COMPANY      USER GBJBATD0      10/10/97
                "BRUM" TRAINING & SERVICE BRANCH    16:18:40
Cover Type/Job Category Enq'y (Detail)

Cover Type..... *A   Total Copier Cover
Currency Code..... GBP   Calibration
Job Category..... CAL
Invoice? Labour  Mileage  Travel  Misc.  Major    Minor    Consume  Supplies
(1/0)           █

Job Category....
1 CAL Calibration
- CSR Customer Ser
- PMA Schedule "A"
- PMB Schedule "B"
- PMC Schedule "C"
- WTY Warranty Cal

Position to : █ More : +

1 Item Number      Description
1 SN0008           Deck Chains : "Titanic" (Nearly New)
1 SN0009           Deck Chains : "Olympic" (Well Worn)
1 SN001            Piston Flange Plate 83mm
1 SN002           Air-Brake Pressure Release Lever
1 SN006           Ball-Cock Arm 26"
1 SN014           Anchor Chain 3.5" Link (Titanic)
1 SN025           Cable Harness - complete 12v 60a

*** ALL ***

F12=Previous  F14=
```

11-37 SA MW KS CL IM DM II STUD140 KB PKH317S1



Select **F12=Previous** to return to the previous screen.

District File Enquiry



27/WOM

Use this option to enquire on the User IDs, authorised to teams, within a district.

An unauthorised user cannot access Engineer Work Allocation or progress any jobs.

District Enquiry Detail Screen



To display this screen, select the District File option, then select a district number and press **Enter**.

This screen displays the users who have the authority to access the teams in this district, in Engineer Work Allocation.

SS557	Demonstration Company CENTRAL BRANCH	USER BRERETM	25/11/93 14:51:41
District Enquiry			
District Number..... D1 District 1			
Team	Description	User Id	
TM1	Team 1	BRERETM	
TM1	Team 1	QSECOFR	
F3=Exit F12=Previous			



Select **F3=Exit** to return to the menu.

Team File Enquiry



28/WOM

Use this enquiry to display the territories, field service groups and job categories defined to a team.

Team Enquiry Detail Screen



To display this screen, select the Team File option, select a team number, and press **Enter**.

SS558	Demonstration Company CENTRAL BRANCH	BRERETM	25/11/93 14:52:11
Team Enquiry			
Team Number.....		TM1	Team 1
Field Service Group G1 Group 1	Territory T01 Territory 1	Job Category ** ALL CATEGORIES **	
F3=Exit F12=Previous			

This screen displays, for each team, all the field service groups, territories and defined job categories.



Select **F3=Exit** to return to the menu.

Field Service Group Enquiry



29/WOM

Use this enquiry to display field service group details, which link divisions and model families within a group.

You set up a team of engineers by allocating certain combinations of field service group, territory and job category characteristics.

Field Service Group Enquiry Detail Screen



To display this screen, select the Field Service Group option, then select a Field Service Group and press **Enter**.

SS559	Demonstration Company	BRERETM	25/11/93
	CENTRAL BRANCH		14:52:28
Field Service Group Enquiry			
Field Service Group..... G1 Group 1			
Model	Division	Model Group	Model Subgroup
	10		
	Environmental		
F3=Exit F12=Previous F13=Fold/Truncate			

The enquiry displays a list of divisions, model groups, model sub-groups and models defined to the selected field service group.

Functions:

F13

Fold/Truncate. Use this function to toggle between displaying descriptions of the codes and just the codes.



Select **F3=Exit** to return to the menu.

3-D Matrix Enquiry



30/WOM

Use this enquiry to display the percentage change to apply to the call response time depending on the customer priority, the volume usage of the model and whether or not the machine is working.

3-D Matrix Enquiry Detail Screen



To display this screen, select the 3-D Matrix option.

SS555	Demonstration Company				USER BRERETM		25/11/93	
	CENTRAL BRANCH						14:52:55	
3-D Matrix	Enquiry		PRIORITY 1		PRIORITY 2		PRIORITY 3	
	MACHINE		MACHINE		MACHINE		MACHINE	
Vol Seg	UP	DOWN	UP	DOWN	UP	DOWN	UP	DOWN
10	1	2	2	3	3	4	4	5
20	2	3	3	4	4	5	5	6
30	3	4	4	5	5	6	6	7
99	5	10	10	15	15	20	20	25

F3=Exit

The 3-D Matrix displays for each volume segment record set up on the volume segment file.

The screen shows the percentage reduction to apply to the call response time for up to four customer priorities. You define the reduction depending on whether the machine is up (working), or down (not working).



Select **F3=Exit** to return to the menu.

Special Serial Numbers Enquiry

1... **2...** 31/WOM

Use this enquiry to display the response times for specific model and serial number combinations, with account or address codes and installation site names.

Serial Number Enquiry Selection Screen



To display the Serial Number Enquiry Selection Screen, select the Special Serial Numbers Enquiry option.

Use this screen to select the serial number and model, for which you want to display the details.

SS554	Demonstration Company CENTRAL BRANCH	USER BRERETM	25/11/93 14:53:26
Special Serial Numbers Enquiry			
Serial Number.....	<u>W930001</u>	Model.....	<u>WA10</u>
F3=Exit F4=Prompt F6=List of Serial Numbers			

Fields:

Serial Number

Enter the serial number to enquire on.

Model

Enter the model to enquire on.



Tip: Leave the serial number field blank, to display a screen showing all the serial numbers for this model. Select the serial number you require by entering 1 alongside it.

Functions:

F6

List of Serial Numbers. Use this function to display a list of the serial numbers for which you have entered a response time.



Press **Enter** to display the Serial Number Enquiry Detail Screen.

Serial Number Enquiry Detail Screen



To display this screen, on the Serial Number Enquiry Selection Screen, select a serial number and model and press **Enter**.

SS554	Demonstration Company CENTRAL BRANCH	USER BRERETM	25/11/93 14:53:42
Special Serial Numbers Enquiry			
Serial Number.....	W930001	Model.....	WA10
Account Number.....	C03 / 000	Jones and Crossland Ltd.	
Response time	1:15		
F3=Exit F12=Previous			

For the selected model and serial number, the screen displays the customer account and address details and installation site name, with the response time defined for the machine.



Select **F3=Exit** to return to the menu.

Condition Code Enquiry



32/WOM

You use this enquiry to display condition and symptoms relationships. These apply to the equipment, and you can enter them when you create a job and when you complete a technical report.

Condition/Symptom Code Enquiry Selection Screen



To display this screen, select the Condition Code (Enquiries) option.

Use this screen to select the model group and division for which you want to display the condition and symptom code details.

Fields:

Division

Select the division.

Model Group

Select the model group.



Enter a division and model group and press **Enter** to display the Condition/Symptom Code Enquiry Screen.

Condition/Symptom Code Enquiry Screen



To display this screen, on the Condition/Symptom Code Enquiry Selection Screen, enter a division and model group and press **Enter**.

W0596	Z1 - Demonstration Company	User GBJBATD0	12/12/97	
	WORKSHOP BRANCH		14:48:53	
Condition/Symptom code enquiry				
Division.....: 00		Environmental Monitoring		
Model group.....: 100		Analysers		
Cond	Description	Symptom	Description	Def
Code		Codes		
A	Code A	1 1 1	Environmental Monitoring	1
A	Code A	1 2 2	Black&White Fairies	0
A	Code A	3 3 3	Analysers failed	0
F3=Exit F12=Previous				

This screen displays all the condition codes defined for the specified division and model group. The information includes the symptom codes, description and which code is the default.

For more information on the fields, see the Condition Code Maintenance section.



To leave the enquiry, select **F3=Exit**.

Defect Code Enquiry



33/WOM

You use this enquiry to display the defect and repair relationships. These apply to the parts the engineer fits to equipment during a repair. You enter them when you complete a technical report to show the condition of the part removed.

Defect Code Enquiry Selection Screen



To display this screen, select the Defect Code (Enquiries) option.

Use this screen to select the defect code you want to display the details for.

Fields:

Defect Code

Select the defect required.



Press **Enter** to display the Defect Code Enquiry Screen.

Defect Code Enquiry Screen

 To display this screen, on the Defect Code Enquiry Selection Screen, enter a defect and press **Enter**.

```
W0597          Z1 - Demonstration Company      USER GBJBATD0  12/12/97
                  WORKSHOP BRANCH                14:51:23

Defect Code Enquiry

Defect Code..... A          Air-pipe split

Repair code   Description                      Dft      Add/Replace
  A          test8                          1         0
  B          Both Speakers                   0         1
  C          Clean                           0         0
  I          R/H Speaker                     0         0
  L          L/H Speaker                     0         0
  R          Replace                         0         0
  1          Use sealing tape                 0         1
  2          Replace with new                 0         1
  3          Fit a spare part                 0         1
  4          Can't touch this                 0         1
  5          test1                           0         1      +

F3=Exit      F12=Previous
```

This screen displays the defined repair codes for the specified defect. The information displayed includes the description, the default repair and whether you need to add or replace a part.

For more information on each field, see the Defect Code Maintenance section.

 To leave the enquiry, select **F3=Exit**.