

## Verification



Card

## Features




LED  
Indicator



Dust Proof &  
Water Proof



Built-in  
Beeper



High Speed  
Processor



## Card Reader

### TW102 RS485

- Built-in audible beeper
- Display the reader status with LED Indicator
- DIP Switch
- RS 485 and Weigand (W26/34) protocol
- Read EM Card
- Dust-proof and Waterproof design



(+91)-11-41916615  
+91-95999-53923



D-162, Okhla Industrial Area  
Phase I, New Delhi, 110020



[sales@timewatchindia.com](mailto:sales@timewatchindia.com)  
[www.timewatchindia.com](http://www.timewatchindia.com)

## Specification

Model	TW102 RS485
Power	12V DC
Working Current	<500mA
Processor	32-Bit
Reading Frequency	125KHz
Reading Range	50-60mm (1.8 to 1.96")
ID Settings	Setting by the DIP switch on the Main Board
Audio Alert	Beeper
Power Consumption	≤6W
LED Indicator	Status LED indicator
Working Temperature	-40 °C to 70 °C (-40 °F to 158 °F)
Protection Level IP	IP 64



**Head Office :** D-162, Okhla Industrial Area Phase I,  
New Delhi, 110020.



**Regional Office :** Mumbai, Bengaluru, Ahmedabad,  
Chennai, Kolkata.

**International Office :** Dubai



**Phone :** +91-95999-53923



**Sales :** sales@timewatchindia.com



**Support :** helpdesk@timewatchindia.com

**Disclaimer :** All pictures shown are for illustration purposes only. The actual product and color may vary due to product enhancement. The brief specification is mentioned and may change without prior notice. Please consult us before placing any order.

