FM Towns Marty 2 Main Board

Designator	Capacity	Voltage	Temp	Lead Spacing	Size	Brand	Series	Notes
			(Not Verified)		(Not Verified)	(Not Verified)	(Not Verified)	
C1	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C2	47uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C3	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C4	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C5	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C6	33uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C7	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C8	2.2uF	50v	105	5mm	4x7	Chemi-Con	KMA	
C9	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C10	33uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C11	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
				_				Inductor soldered from positive leg to D7 on
C12	33uF	16v	105	5mm	6x7	Chemi-Con	KMA	bottom of the board
C15	10uF	16v	105	5mm	4x7	Chemi-Con	KMA	
C16	10uF	16v	105	5mm	4x7	Chemi-Con	KMA	
C17	47uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C18	47uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C19	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C20								Unpopulated
C21	33uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C22	470uF	10v	105	2.5mm	6x11	Chemi-Con	KMG	
C24	33uF	16v	105	5mm	6x7	Chemi-Con	KMA	
C26	1uF	50v	105	5mm	4x7	Chemi-Con	KMA	
C27	1uF	50v	105	5mm	4x7	Chemi-Con	KMA	
C28	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C29	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C30	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C31	100uF	16v	105	5mm	7x7	Chemi-Con	KMA	
C32	10uF	16v	105	5mm	4x7	Chemi-Con	KMA	
C155								Unpopulated
C170	0.47uF	50v	85	5mm	5x11	ELNA	RE2	
C171	0.47uF	50v	85	5mm	5x11	ELNA	RE2	
Board	CA2014	2-B21X	12:00:00 AM	MC32	S O 32D	A31061	MG32 E	

FM Towns Marty 2 Power Supply

Designator	Capacity	Voltage	Temp	Lead Spacing	Size	Brand	Series	Notes
					(Not Verified)			
C5	100uF	200v	105	8mm	12x26			
C6	100uF	200v	105	8mm	12x26			
C7	4.7uF	400v	105	5mm	10x17			
C13	680uF	16v	105	5mm	8x11			
C14	120uF	16v	105	5mm	6x14			
C15	1800uF	10v	105	5mm	12x20			
C16	1800uF	10v	105	5mm	12x20			
C17	120uF	16v	105	5mm	6x14			
C18	100uF	35v	85	5mm	6x11			
C19	47uF	35v	105	5mm	6x11			
Board	CA02951-0800		9301289					

FM Towns Marty 2 CD Drive

Designator	Capacity	Voltage	Temp	Lead Spacing	Size	Brand	Series	Notes
			(Not Verified)		(Not Verified)			
C2	100uF	6.3v	85	2.5mm	6x11			
C4	100uF	10v	105	2.5mm	6x7			
C5	330uF	6.3v	105	2.5mm	8x11			
C7	100uF	6.3v	85	2.5mm	6x7			
C8	100uF	6.3v	105	2.5mm	6x11			
C10	100uF	6.3v	105	2.5mm	6x11			
C12	100uF	16v	105	2.5mm	6x11			
C13	4.7uF	50v	105	2.5mm	5x7			Bipolar
C14	47uF	6.3v	105	2.5mm	4x7			
C15	47uF	6.3v	105	2.5mm	4x7			
C17	1uF	50v	105	2.5mm	5x7			
C18	1uF	50v	105	2.5mm	5x7			
C19	22uF	16v	105	2.5mm	4x7			
C20	330uF	6.3v	105	2.5mm	8x11			
Board	CA02950-0319		3331F	BP60PB50-3		EYPC 94H8	AG-6	

FM Towns Marty 2 Floppy Drive

Designator	Capacity	Voltage	Temp	Lead Spacing	Size	Brand	Series	Notes
C6	22uF	6.3v	85	10mm	4x6	Panasonic	SUS	Axial
C10	220uF	6.3v	85	2.5mm	6x7	Panasonic	KA	
Board	EAMX5 94V-0		ME26	SPB60	331231N			