Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
C114	1000uF	10V	85	10X16	5MM	Unicon	CE	
C116	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C117	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C118	4.7uF	50V	85	5X11	2.5MM	Unicon	CE	
Board	PAH-20154C	REV. NO	REV. NO 18163 04A					

FDC - Sound Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
C10	47uF	25V	85	6X11	2.5	Unicon	CE	
C14	10uF	50V	85	5X11	2.5	Unicon	CE	
C27	4.7uF	50V	85	5X11	2.5	Unicon	CE	
C29	4.7uF	50V	85	5X11	2.5	Unicon	CE	
C31	4.7uF	50V	85	5X11	2.5	Unicon	CE	
C32	10uF	50V	85	5X11	2.5	Unicon	CE	
C33	10uF	50V	85	5X11	2.5	Unicon	CE	
C34	4.7uF	50V	85	5X11	2.5	Unicon	CE	
Board	W4FAG FD	C/SOUND	PAH-3P155C	21321 06A				

Fujitsu FM77AV-2 Video Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
	·		·					
C1	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C2	470uF	16V	85	10X11	5MM	Unicon	CE	
C3	470uF	16V	85	10X11	5MM	Unicon	CE	
C4	470uF	16V	85	10X11	5MM	Unicon	CE	
C6	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C8	100uF	25V	85	8X11	2.5MM	Unicon	CE	Original cap has short spacers, replacement should fit fine without
C9	100uF	25V	85	8X11	2.5MM	Unicon	CE	Original cap has short spacers, replacement should fit fine without
C10	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C11	47uF	25V	85	6X11	2.5MM	Unicon	CE	Silkscreen not visible with cap in place
C12	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C13	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C14	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C15	47uF	25V	85	6X11	2.5MM	Unicon	CE	Original cap has long spacers, mount under board instead
C17	47uF	25V	85	6X11	2.5MM	Unicon	CE	Silkscreen not visible with cap in place
C18	470uF	16V	85	10X11	5MM	Unicon	CE	
C20	47uF	25V	85	6X11	2.5MM	Unicon	CE	
C22	100uF	25V	85	8X11	2.5MM	Unicon	CE	
C24	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C26	100uF	25V	85	8X11	2.5MM	Unicon	CE	
C27	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C31	1uF	50V	85	5X11	2.5MM	Unicon	CE	
C32	100uF	25V	85	8X11	2.5MM	Unicon	CE	Original cap has short spacers, replacement should fit fine without
C38	1uF	50V	85	5X11	2.5MM	Unicon	CE	
C39	100uF	25V	85	8X11	5MM	Unicon	CE	
C40	100uF	25V	85	8X11	5MM	Unicon	CE	
C41	100uF	25V	85	8X11	5MM	Unicon	CE	
C42	100uF	25V	85	8X11	2.5MM	Unicon	CE	Yes, 2 C42s. This is the bigger one
C42	10uF	50V	85	5X11	2.5MM	Unicon	CE	yes, 2 C42s. This is the smaller one
C44	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C46	10uF	50V	85	5X11	2.5MM	Unicon	CE	
C47	47uF	25V	85	6X11	2.5MM	Unicon	CE	

Fujitsu FM77AV-2 Video Board

_						
	Board	PAH-3P156B				

Fujitsu FM77AV-2 LED Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
Board	PAH-4P157A	YKC87V-0						

RF Receiver Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series
C2201	10uF	16V	85	4X7	5MM	ELNA	Н
C2202	100uF	16V	85	6X7	4MM	ELNA	Н
C2206	47uF	16V	85	6X7	4MM	ELNA	Н
Board	DJH 2061628009-002		YKC31V-0				

Power Supply

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series
C09	4.7uF	50V	105	5X11	5MM	Marcon	CE-US
C10	1uF	50V	105	5X11	5MM	Marcon	CE-US
C11	2200uF	10V	105	15X30	8MM	Chemi-con	SXA
C12	2200uF	10V	105	15X30	8MM	Chemi-con	SXA
C13	2200uF	10V	105	15X30	8MM	Chemi-con	SXA
C14	2200uF	10V	105	15X30	8MM	Chemi-con	SXA
C15	1000uF	25V	105	15X30	8MM	Chemi-con	SXA
C16	330uF	25V	105	10X20	5MM	Marcon	CE-US
C17	330uF	25V	105	12X25	5MM	Chemi-con	SXA
C18	330uF	25V	105	10X20	5MM	Marcon	CE-US
C19	1000uF	10V	105	12X25	5MM	Chemi-con	SXA
C20	2200uF	10V	105	15X30	8MM	Chemi-con	SXA
C49	10uF	35V	105	5X11	5MM	Marcon	CE-US
C50	470uF	200V	85	30X35	10MM	Panasonic	CEHR
Board	SPS-594V-0	P-850549					
Fuse	125VAC	5A					