

Sharp MZ-700

Main Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
C2	1uF	50V	85	5X11	5MM	Nichicon	SE	
C4	100uF	10V	85	8X11	5MM	Nichicon		
C20	22uF	16V	85	5X11	5MM	Nichicon	SE	
C24	1uF	50V	85	5X11	5MM	Nichicon	SE	
C26	1uF	50V	85	5X11	5MM	Nichicon	SE	
C27	10uF	16V	85	5X11	5MM	Nichicon	SE	
C37	100uF	10V	85	8X11	5MM	Nichicon		
C82	10uF	16V	85	5X11	5MM	Nichicon	SE	
C86	1uF	50V	85	5X11	5MM	Nichicon	SE	
Board	N1011AC-31E							

Sharp MZ-700

Video Board

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series
C3	100uF	10V	85	6X11	3MM	Panasonic	
C7	0.47uF	50V	85	5X11	3MM	Panasonic	
C18	100uF	10V	85	6X11	3MM	Panasonic	
C13	100uF	10V	85	6X11	3MM	Panasonic	
C14	100uF	10V	85	6X11	3MM	Panasonic	
C18	100uF	10V	85	6X11	3MM	Panasonic	
C19	100uF	10V	85	6X11	3MM	Panasonic	
C22	470uF	6.3V	85	10X11	5MM	Panasonic	
C25	100uF	10V	85	6X11	3MM	Panasonic	
Board	MITSUMI	EMC-NJ1201					

Sharp MZ-700

Power Supply

Designation	Capacitance	Voltage	Temp	Size	Lead Spacing	Brand	Series	Notes
C4	150uF	200V	105	25X25	10MM	Nichicon	CE	
C5	3.3uF	200V	105	10X20	5MM	Nichicon	PL-U	
C9	33uF	35V	105	5X11	2.5MM	Nichicon	PC	
C10	1000uF	10V	105	12X20	5MM	Nichicon	PC	
C11	1000uF	10V	105	12X20	5MM	Nichicon	PC	
C12	1000uF	10V	105	12X20	5MM	Nichicon	PC	
BOARD	A06-2083758		JCI-ALS					
F1	125V 3A							