




GNUSim8085 - 8085 Microprocessor Simulator

File Reset Assembler Debug Help

Registers: A FD, BC 06 07, DE 00 04, HL 00 11, PSW 00 00, PC 42 0C, SP FF FF, Int-Reg 00

Flag: S 1, Z 0, AC 0, P 0, C 1

Decimal - Hex Conversion: Decimal 0, Hex 0, To Hex, To Dec

I/O Ports: 0, Update Port Value

Memory: 0, Update Memory

Load me at:

```
1 LDA 8000
2 MOV B,A
3 LDA 8001
4 MOV B
5 WZA 8002
6 RST 1
```

Start: 8000

Address (hex)	Address	Data
1F40	8000	6
1F41	8001	3
1F42	8002	1
1F43	8003	0
1F44	8004	0
1F45	8005	0
1F46	8006	0
1F47	8007	0
1F48	8008	0
1F49	8009	0
1F4A	8010	0
1F4B	8011	0
1F4C	8012	0
1F4D	8013	0

Line No: 0, Assembler Message: Program assembled successfully

