

Task-1

USB Webcam Setup and Test — Windows

1. Connect the webcam
 - Plug the USB webcam into an available USB port on the computer.
 - Check that the webcam's indicator light turns on, if it has one.
2. Wait for Windows to detect it
 - Windows 10 should automatically detect and install the required driver.
 - Wait for the notification that the device is ready to use.
3. Install the driver if required
 - Open Device Manager by pressing Windows + X - Device Manager.
 - Expand Cameras or Imaging Devices.
 - If the webcam has a warning icon, right-click it - Update driver - Search automatically for drivers.
4. Open the Camera app
 - Click Start and search for Camera.
 - Open the Camera app.
 - Allow camera access if Windows asks for permission.
5. Check the webcam preview
 - Make sure the external USB webcam is selected.
 - Confirm that a live video preview appears.
6. Capture a photo
 - Position yourself in front of the webcam.
 - Click the Take Photo button.
 - Open the photo preview to confirm that the image was successfully captured.

Task-2

Local Printer Setup and Test Page — Windows

1. Connect the printer
 - For a USB printer, connect the USB cable to the computer.
 - For a network printer, connect the printer to the same Wi-Fi/Ethernet network as the PC.
 - Turn the printer on and check that it is ready.
2. Open Printer Settings

- Go to Settings → Devices → Printers & scanners.
- Click Add a printer or scanner.
- 3. Add the printer
 - Wait for Windows to detect the printer.
 - Select the correct printer and click Add device.
 - If it is not detected, choose The printer that I want isn't listed and follow the manual setup options.
- 4. Install the correct driver
 - Windows may automatically install the required driver.
 - If prompted, download the correct driver for the printer model and Windows version from the manufacturer's official website and install it.
 - Restart the PC if required.
- 5. Check the printer status
 - Return to Printers & scanners.
 - Select the printer → Manage.
 - Confirm that it shows as Ready/Online.
- 6. Print a test page
 - Select Printer properties.
 - On the General tab, click Print Test Page.
 - Check that the page prints correctly.

Task-3

Simulated Printer Connectivity Troubleshooting

1. Disconnect the printer
 - Turn on the printer.
 - Unplug the USB cable connecting the printer to the PC.
 - Windows may show that the printer is unavailable or not detected.
2. Open Device Manager
 - Press Windows + X → Device Manager.
 - Look under Printers, Print queues, or Universal Serial Bus controllers.
3. Check for error indicators
 - Look for a yellow warning triangle, unknown device, or missing printer.
 - A warning icon can indicate a driver or hardware-detection problem.
4. Reconnect the USB cable

- Plug the printer's USB cable firmly back into the PC.
- If possible, try a different USB port.
- 5. Scan for hardware changes
 - In Device Manager, click Action → Scan for hardware changes.
 - Windows should detect the reconnected printer and refresh the device list.
- 6. Check or update the driver
 - If the printer appears with a warning icon, right-click it → Update driver → Search automatically for drivers.
 - If necessary, install the correct driver from the printer manufacturer's website.
- 7. Verify the printer
 - Go to Settings → Devices → Printers & scanners.
 - Confirm that the printer appears and shows as Ready/Online.
- 8. Test the connection
 - Print a test page to confirm that the problem has been resolved.

Task-4

Webcam Not Working in Zoom — Troubleshooting Steps

1. Confirm the webcam works
 - Open the Windows Camera app.
 - Verify that the webcam displays live video.
 - Since it works here, the webcam hardware and basic driver are likely functioning.
2. Close other apps using the webcam
 - Close Camera, Microsoft Teams, Skype, Google Meet, or any other application that might be using the webcam.
 - Completely close them from the taskbar or Task Manager if necessary.
 - Restart Zoom.
3. Check Windows camera permissions
 - Go to Settings → Privacy → Camera.
 - Turn on Allow access to the camera on this device.
 - Enable Allow apps to access your camera.
 - Also enable Allow desktop apps to access your camera, because Zoom is a desktop application.
4. Select the correct webcam in Zoom

- Open Zoom → Settings → Video.
 - Under Camera, select the correct USB/webcam device.
 - Check whether the video preview appears.
5. Restart Zoom
- Exit Zoom completely.
 - Reopen it and test the camera again.
 - If necessary, restart the computer.
6. Check the webcam driver
- Press Windows + X → Device Manager.
 - Expand Cameras or Imaging Devices.
 - Make sure the webcam has no yellow warning icon.
 - Right-click it → Update driver → Search automatically for drivers.
7. Test the webcam in Zoom
- Open Zoom → Settings → Video.
 - Confirm that the live preview is now visible.
 - Start a test meeting to verify both video and camera access.