SmartAir X1 Smart Air Purifier

User Manual

TechNova Electronics. Model TN-SAX1. Manual version 1.2, October 2026.

Read this manual before using the product and keep it for future reference.

Contents

1. Safety Instructions ..... page 3

2. Product Specifications ..... page 4

3. What's in the Box ..... page 5

4. Installation ..... page 6

5. Connecting to Wi-Fi ..... page 7

6. Using the SmartAir X1 ..... page 8

7. Maintenance and Filter Replacement ..... page 9

8. Troubleshooting ..... page 10

9. Warranty Policy ..... page 11

10. Returns and Refunds ..... page 11

11. Frequently Asked Questions ..... page 12

12. Contacting Support ..... page 12

1. Safety Instructions

- Use only the power adapter supplied with the product.
- Do not use the device in bathrooms or other wet areas.
- Keep at least 30 cm of free space around the air inlet and outlet.
- Unplug the device before cleaning or replacing the filter.
- Do not insert objects into the air outlet.
- Children should be supervised to ensure they do not play with the device.

2. Product Specifications

The table below lists the technical specifications of the SmartAir X1.

Specification	Value
Model number	TN-SAX1
Product type	Smart air purifier with HEPA filtration
Recommended room size	Up to 45 m² (485 sq ft)
Clean Air Delivery Rate (CADR)	320 m³/h
Filter	3-stage: pre-filter, True HEPA H13, activated carbon
Noise level	22 dB (Sleep mode) to 52 dB (Turbo mode)
Power supply	100-240 V AC, 50/60 Hz, external adapter (24 V DC)
Power consumption	4 W (Sleep) to 38 W (Turbo)
Wi-Fi	2.4 GHz, IEEE 802.11 b/g/n (5 GHz networks are not supported)
App	TechNova Home app (iOS 16+ and Android 10+)
Sensors	PM2.5 laser sensor, temperature, humidity
Dimensions (W x D x H)	26 x 26 x 54 cm
Weight	5.8 kg
Colour	Arctic White

3. What's in the Box

- SmartAir X1 air purifier (filter pre-installed, in plastic wrapping)
- Power adapter (24 V DC) with 1.8 m cable
- Quick start guide
- Warranty card

4. Installation

Follow these steps to install the SmartAir X1:

1. Unpack the device and place it on a flat, stable floor surface.
2. Open the filter cover at the bottom of the device by turning it anticlockwise.
3. Remove the plastic wrapping from the filter. The device will not run correctly with the wrapping on.
4. Put the filter back and close the cover by turning it clockwise until it clicks.
5. Connect the power adapter to the device and to a wall socket.
6. Press the power button. The ring light turns blue when the device is ready.

Placement tips

Place the device at least 30 cm from walls and furniture and away from curtains that could block the air inlet. Installation takes about 5 minutes and requires no tools.

5. Connecting to Wi-Fi

The SmartAir X1 connects to 2.4 GHz Wi-Fi networks (802.11 b/g/n). 5 GHz networks are not supported.

1. Install the TechNova Home app (iOS 16+ or Android 10+) and create an account.
2. Hold the Wi-Fi button on the device for 3 seconds until the Wi-Fi light blinks.
3. In the app, tap Add Device and select SmartAir X1.
4. Choose your 2.4 GHz network and enter the password.
5. Wait until the Wi-Fi light stays on. Pairing takes up to 2 minutes.

6. Using the SmartAir X1

Mode	Description
Auto	Adjusts fan speed automatically based on the PM2.5 sensor.
Sleep	Quietest setting (22 dB). Lights are dimmed.
Manual	Choose fan speed 1, 2 or 3 yourself.
Turbo	Maximum purification for 30 minutes, then returns to Auto.

The ring light shows air quality: blue = good, yellow = moderate, red = poor.

7. Maintenance and Filter Replacement

Replace the filter every 6 months under normal use. The filter indicator and the app show the remaining filter life. Replacement filter part number: TN-SAX1-F.

1. Unplug the device.
2. Open the filter cover and remove the old filter.
3. Insert the new filter and remove its plastic wrapping.
4. Close the cover, plug in the device and hold Filter Reset for 5 seconds.

Clean the pre-filter every 2 weeks with a vacuum cleaner. Only the pre-filter may be rinsed with water.

8. Troubleshooting

Problem	Possible cause	What to do
The device does not turn on	Power adapter not connected, socket has no power, or filter cover not closed	Check that the adapter is firmly plugged into the device and the wall socket. Try another socket. Make sure the filter cover is fully closed: the device will not start while the cover is open (safety switch). Then press and hold the power button for 2 seconds.
The power light blinks red	Filter not installed or filter life has reached 0%	Install or replace the filter, then hold the Filter Reset button for 5 seconds.
The device cannot connect to Wi-Fi	5 GHz network, wrong password, or router too far away	Connect to a 2.4 GHz network. Re-enter the password. Move the device within 10 m of the router. Reset Wi-Fi by holding the Wi-Fi button for 10 seconds.
Air quality reading stays high	Dirty pre-filter, windows open, or sensor covered by dust	Clean the pre-filter, close windows, and wipe the sensor inlet with a dry cloth.
Unusual noise	Device on an uneven surface or packaging left inside	Place the device on a flat, stable surface and remove all plastic wrapping from the filter.

If the problem continues after these steps, contact TechNova Support (see chapter 12).

9. Warranty Policy

TechNova Electronics provides a 24-month limited warranty for the SmartAir X1, starting on the date of purchase shown on your receipt.

What is covered

Defects in materials and workmanship under normal household use.

What is not covered

- Filters (consumable parts)
- Damage caused by accidents, misuse, water, or unauthorised repairs
- Commercial or industrial use

How to make a warranty claim

Contact TechNova Support with your order number or receipt and a description of the problem. We will repair or replace the device free of charge if it is covered.

10. Returns and Refunds

You can return the SmartAir X1 within 30 days of delivery for a full refund, provided it is returned with all original accessories and packaging. Returns after 30 days are not accepted for refund; the warranty still applies to defects.

Refunds are issued to the original payment method within 7-10 business days after we receive the returned item. Return shipping is free for defective products; otherwise the customer pays return shipping.

11. Frequently Asked Questions

Does the SmartAir X1 support Wi-Fi?

Yes. It connects to 2.4 GHz Wi-Fi networks (802.11 b/g/n). 5 GHz networks are not supported.

How often should I replace the filter?

Every 6 months under normal use. The app and the filter indicator tell you when it is time.

Can I use the SmartAir X1 without the app?

Yes. All modes can be controlled with the buttons on the top panel. The app is only needed for schedules, remote control and air-quality history.

Is the filter washable?

Only the pre-filter can be vacuumed or rinsed. The HEPA and carbon layers must not be washed.

Where can I buy replacement filters?

From the TechNova online store or authorised resellers (part number TN-SAX1-F).

12. Contacting Support

Email: support@technova.example. Phone: +1-555-0100. Hours: Monday to Friday, 9:00-18:00 (UTC-5). Please have your model number (TN-SAX1) and order number ready.