

Telebirr Phone Setup - Simple Step-by-Step Guide

Simple step-by-step phone setup

Use this guide from the first Welcome screen on the phone.

Get these items from the supervisor

1. Get the Wi-Fi name and password.
2. Get the AirDroid QR code.
3. Get the OpenClaw setup code or QR code.
4. Get the Device Gateway URL.
5. Get the MDM certificate alias.
6. Get the Telebirr Agent activation code.
7. Get the SIM 1 ICCID.
8. Get the SIM 2 ICCID.
9. Keep the Telebirr PIN for SIM 1 with you.
10. Keep the Telebirr PIN for SIM 2 with you.

1. Put in the two SIM cards

1. Hold the power button.
2. Tap Power off.
3. Remove the SIM tray.
4. Put the first Telebirr SIM into SIM 1.
5. Put the second Telebirr SIM into SIM 2.
6. Put the SIM tray back into the phone.
7. Hold the power button to turn on the phone.
8. Wait for the Welcome screen.

2. Start AirDroid setup

1. Stay on the first Welcome screen.
2. Tap the empty white area six times quickly.
3. Wait for the QR scanner to open.
4. Tap the Wi-Fi network name supplied by the supervisor.
5. Type the Wi-Fi password.
6. Tap Connect.
7. Point the camera at the AirDroid QR code.
8. Wait for the QR code to scan.
9. Tap Continue.
10. Tap Next.
11. Tap Accept.
12. Tap Allow when Android asks for permission.
13. Wait until the Android home screen appears.

3. Finish Biz Daemon setup

1. Open Biz Daemon.
2. Tap the first permission that is not enabled.
3. Tap Allow.
4. Return to Biz Daemon.
5. Tap the next permission that is not enabled.
6. Tap Allow.
7. Repeat until all basic permissions are enabled.
8. Tap Accessibility.
9. Tap Biz Daemon.
10. Turn on Use Biz Daemon.
11. Tap Allow.
12. Return to Biz Daemon.
13. Tap Usage access.
14. Tap Biz Daemon.
15. Turn on Permit usage access.
16. Return to Biz Daemon.
17. Tap Install unknown apps.
18. Turn on Allow from this source.
19. Return to Biz Daemon.
20. Tap Notifications.
21. Turn on Allow notifications.
22. Return to Biz Daemon.
23. Tap Battery optimization.
24. Tap Allow or Don't optimize.
25. Return to Biz Daemon.
26. Tap Continue.

4. Wait for the two applications

1. Keep the phone connected to Wi-Fi.
2. Keep the phone connected to the charger.
3. Wait for the OpenClaw icon to appear.
4. Wait for the Telebirr Device Agent icon to appear.

5. Change the phone to English

1. Open Settings.
2. Tap System.
3. Tap Languages & input.
4. Tap Languages.
5. Tap Add a language.
6. Tap English.
7. Tap United Kingdom or United States.
8. Move English to the top of the list.
9. Return to Settings.
10. Tap Date & time.
11. Turn on Set time automatically.
12. Turn on Set time zone automatically.

6. Allow the applications to keep running

1. Open Settings.
2. Tap Apps.
3. Tap OpenClaw.
4. Tap Battery.
5. Tap Unrestricted or No restrictions.
6. Return to Apps.
7. Tap Telebirr Device Agent.
8. Tap Battery.
9. Tap Unrestricted or No restrictions.
10. Return to the home screen.

7. Connect OpenClaw

1. Open OpenClaw.
2. Tap Connect.
3. Tap Setup Code.
4. Scan the OpenClaw QR code or type the setup code supplied by the supervisor.
5. Tap Pair or Submit.
6. Wait for the supervisor to approve the phone.
7. Wait until the screen says Connected or Online.
8. Return to the home screen.

8. Give permissions to Telebirr Device Agent

1. Open Telebirr Device Agent.
2. When Android asks for SMS permission, tap Allow.
3. When Android asks for Phone permission, tap Allow.
4. When Android asks for notification permission, tap Allow.
5. Open Settings.
6. Tap Accessibility.
7. Tap Downloaded apps, Installed services, or Accessibility services.
8. Tap Telebirr deterministic USSD control.
9. Turn on Use service.
10. Tap Allow.
11. Return to Telebirr Device Agent.

9. Activate Telebirr Device Agent

1. Tap the Device Gateway URL field.
2. Type the Device Gateway URL supplied by the supervisor.
3. Tap the One-time activation code field.
4. Type the Telebirr Agent activation code supplied by the supervisor.
5. Tap the MDM client certificate alias field.
6. Type the MDM certificate alias supplied by the supervisor.
7. Tap Activate.
8. Wait until the screen shows Activated.
9. Tap Confirm OpenClaw is paired.
10. Wait for the next screen.

10. Enter the Telebirr PIN for SIM 1

1. Tap SIM ICCID.
2. Type the SIM 1 ICCID supplied by the supervisor.
3. Tap Telebirr PIN (local only).
4. Type the Telebirr PIN for SIM 1.
5. Tap Confirm Telebirr PIN (local only).
6. Type the same Telebirr PIN again.
7. Tap Store local SIM PIN.
8. Wait for the saved message.

11. Enter the Telebirr PIN for SIM 2

1. Tap SIM ICCID.
2. Delete the SIM 1 ICCID.
3. Type the SIM 2 ICCID supplied by the supervisor.
4. Tap Telebirr PIN (local only).
5. Type the Telebirr PIN for SIM 2.
6. Tap Confirm Telebirr PIN (local only).
7. Type the same Telebirr PIN again.
8. Tap Store local SIM PIN.
9. Wait for the saved message.

12. Finish the setup

1. Connect the charger.
2. Keep Wi-Fi turned on.
3. Open Telebirr Device Agent.
4. Send this message to the supervisor: **PHONE SETUP DONE**.
5. Leave the phone powered on and connected to the charger.