

Fixed Point Parking

1. Course Content

Note: This program runs on a sandbox map; you will need to adjust the program for your personal map.

1. Learn the actions the car takes after recognizing stop
2. Learn the newly emerged key source code

2. Road Sign Detection

Road sign detection source code path:

```
/home/jetson/yahboomcar_auto/src/auto_driver/scripts/auto_drive.py
```

3. Program Startup

3.1 Startup Command

- Parameter Configuration

Parameter path:

```
/home/jetson/yahboomcar_auto/src/auto_driver/config/auto_drive_node.yaml
```

```
turn_radius: 0.4
linear_speed: 0.13
angular_speed: -0.55
duration: 2.0
response_distance_1: 2900
response_distance_2: 132
cooldown_time: 0.2
DEBUG_MODE: False
DEBUG_MODE_2: True
START_AutoDrive: True
Kp: -0.62
Ki: 0.0
Kd: -0.1
max_integral: 1000.0
image_size: [640, 480]
```

After modifying parameters, restart the launch file to use the modified parameters.

- Start camera + chassis + autonomous driving node (need to run in virtual environment terminal)

```
roslaunch auto_driver auto_drive.launch
```

```

(yolov11) jetson@yahboom:~$ roslaunch auto_driver auto_driver.launch
... logging to /home/jetson/.ros/log/2add7f36-d0c0-11f0-9d82-48b62d5ab21e/roslaunch-yahboom-15809.log
Checking log directory for disk usage. This may take a while.
Press Ctrl-C to interrupt
Done checking log file disk usage. Usage is <1GB.

started roslaunch server http://yahboom:44059/

SUMMARY
=====

PARAMETERS
* /ascamera_hp60c/color_pcl: False
* /ascamera_hp60c/confPath: /home/jetson/yahb...
* /ascamera_hp60c/depth_height: 480
* /ascamera_hp60c/depth_width: 640
* /ascamera_hp60c/fps: 30
* /ascamera_hp60c/pub_mono8: False
* /ascamera_hp60c/pub_tfTree: True
* /ascamera_hp60c/rgb_height: 480
* /ascamera_hp60c/rgb_width: 640
* /ascamera_hp60c/usb_bus_no: -1
* /ascamera_hp60c/usb_path: null
* /auto_drive/DEBUG_MODE: False
* /auto_drive/DEBUG_MODE_2: True
* /auto_drive/Kd: -0.1
* /auto_drive/Ki: 0.0
* /auto_drive/Kp: -0.62
* /auto_drive/START_AutoDrive: False
* /auto_drive/angular_speed: -0.55
* /auto_drive/cooldown_time: 0.2
* /auto_drive/duration: 2.0
* /auto_drive/image_size: [640, 480]
* /auto_drive/linear_speed: 0.13
* /auto_drive/max_integral: 1000.0
* /auto_drive/response_distance_1: 2900
* /auto_drive/response_distance_2: 132
* /auto_drive/turn_radius: 0.4

```

3.2 Car movement after recognizing parking

When the program recognizes parking, the program will print stop

```
jetson@yahboom: ~  
jetson@yahboom: ~ 80x24  
different models of devices is not recommended and is likely to affect performance or even cause errors.  
[ascamera_node-1] [INFO] [1764671375.556312801] [ascamera_hp60c.camera_publisher]: 2025-12-02 18:29:35[INFO] [CameraHp60c.cpp] [1148] [streamCallback] set gain ret 0, gain 4  
[auto_drive-4] [12/02/2025-18:29:35] [TRT] [I] [MemUsageChange] TensorRT-managed allocation in IExecutionContext creation: CPU +0, GPU +19, now: CPU 0, GPU 28 (MiB)  
[yolo_detect-3] [12/02/2025-18:29:35] [TRT] [I] [MemUsageChange] TensorRT-managed allocation in IExecutionContext creation: CPU +0, GPU +19, now: CPU 0, GPU 28 (MiB)  
[auto_drive-4] [INFO] [1764671378.387579116] [auto_drive]: current_sign redlight  
[auto_drive-4] [INFO] [1764671378.390984163] [auto_drive]: red_stop  
[auto_drive-4] [INFO] [1764671832.607130196] [auto_drive]: current_sign greenlight  
[auto_drive-4] [INFO] [1764671832.608561506] [auto_drive]: greenlight  
[auto_drive-4] [INFO] [1764673308.321102763] [auto_drive]: current_sign parkA  
[auto_drive-4] [INFO] [1764673308.323742671] [auto_drive]: parking A  
[auto_drive-4] [INFO] [1764674001.122264527] [auto_drive]: current_sign speedlimit  
[auto_drive-4] [INFO] [1764674001.122991778] [auto_drive]: slow down  
[auto_drive-4] [INFO] [1764674013.459037728] [auto_drive]: current_sign stop  
[auto_drive-4] [INFO] [1764674016.463009335] [auto_drive]: Stop action completed
```

The car will stop at a fixed point for three seconds, then resume driving along the line



The fixed point parking handling function is in the auto_drive.py file. Below is the function that is entered after recognizing parking. Users can modify the car's movement after recognizing the road sign themselves

```
def stop(self):
    rospy.loginfo('Stop')
    self.flag = True
    self._set_current_speed(linear_x=0.0)
    time.sleep(3)
    self.flag = False
    self._set_current_speed(linear_x=self.drive_speed, angular_z=0.0)
```

4. Source Code Analysis

4.1, auto_drive.py

YOLO signpost message reception:

```
results = self.sign_detect.get_infer_result(frame, True)
annotated_frame = frame.copy()
```

Multiple filtering mechanisms: mainly to prevent continuously recognizing road signs and triggering actions; the action will only be unlocked when different road signs are recognized.

```
# If a sign that requires cooldown is detected, start cooldown
if detected_sign_requires_cooldown:
    self.sign_cooldown = True
    self.last_sign_time = current_time
    rospy.loginfo(f"Sign detected, starting {self.cooldown_duration}s cooldown")
# Check if the repeated sign should be ignored
should_ignore = False
if obj.class_name == self.last_sign:
    should_ignore = True
```

Event queue processing

```
def _event_handling_worker(self):
    '''Event handling worker thread'''
    # sign handling mapping table
    sign_handlers = {
        "straight": self.go_straight,
        "turnright": lambda: self.turn('right'),
        "turnright_ground": self.do_nothing,
        "honking": self.car_horn,
        "sidewalk": self.slow_down,
        "sidewalk_ground": self.do_nothing,
        "speedlimit": self.slow_down,
        "stop": self.stop,
        "school": self.school,
        "parkA": self.parking_A,
        "parkB": self.parking_A,
        "greenlight": self.go_straight,
        "redlight": self.red_stop,
        "yellowlight": self.stop,
```

```
        "out_park": self.out_parking
    }

    # sign enable index mapping
    sign_enable_map = {
        "straight": 10, "turnright": 11, "honking": 1, "sidewalk": 6,
        "sidewalk_ground": 7, "speedlimit": 8, "stop": 9, "school": 5,
        "parkA": 2, "parkB": 3, "greenlight": 0, "redlight": 4,
        "yellowlight": 13
    }
```

Specific action implementation

```
def stop(self):
    rospy.loginfo('Stop')
    self.flag = True
    self._set_current_speed(linear_x=0.0)
    time.sleep(3)
    self.flag = False
    self._set_current_speed(linear_x=self.drive_speed, angular_z=0.0)
```