

ASTERLINK COMMUNICATIONS

Customer Support Operations Manual

Consumer Connectivity, Mobile Service, Billing, Account, and Service Operations

Document CS-OPS-01 | Version 1.0 | Effective October 2026 | Internal Use Only

Purpose

This manual provides first-line support guidance for common consumer telecom complaints across home internet, Wi-Fi, mobile network service, voice and messaging, SIM/eSIM, device activation, billing, payments, account access, number transfers, orders, international service, and related operations. Each article describes the customer-visible issue pattern and a standard set of resolution actions. Where a case does not fit a documented pattern, the unclassified-case procedure provides a controlled escalation path.

Support Coverage

The manual contains 48 issue articles grouped into five operational families. The coverage is intentionally symptom-oriented so that agents can match customer language such as 'Wi-Fi works but there is no internet', 'my calls keep dropping', 'my payment went through but the bill is still overdue', or 'my eSIM is stuck activating' to the relevant operating procedure.

Triage Principles

Identify the affected product and primary symptom before changing account or network state. Distinguish operational severity from customer sentiment. Avoid repeating troubleshooting the customer has already completed. Prefer the most specific documented procedure that matches the evidence. Do not force ambiguous or novel cases into an unrelated category; use the unclassified-case procedure and escalate with a complete evidence package.

Issue Families

Home Internet and Wi-Fi: fixed broadband outages, intermittent service, speed, latency, Wi-Fi, gateway, fiber/DSL access, fixed wireless, installation, and mesh/extenders.

Mobile Network, Voice, and Messaging: no service, data, calling, messaging, voicemail, Wi-Fi Calling, hotspot, network settings, and area incidents.

SIM, eSIM, and Device Support: physical SIM, eSIM, device activation, compatibility/unlock, lost or stolen devices, and basic device stability.

Billing, Payments, Plans, and Account: payments, charges, plans, refunds, prepaid, login/security, profile and permissions.

Orders, Number Transfers, International Service, and Other Cases: porting, orders, moves/cancellations, international service and billing, and unclassified complaints.

Home Internet and Wi-Fi

Complete Home Internet Outage

KB-NET-001

Use this procedure when the customer's home internet is completely unavailable rather than merely slow or unstable. Customers may say that no device can get online, websites and applications will not load, the router appears powered on but there is no internet, or Wi-Fi remains visible while every connected device reports no internet access. The problem may affect fiber, DSL, cable-equivalent access, or fixed wireless home internet. When several devices fail at the same time, the likely fault is beyond a single phone or laptop and may involve the WAN session, gateway provisioning, access line, customer-premises equipment, upstream network, or an area outage. A complete outage should be distinguished from intermittent connectivity, where service repeatedly returns, and from weak Wi-Fi coverage, where only certain rooms or wireless devices are affected. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm whether all connected devices are affected and whether the local gateway or router remains reachable.
- 2 Check gateway power, cabling, WAN/session state, service provisioning, and any current area outage or maintenance event.
- 3 Restore or reprovision the broadband session when the service profile or WAN state is inconsistent.
- 4 Escalate unresolved access-line or upstream network failures with equipment state and timestamps attached.
- 5 Verify internet access on a known-good device before closing the case.

Intermittent Broadband and Recurring Internet Drops

KB-NET-002

Use this procedure when internet access repeatedly disconnects and returns instead of remaining fully offline. Customers may describe the connection cutting out several times a day, failing at roughly the same time every evening, dropping during work calls, disconnecting online games, or showing Wi-Fi as connected while internet access disappears for a few minutes. A router restart may restore service briefly before the issue returns. If both Ethernet and Wi-Fi devices lose connectivity together, investigate the WAN session, access line, optical or radio link, gateway stability, or peak-hour network congestion. If wired Ethernet remains stable while only Wi-Fi devices fail, the problem is more likely local wireless coverage or interference. Repeatable evening failures, frequent WAN resets, or short service interruptions are strong indicators for this article. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Determine whether the interruption affects Wi-Fi only or both wired and wireless devices.
- 2 Record the frequency, duration, and approximate times of the connection drops.
- 3 Review gateway/WAN logs and access-line, optical, or radio-link health around the affected periods.
- 4 Correct gateway firmware, configuration, or session instability when identified.
- 5 Escalate recurring upstream instability or congestion with timestamps and diagnostic evidence.

Slow Home Internet Throughput

KB-NET-003

Use this procedure when home internet works but performs substantially below the expected speed. Customers may report buffering video, unusually slow downloads, long page-load times, poor file-transfer performance, or speed-test results far below the subscribed plan. A customer on a high-speed fiber plan may see only a small fraction of the expected throughput, or performance may deteriorate mainly in the evening. Possible causes include weak Wi-Fi, device limitations, an incorrect service profile, access-line errors, radio conditions, overloaded customer equipment, or network congestion. For fixed broadband, a wired or near-gateway test is important because poor Wi-Fi performance does not necessarily mean the access service itself is slow. If speed is normal but applications respond slowly, use the latency and packet-delay procedure instead. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires

escalation.

- 1 Compare measured throughput with the subscribed plan and current service profile.
- 2 Test on more than one device and, where possible, perform a wired or near-gateway speed test.
- 3 Check local Wi-Fi conditions, gateway load, access-line quality, radio quality, and network congestion indicators.
- 4 Correct local bottlenecks or reapply the correct speed/service profile where required.
- 5 Escalate persistent access-network or capacity degradation with repeatable test results.

High Latency, Jitter, Packet Loss, or Ping Spikes

KB-NET-004

Use this procedure when bandwidth appears acceptable but interactive applications perform poorly because of delay or unstable packet delivery. Customers may report high ping, gaming lag, jitter, packet loss, stuttering voice or video calls, remote-desktop freezes, delayed responses, or applications that feel slow despite normal download and upload speeds. A connection can carry large amounts of data while still being unsuitable for real-time traffic. Causes may include Wi-Fi interference, unstable access links, overloaded network paths, peak-hour congestion, packet loss, or routing problems. Repeated delay at similar times of day, latency that remains high on Ethernet, or packet loss to multiple destinations suggests a network-side issue rather than a simple Wi-Fi speed problem. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Measure latency, jitter, and packet loss separately from throughput.
- 2 Compare results at different times and, for fixed broadband, compare wired and Wi-Fi performance.
- 3 Record affected applications, destinations, timestamps, and any repeatable packet-loss pattern.
- 4 Correct local wireless interference or access-link instability when isolated.
- 5 Escalate repeatable upstream latency, congestion, or routing faults with measurements attached.

Weak Wi-Fi Signal, Dead Zones, or Wireless Interference

KB-NET-005

Use this procedure when the underlying internet service is working but Wi-Fi performance is poor in specific rooms, floors, or areas of the premises. Customers may say that Wi-Fi is strong beside the router but weak in a bedroom, upstairs room, kitchen, garage, or distant office; devices may disconnect when moved away from the gateway; or streaming may buffer only in certain parts of the home. A key indicator is that Ethernet or devices close to the gateway remain stable while distant wireless devices experience weak signal or poor performance. Common causes include poor router placement, walls and floors, neighboring Wi-Fi networks, interference, inappropriate frequency-band selection, or premises that require additional access points or mesh coverage. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm that the underlying internet service is stable using Ethernet or a near-gateway test.
- 2 Compare Wi-Fi signal and performance across affected and unaffected locations.
- 3 Review router placement, physical obstructions, band selection, and channel congestion.
- 4 Adjust supported Wi-Fi settings or placement and use an approved extender or mesh solution when coverage is insufficient.
- 5 Verify performance in the previously affected rooms after changes.

Unable to Join the Home Wi-Fi Network

KB-NET-006

Use this procedure when a device can see the home Wi-Fi network but cannot connect, repeatedly rejects the password, asks for credentials again, or reports an authentication or connection failure. The internet service may be working normally for other devices. Customers may mention that a new phone, laptop, television, console, or smart-home device cannot join the network, or that all wireless devices stopped joining after the Wi-Fi name or password was changed. The issue may involve incorrect credentials, saved outdated credentials on the device,

disabled Wi-Fi access, unsupported security settings, band compatibility, device restrictions, or a gateway configuration problem. If devices can join Wi-Fi successfully but there is no internet access, use the complete outage or gateway connectivity procedure instead. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the correct Wi-Fi network name and current password.
- 2 Check whether other devices can connect and whether the affected device has an old saved network profile.
- 3 Review supported security mode, band compatibility, device access controls, and gateway Wi-Fi status.
- 4 Reconnect the device after forgetting the saved network or restore approved Wi-Fi settings where necessary.
- 5 Escalate suspected gateway hardware or firmware faults when multiple compatible devices cannot associate.

Router or Gateway Configuration Lost After Reset, Replacement, or Update

KB-NET-007

Use this procedure when connectivity fails or customer settings disappear after a router, modem, or gateway has been factory-reset, replaced, reconfigured, or updated. Customers may report that Wi-Fi is available after a reset but there is no internet, a replacement router cannot establish service, custom Wi-Fi settings disappeared, or the broadband light is healthy while the WAN session remains down. A healthy physical line does not guarantee service if the gateway has lost the correct WAN configuration, service profile, credentials, VLAN settings, or provider-side provisioning. This issue is distinct from an access-line outage because the physical broadband link may appear normal while the gateway is unable to establish the required service session. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm whether the issue began after a reset, replacement, configuration change, or firmware update.
- 2 Verify that the underlying access link is healthy before changing gateway configuration.
- 3 Compare the current WAN/service settings with the approved account profile and required provisioning.
- 4 Restore or reprovision the approved gateway profile and customer Wi-Fi settings where necessary.
- 5 Escalate when the gateway cannot accept the correct profile or appears defective.

Fiber Optical Signal Loss, Red LOS, or Unstable PON

KB-NET-008

Use this procedure for fiber customers reporting a red or blinking LOS light, an unstable PON indicator, an optical warning, or a complete service loss associated with the optical network terminal. Customers may say that the internet stopped after construction work, after the fiber cable was moved, after maintenance in the building, or without any obvious change. A persistent LOS condition generally indicates that the optical terminal is not receiving the expected signal from the fiber network. Restarting the Wi-Fi router usually does not correct a genuine optical-path failure because the problem occurs before the router's internet session. This article should be preferred over ordinary router or Wi-Fi troubleshooting when the customer's optical indicators clearly show signal loss. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the ONT/optical status indicators and whether the LOS condition is persistent.
- 2 Check for visible, safe-to-observe cable disturbance without asking the customer to manipulate fragile optical connectors.
- 3 Review network-side optical status and nearby fiber incidents where available.
- 4 Restore the optical path remotely when possible or arrange fiber-access/field repair.
- 5 Verify normal optical status and internet connectivity after restoration.

DSL Line Not Synchronizing or Broadband Light Not Stable

KB-NET-009

Use this procedure when a DSL customer reports that the modem cannot obtain line synchronization, the DSL or broadband light remains off or flashing, or internet service will not establish even after a restart. Customers may mention that the phone line is connected but the modem never reaches a stable broadband state, that service stopped after cabling was moved, or that filters and telephone equipment were recently changed. Possible causes include line-quality problems, incorrect filtering, loose cabling, inside-wiring faults, service-profile issues, or an access-network fault. This differs from a Wi-Fi issue because the modem itself is not establishing the underlying DSL link. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the DSL/broadband indicator state and whether the modem detects the access line.
- 2 Check the wall connection, approved filters, telephone devices, and modem cabling.
- 3 Review line-quality and synchronization status where available.
- 4 Reprovision the DSL service profile if the line is healthy but session establishment is inconsistent.
- 5 Escalate persistent line-synchronization failures for access-line investigation.

5G or LTE Home Internet Weak Signal and Gateway Placement

KB-NET-010

Use this procedure when fixed wireless home internet is unavailable, unstable, or slow because the home gateway has weak cellular signal or poor placement. Customers may report a red or amber gateway status, low signal, service that improves near a window, repeated connection drops, or very different performance depending on where the gateway is placed. Fixed wireless gateways depend on both the cellular connection to the network and the local Wi-Fi network inside the home. Placement near an exterior-facing window or in an elevated, unobstructed location can materially affect network signal, while poor Wi-Fi coverage inside the home is a separate issue. This article is appropriate when the gateway's cellular or access signal is weak rather than when the internet connection is healthy but a distant room has poor Wi-Fi. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Check the gateway's network-signal and status indicators.
- 2 Confirm that the gateway is placed in an approved elevated location with minimal obstruction and good network signal.
- 3 Compare service stability and performance after relocating the gateway within supported placement guidance.
- 4 Separate weak cellular access signal from local Wi-Fi coverage problems.
- 5 Escalate persistent weak-signal or coverage failures when no supported placement provides reliable service.

Home Internet Activation or Initial Installation Not Completing

KB-NET-011

Use this procedure when a new or replacement home internet service cannot complete initial activation, self-installation, or equipment setup. Customers may report that the gateway never reaches a ready state, service is not visible in the account, the router cannot activate, an installation step remains pending, or the service is physically connected but not provisioned. The issue may involve incorrect equipment association, an incomplete order, missing account activation, a failed line or signal check, unsupported installation location, or a provisioning task that did not complete. This article is intended for first-time or replacement setup rather than a previously working service that has suddenly failed. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the service order, equipment identifier, account activation state, and intended service address.
- 2 Check that required hardware is connected and showing the expected startup state.
- 3 Confirm network signal or access-line availability before retrying activation.
- 4 Reconcile incomplete equipment association or provisioning tasks where supported.

- 5 Escalate failed activation or installation states that remain pending after prerequisites are confirmed.

Wi-Fi Extender or Mesh Node Not Pairing or Providing Coverage

KB-NET-012

Use this procedure when a Wi-Fi extender, mesh node, or secondary access point will not pair with the main gateway, repeatedly disconnects, shows poor backhaul quality, or fails to improve coverage. Customers may say the extender is powered on but not visible, pairing fails, devices continue connecting to a weak router signal, or the added unit provides little improvement in the intended room. The problem can result from incompatible equipment, outdated firmware, excessive distance from the primary gateway, poor placement, failed pairing, or weak backhaul between nodes. This differs from general Wi-Fi coverage because the customer has already introduced a supported extension device that is not operating correctly. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify extender or mesh compatibility with the customer's gateway and current firmware.
- 2 Confirm the unit is within an appropriate distance from the primary gateway during pairing.
- 3 Retry supported pairing and check the node's backhaul or link-quality status.
- 4 Reposition the node to balance strong backhaul with useful coverage.
- 5 Replace or escalate a node that cannot pair or maintain a stable supported connection.

Mobile Network, Voice, and Messaging

No Mobile Service, Emergency Calls Only, or Network Registration Failure

KB-MOB-001

Use this procedure when a mobile device cannot register normally on the cellular network and shows no service, searching, emergency calls only, or a similar registration state. Customers may be unable to call, text, or use mobile data. The issue can follow a SIM change, device change, activation, software update, travel to a different coverage area, or occur without an obvious trigger. Possible causes include a local network outage, weak coverage, disabled cellular service, an inactive or incorrectly provisioned SIM/eSIM, account restriction, incompatible device, or stale network registration. If calls and texts work but mobile data alone fails, use the mobile-data procedure instead. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Check local coverage/outage status and confirm the device has cellular service enabled.
- 2 Verify the line is active and the SIM/eSIM is correctly provisioned for the device.
- 3 Refresh network registration or supported network settings and restart the device where appropriate.
- 4 Test in another location or compatible device when needed to separate device, SIM, and coverage causes.
- 5 Escalate persistent network registration failures after account, device, and SIM causes are ruled out.

Mobile Data Not Working While Calls or Texts Still Work

KB-MOB-002

Use this procedure when a mobile customer has cellular signal and can make calls or send texts but cannot access the internet using mobile data. Customers may say the phone shows 4G or 5G but applications report no internet, mobile data stopped after changing phones, data failed after a plan or recharge change, or voice service is normal while internet access is unavailable. Because voice service works, the line is generally registered to the network; likely causes include data entitlement, APN or carrier-profile configuration, device data settings, provisioning, usage restrictions, or an incomplete service update. This applies to prepaid and postpaid lines and should be distinguished from a full no-service condition. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm voice/text service works and mobile data is enabled on the device.
- 2 Verify active data entitlement, plan state, usage restrictions, and account provisioning.
- 3 Check the approved carrier/APN profile and recent device, SIM, or plan changes.
- 4 Refresh or reapply mobile-data provisioning and supported network settings.
- 5 Escalate when correct provisioning still fails on a known-good compatible device in coverage.

Slow Mobile Data or Poor Cellular Internet Performance

KB-MOB-003

Use this procedure when mobile data works but is much slower than expected. Customers may report slow downloads, buffering, poor browsing, low speed-test results, or good performance in one place and poor performance elsewhere. Causes can include weak radio signal, distance from a cell site, building materials, terrain, heavy foliage, device limitations, plan-based speed controls, temporary network events, or congestion when many users are active in the same area. Performance may vary by location and time even when the device displays 4G or 5G. If the customer has no data connection at all, use the mobile-data-unavailable procedure. If data speed is good but real-time applications lag, investigate latency or packet loss. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the customer's plan/data state and whether any speed restriction or data-management condition applies.
- 2 Compare signal quality and performance across locations and times of day.
- 3 Check for local network incidents or congestion and test on a known-good device when appropriate.
- 4 Refresh supported network settings if the device appears stuck on an inappropriate network state.
- 5 Escalate repeatable network-side performance degradation with location, time, and test results.

Dropped Calls, Robotic Audio, One-Way Audio, or Poor Call Quality

KB-MOB-004

Use this procedure when a customer can place or receive mobile calls but experiences repeated call drops, distorted or robotic audio, one-way audio, temporary silence, clipping, or unreliable voice quality. The problem may occur everywhere, only in one building or neighborhood, or only on a specific device. Customers may report normal signal bars even while calls drop, or calls that work outdoors but fail indoors. Potential causes include weak or unstable radio coverage, local interference, voice/IMS registration problems, network incidents, device configuration, or device-specific radio faults. Determining whether the issue follows the location, SIM/account, or handset is central to separating a network problem from a device problem. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Determine whether the issue occurs in one location, multiple locations, or only on one device.
- 2 Record whether calls drop, distort, lose audio, or fail in another repeatable way.
- 3 Check voice/IMS registration, recent device changes, and local network incidents.
- 4 Refresh supported voice/network registration settings or isolate the device when appropriate.
- 5 Escalate repeatable network-side call degradation with locations, timestamps, and examples.

Unable to Make or Receive Mobile Calls

KB-MOB-005

Use this procedure when the device appears registered to the network but the customer cannot make outgoing calls, cannot receive incoming calls, or both. Customers may see calls fail immediately, hear an error message, find that incoming calls go directly to voicemail, or report that only certain destinations fail. Possible causes include an account or line restriction, network outage, voice-service provisioning issue, call forwarding or blocking settings, device network settings, SIM registration

problems, or a service feature that is not active. If the device shows no service or emergency calls only, start with the network-registration procedure instead. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm network registration, coverage, and whether the issue affects outgoing calls, incoming calls, or both.
- 2 Check line status, voice-service provisioning, call forwarding, blocking, and relevant account restrictions.
- 3 Test a known destination and review any error message or failure pattern.
- 4 Refresh supported voice/network settings or provisioning where appropriate.
- 5 Escalate persistent calling failures after coverage, account, SIM, and device causes are ruled out.

SMS, MMS, Group Messaging, or RCS Not Sending or Receiving

KB-MOB-006

Use this procedure when a customer cannot send or receive text messages, picture/video messages, group messages, or RCS chats. Customers may report messages stuck on sending, failed delivery, missing incoming messages, media that will not download, group chats that split into individual threads, or RCS remaining disconnected. Possible causes include weak network coverage, mobile-data restrictions, messaging blocks, incorrect message-center or carrier settings, unsupported RCS state, outdated software, number-porting transitions, or device/app configuration. MMS and many advanced messaging features require data connectivity even when ordinary SMS may still work. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Identify whether the failure affects SMS, MMS, group messaging, RCS, or all messaging.
- 2 Confirm network coverage, mobile-data availability, line messaging permissions, and current software/app state.
- 3 Check supported carrier messaging settings and whether RCS is registered/connected when applicable.
- 4 Refresh the messaging/network state or re-register supported advanced messaging services.
- 5 Escalate persistent network-side messaging failures with examples and affected destinations.

Voicemail or Visual Voicemail Not Working

KB-MOB-007

Use this procedure when voicemail cannot be accessed, Visual Voicemail will not load or download, voicemail notifications are missing, callers cannot leave messages, or the mailbox is not behaving normally. Common causes include voicemail not being set up after activation or a device/SIM change, weak or unavailable network connectivity, a full mailbox, call-forwarding settings, missing voicemail features, an incorrect voicemail password, or an application-specific issue. Visual Voicemail typically requires data connectivity, while traditional voicemail can often be tested by dialing the voicemail service directly. If the customer cannot make or receive calls at all, resolve the calling issue before treating voicemail as the primary problem. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the customer can make a normal test call and has sufficient network/data connectivity.
- 2 Verify voicemail is active and the mailbox has been set up for the line.
- 3 Check call-forwarding behavior, mailbox capacity, voicemail password, and Visual Voicemail application state.
- 4 Test direct voicemail access separately from the Visual Voicemail application.
- 5 Reset or reprovision voicemail when required and escalate unresolved mailbox/service failures.

Wi-Fi Calling Will Not Activate or Calls Fail Over Wi-Fi

KB-MOB-008

Use this procedure when a compatible device cannot enable Wi-Fi Calling, repeatedly turns the feature off, fails to register, or cannot reliably place calls or texts over Wi-Fi. Customers may rely on Wi-Fi Calling in buildings with weak cellular coverage or while traveling. The feature generally requires an active eligible line, compatible device,

working Wi-Fi internet connection, current software, and successful service registration. Failures may be caused by poor Wi-Fi connectivity, incomplete account provisioning, device incompatibility, stale registration, missing emergency-address information, or software/network settings. If the customer's Wi-Fi itself is not working, resolve the underlying internet connection first. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the line and device support Wi-Fi Calling and that the Wi-Fi internet connection is stable.
- 2 Verify required account/service registration information and current software.
- 3 Refresh Wi-Fi Calling registration or supported network settings where appropriate.
- 4 Test calling over a known-good Wi-Fi network to separate Wi-Fi and cellular causes.
- 5 Escalate persistent service-registration failures after eligibility and connectivity are confirmed.

Mobile Hotspot or Tethering Not Working or Too Slow

KB-MOB-009

Use this procedure when a customer cannot enable personal hotspot/tethering, connected devices cannot access the internet through the phone, hotspot performance is unexpectedly slow, or tethering stops after a plan or device change. The issue may involve plan eligibility, hotspot data allowance, device settings, mobile-data availability, connected-device limits, Wi-Fi band compatibility, software, or network congestion. A hotspot cannot provide better connectivity than the phone's own mobile-data connection, so poor cellular data performance will also affect tethered devices. If mobile data on the phone itself is unavailable, resolve that issue first. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm mobile data works on the host device and the plan includes the required hotspot capability.
- 2 Check hotspot settings, password, connected-device limits, and any hotspot data allowance or restriction.
- 3 Test with one connected device and review cellular signal/network performance.
- 4 Refresh supported network settings or hotspot configuration when needed.
- 5 Escalate entitlement/provisioning problems that remain after device configuration is verified.

Carrier Profile, APN, or Mobile Network Settings Incorrect

KB-MOB-010

Use this procedure when calls, messaging, or mobile data problems are likely caused by incorrect carrier settings, APN configuration, network mode, or stale device network state. Customers may experience mobile data that stopped after changing devices, a bring-your-own-device that can call but cannot use data, repeated registration problems after manual network changes, or services that work only after a network reset. Carrier-managed devices normally receive approved settings automatically, while unlocked or transferred devices may require additional validation. This article should be used when there is evidence of a configuration mismatch rather than a broad network outage. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the device model, software state, and whether the device was supplied by AsterLink or brought from another carrier.
- 2 Compare the current carrier/APN/network profile with the approved configuration for the service.
- 3 Remove unsupported manual settings and refresh the carrier/network configuration where appropriate.
- 4 Restart or re-register the device after applying the supported profile.
- 5 Escalate if approved settings do not restore service on a compatible device.

Area Network Outage or Local Coverage Degradation

KB-MOB-011

Use this procedure when multiple services or multiple customers in the same area report sudden loss of signal, degraded data, dropped calls, or

intermittent service. Customers may say that service worked normally before a specific time, several household members are affected, neighbors report the same issue, or performance changes sharply when leaving the neighborhood. A local network outage, site maintenance, backhaul failure, power issue, capacity event, or weather-related impact can affect voice, messaging, and data together. This topic differs from a device-specific issue because the failure is correlated with location or a wider group of users. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Check current network incidents, maintenance, and coverage status for the reported area.
- 2 Confirm whether multiple devices, lines, or nearby customers are affected.
- 3 Record location, start time, affected services, and whether service improves elsewhere.
- 4 Avoid unnecessary device reprovisioning when a confirmed area event explains the symptoms.
- 5 Escalate unreported but reproducible area-wide degradation to network operations.

SIM, eSIM, and Device Support

Physical SIM Activation, Replacement, or Registration Problem

KB-DEV-001

Use this procedure when a physical SIM is new, recently replaced, moved to another device, detected by the phone but not active, or unable to register correctly. Customers may see no service, not registered on network, emergency calls only, or an activation that appears incomplete. Possible causes include an uncompleted SIM swap, incorrect SIM identifier on the account, stale network provisioning, a blocked or inactive line, device incompatibility, or a defective SIM. A correctly activated physical SIM should be associated with the intended line and a compatible device before network registration is expected to succeed. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the intended line, SIM identifier, account status, and device compatibility.
- 2 Confirm the SIM is properly inserted and recognized by the device.
- 3 Complete or refresh the supported SIM activation/registration workflow.
- 4 Test registration after rebooting or on a known-compatible device where appropriate.
- 5 Replace or escalate a SIM that remains unable to register despite correct provisioning.

eSIM Download, Activation, or Device-to-Device Transfer Failure

KB-DEV-002

Use this procedure when an eSIM will not download, remains stuck on activating, was deleted accidentally, fails during transfer to a new phone, or appears installed but cannot register for service. Customers may say the QR code no longer works, the old device lost service before the new one activated, the cellular plan is present but inactive, or the device never received an activation notification. Common causes include an already-consumed activation token, incompatible device, incomplete provisioning, stale eSIM state, device identifier mismatch, or transfer prerequisites that were not met. Successful eSIM activation generally requires a compatible device, working Wi-Fi during download, and the correct profile associated with the intended line. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify device compatibility, line eligibility, and current eSIM/profile state.
- 2 Check whether the activation profile or token has already been consumed or invalidated.
- 3 Confirm the intended device identifiers are associated with the line.
- 4 Clear stale activation state or issue a new approved eSIM profile when required.
- 5 Verify voice, text, and data registration on the new eSIM before closing.

New Phone or Replacement Device Activation Not Completing

KB-DEV-003

Use this procedure when a newly purchased, upgraded, replacement, or warranty device cannot complete service activation. Customers may report that the device powers on but has no service, activation remains pending, the old device still has service, the new SIM/eSIM is not active, or account systems still show the previous device. Possible causes include an incomplete device swap, SIM/eSIM mismatch, unsupported device, pending order state, activation lock, network provisioning delay, or a device identifier that was not correctly associated with the line. This article is intended for initial service setup after a device change rather than a previously active device that suddenly lost network service. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the line, device identifier, order/upgrade status, and intended SIM/eSIM association.
- 2 Confirm any required device setup, connectivity, and software prerequisites.
- 3 Complete or reconcile the supported activation/device-swap workflow.
- 4 Refresh network registration after the new device is correctly associated.
- 5 Escalate activation states that remain pending after account and device prerequisites are confirmed.

Bring-Your-Own-Device Compatibility or Device Unlock Problem

KB-DEV-004

Use this procedure when a customer brings a device from another carrier or retailer and cannot activate it, use all services, or complete an unlock-related requirement. Customers may report that the SIM/eSIM installs but there is no service, data does not work, the device says SIM not supported, activation is rejected, or the handset remains locked to a previous provider. A device may need to support AsterLink network technologies and bands, have a clean device status, be unlocked by the previous provider, and receive the correct carrier configuration. A device that is technically compatible may still require network or APN configuration before all features work. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify device identifier, compatibility, lock state, and whether the device is eligible for activation.
- 2 Confirm the device supports the required network services and current software.
- 3 Complete the approved SIM/eSIM activation and carrier-profile configuration.
- 4 Direct unresolved carrier-lock issues to the responsible prior provider when applicable.
- 5 Escalate compatible-device provisioning failures that persist after configuration is correct.

Lost or Stolen Mobile Device

KB-DEV-005

Use this procedure when a customer reports that a phone, tablet, hotspot, or connected device is lost or stolen. The immediate goals are to protect the line and account, reduce the risk of unauthorized usage, and help the customer secure the device and associated accounts. Customers may need service suspended, the device blocked, a replacement SIM/eSIM, or guidance on device-location and remote-lock tools that were already enabled. Support staff should avoid asking for unnecessary personal secrets or device credentials and should follow identity-verification requirements before making account changes. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Complete the approved identity-verification process before changing line or device status.
- 2 Suspend the affected line or block the device using the supported loss/theft workflow.
- 3 Advise the customer to use previously enabled operating-system location/lock tools and secure sensitive accounts.
- 4 Arrange replacement SIM/eSIM or device support according to account eligibility.
- 5 Escalate suspected account compromise, fraud, or unauthorized changes to the security team.

Device Will Not Power On, Charge, or Remain Stable

KB-DEV-006

Use this procedure for basic device-hardware or operating-system symptoms that prevent normal telecom service, including a phone that will not power on, does not charge, repeatedly restarts, freezes, crashes, becomes unusually hot, or cannot remain operational long enough to connect to the network. Customers may initially describe this as a service problem because calls and data are unavailable, but the primary fault is device stability or power. The support objective is to separate a device failure from a SIM/account/network problem and determine whether basic supported recovery steps, warranty, repair, or device protection should be used. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm whether the device powers on, charges, and remains stable independently of network service.
- 2 Use supported restart, charging, software-update, or safe-mode recovery steps appropriate to the device.
- 3 Test SIM/service on another compatible device when necessary to separate line and hardware causes.
- 4 Check warranty, protection, repair, or replacement eligibility when the fault appears hardware-related.
- 5 Escalate safety-related battery swelling, overheating, or physical damage according to device-safety policy.

Billing, Payments, Plans, and Account

Successful Payment Not Reflected on the Account

KB-BIL-001

Use this procedure when the customer says a bill payment, recharge, or renewal succeeded through a bank, card, wallet, or payment channel but the AsterLink account still shows unpaid, overdue, pending, or an unchanged balance. Customers may provide a transaction reference, bank confirmation, or payment receipt and may be concerned about suspension or making a second payment. Possible causes include delayed reconciliation, payment posted to another account, a gateway transaction that did not match the billing system, or a recharge event that did not update the service balance. Do not advise the customer to pay again until the existing transaction state has been checked. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Capture the transaction reference, amount, timestamp, payment method, and intended account.
- 2 Verify the payment state in the payment channel and AsterLink billing/recharge systems.
- 3 Check whether the payment posted to another linked account or is awaiting reconciliation.
- 4 Reconcile or route a confirmed successful payment to the correct account.
- 5 Confirm the updated balance/service state before closing.

Duplicate Payment or Multiple Charges for the Same Bill

KB-BIL-002

Use this procedure when a customer reports that the same bill, renewal, or service charge was paid or debited more than once. Customers may see two identical card charges, two bank debits within minutes, or multiple payment confirmations for a single billing period. A duplicate may result from a retry after a timeout, a payment-gateway reconciliation issue, an automatic payment processed after a manual payment, or two genuinely separate transactions. It is important to distinguish a duplicate settled charge from a temporary authorization or pending card entry before initiating a refund. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Compare transaction references, amounts, timestamps, and the billing obligation each transaction relates to.
- 2 Confirm whether each entry is settled, pending, reversed, or only an authorization hold.
- 3 Match confirmed payments to billing receipts and identify the duplicate transaction.
- 4 Initiate the approved reversal/refund workflow for a confirmed duplicate.
- 5 Document the reconciliation result and expected refund path.

Bill Higher Than Expected, First Bill, Proration, Fees, or One-Time Charges

KB-BIL-003

Use this procedure when a customer says the total bill is unexpectedly high and the cause is not yet known. Common reasons include first-bill charges, partial-month or prorated service, activation or installation fees, equipment installments, plan changes during a billing cycle, taxes and surcharges, expired promotions, or one-time purchases. Customers may compare the bill with an advertised monthly price and believe they were overcharged when the current bill contains legitimate transitional or one-time items. This article is for explaining and validating the composition of the bill; use a more specific dispute article when a clearly incorrect charge, duplicate payment, roaming charge, or missing promotion is identified. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Review the current bill line by line against the prior bill, recent orders, plan changes, and service start dates.
- 2 Identify one-time, prorated, installment, tax, fee, or promotional changes that explain the difference.
- 3 Confirm whether each charge matches the customer's service and effective dates.
- 4 Correct or dispute only items that cannot be supported by the account history.
- 5 Explain the expected recurring amount after temporary charges or credits complete.

Incorrect Plan, Add-On, Promotion, Discount, or Bill Credit

KB-BIL-004

Use this procedure when the customer says a plan price, add-on, discount, promotion, trade-in credit, autopay discount, bundle discount, or other recurring adjustment is missing or incorrect. Customers may report that an add-on they did not request appears on the bill, a promised discount has disappeared, a device promotion has not started, or a plan change is billed at the wrong rate. These issues often result from eligibility requirements, delayed promotional credits, an add-on that did not deactivate, account changes that removed eligibility, or billing systems that are not synchronized with the effective service configuration. The account history and offer terms should be used to determine whether the charge is expected or requires correction. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Compare the billed plan/add-on/discount with the effective service configuration and account-change history.
- 2 Verify promotion eligibility, required conditions, effective dates, and expected credit timing.
- 3 Correct an incorrect plan/add-on state or submit the approved adjustment when the account history supports it.
- 4 Document why the charge was valid or what correction was applied.
- 5 Confirm the expected treatment on the next bill.

Unexpected Usage, Overage, Data, or Premium-Service Charges

KB-BIL-005

Use this procedure when a customer disputes usage-based charges such as excess data, premium messaging, international usage, hotspot usage, or another metered service. Customers may say they did not knowingly exceed an allowance, believe usage was counted incorrectly, or are surprised by a charge generated by a device or service feature. The investigation should compare usage records, plan allowances, billing periods, alerts, feature settings, and any relevant roaming or premium-service conditions. If the dispute is specifically about international roaming, use the roaming-charge article because rating and partner-network records may require additional review. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Identify the exact usage type, billing period, allowance, and charge being disputed.
- 2 Compare network usage records with the customer's plan and any relevant alerts or thresholds.

- 3 Determine whether the usage is valid, duplicated, delayed, or associated with an unexpected feature.
- 4 Apply an approved adjustment only when records or policy support correction.
- 5 Explain preventive controls or usage alerts relevant to the customer's service.

Refund, Credit, or Reversal Not Received

KB-BIL-006

Use this procedure when a customer says an approved refund, credit balance refund, failed recharge refund, duplicate-payment reversal, device return refund, or billing adjustment has not been received. Customers may have a refund reference and see the item as completed in one system while the bank or card has not yet posted it. Possible causes include normal settlement time, refund to a different payment instrument, a failed or rejected refund, an account credit applied instead of cash refund, or a mismatch between billing and payment systems. Do not create a second refund until the state of the first one has been established. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Locate the original transaction and the refund/credit reference, amount, date, and destination.
- 2 Check whether the refund is initiated, settled, rejected, returned, or applied as an account credit.
- 3 Confirm the destination payment method or account.
- 4 Re-initiate or correct the refund only when the prior attempt failed or was misrouted.
- 5 Provide the updated refund state and reference in the ticket.

Late Payment, Payment Arrangement, or Service Suspended for Non-Payment

KB-BIL-007

Use this procedure when a customer cannot pay by the due date, wants a payment arrangement, has an active arrangement that failed, or reports that service was suspended or restricted because of a past-due balance. Customers may ask for more time to pay, dispute restoration timing, or say they already made a payment but service remains suspended. Eligibility for arrangements, late fees, restoration fees, autopay interaction, and restoration timing depend on account status and current policy. If the payment itself is missing despite being successfully completed, use the payment-not-reflected procedure before treating the case as non-payment. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the past-due balance, payment history, suspension state, and any existing arrangement.
- 2 Determine whether the account is eligible for an approved payment arrangement or immediate restoration workflow.
- 3 Record any scheduled payment terms and explain service-restoration dependencies.
- 4 Restore service through the supported process once the required payment condition is met.
- 5 Escalate inconsistent suspension/restoration states after billing conditions are satisfied.

Prepaid Recharge, Balance, Validity, or Pack Not Applied

KB-BIL-008

Use this procedure for prepaid customers who report that a recharge, top-up, plan pack, data pack, validity extension, or balance change did not apply as expected. Customers may have a successful payment but no new balance, an active pack that does not provide the expected benefit, an expired service despite recent recharge, or a deduction they do not understand. The investigation should compare the recharge transaction, pack eligibility, effective date, validity period, current balance, and usage records. A recharge can succeed financially while the service entitlement fails to post, which requires reconciliation rather than another payment. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the recharge transaction, amount, selected pack, target number/account, and current balance.
- 2 Check the pack's eligibility, activation state, effective date, validity, and included benefits.

- 3 Reconcile a successful payment that did not create the expected prepaid entitlement.
- 4 Correct an incorrectly applied pack or route the case when the selected pack cannot be changed automatically.
- 5 Confirm the updated balance, validity, and active benefits.

Plan, Add-a-Line, Feature, or Service Change Not Applied

KB-BIL-009

Use this procedure when a customer requested a plan change, line addition/removal, feature change, speed upgrade, add-on change, or service modification that appears complete in one system but has not taken effect in billing or network provisioning. Customers may report that the app still shows the old plan, data allowances remain unchanged, broadband speed did not increase, a removed feature still appears, or billing reflects a different configuration from the service. The issue often results from an order stuck between CRM, billing, and provisioning systems, or from a legitimate future effective date that the customer did not expect. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the requested change, order status, effective date, and current account configuration.
- 2 Compare CRM/order state with billing and network/service provisioning.
- 3 Determine whether the change is legitimately scheduled or is stuck/inconsistent.
- 4 Reconcile or reapply the approved change through the supported workflow.
- 5 Confirm service entitlement and billing configuration match after completion.

Account Login, User ID, Password, Passcode, or Verification Problem

KB-ACC-001

Use this procedure when a customer cannot sign in to the AsterLink app or website, cannot receive a verification code, forgot a user ID or password, is locked out after repeated attempts, or cannot complete account recovery. Customers may have changed their phone number or email, lost access to the registered recovery channel, or encounter a verification loop even with the correct password. Account access problems are distinct from network service faults and must be handled with identity and security controls. Support staff should never bypass required verification or request passwords, authentication secrets, or unnecessary sensitive data. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Use the approved identity-verification process before changing account access or recovery information.
- 2 Check account lock state, user ID, registered recovery channels, and verification-delivery status.
- 3 Use supported password/passcode reset, account unlock, or recovery-channel update workflows.
- 4 Confirm successful sign-in without collecting or storing the customer's secret credentials.
- 5 Escalate identity conflicts or recovery situations that cannot be resolved safely.

Unauthorized Account Change, Fraud, or Suspected Account Takeover

KB-ACC-002

Use this procedure when a customer reports an unauthorized SIM/eSIM change, unexpected device activation, unknown line or purchase, password reset they did not request, suspicious account access, fraudulent charge, or other indication that the account may be compromised. The priority is to protect the account, preserve evidence, and avoid making changes based solely on information that may be available to an attacker. Customers may also report phishing, social-engineering attempts, or a lost device followed by account changes. These cases require stronger identity verification and security escalation than ordinary billing or login support. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Apply the approved high-assurance identity-verification process.

- 2 Secure the account using supported locks, credential resets, line/SIM protections, or suspension controls as appropriate.
- 3 Document unauthorized activity, timestamps, affected lines/devices, and relevant transactions.
- 4 Do not disclose sensitive account details until identity is established.
- 5 Escalate confirmed or suspected compromise to fraud/security operations.

Profile, Contact Information, Permissions, or Billing Responsibility Change

KB-ACC-003

Use this procedure when a customer needs to update account contact details, authorized users, line permissions, account ownership, billing responsibility, or other profile information. Customers may no longer have access to an old email or phone number, need to add or remove an authorized person, transfer responsibility for one or more lines, or correct account-holder information. Some changes can affect plan eligibility, discounts, device installments, final bills, or service permissions. Identity verification and authorization are required before making ownership or permission changes. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the account owner or authorized user's identity and the requested scope of change.
- 2 Check eligibility, outstanding balances, installment obligations, locks, or restrictions that may prevent the change.
- 3 Apply the supported profile, permission, or billing-responsibility workflow.
- 4 Explain material plan, pricing, or billing consequences before finalizing when applicable.
- 5 Confirm that the new account/profile permissions are correctly reflected.

Orders, Number Transfers, International Service, and Other Cases

Mobile Number Porting or Transfer Delay

KB-OPS-001

Use this procedure when a customer is moving a phone number between carriers and the port is delayed, partially completed, rejected, or leaving some services unavailable. Customers may report that the old SIM stopped working while the new one has no service, outgoing calls work but incoming calls still reach the previous carrier, SMS or data does not work after the port, or the transfer remains pending beyond the expected window. Possible causes include incorrect account/transfer information, a pending donor-carrier response, number-transfer protection, an incomplete activation, or provisioning tasks that did not complete after the number moved. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Check the transfer order state, timestamps, submitted account/transfer information, and any protection or lock.
- 2 Identify which services remain on the old carrier and which have moved to AsterLink.
- 3 Complete outstanding SIM/eSIM activation or post-port provisioning tasks when the port itself has succeeded.
- 4 Coordinate with number-transfer operations when donor/recipient completion is still pending.
- 5 Verify incoming/outgoing calls, SMS, and data after the transfer completes.

Order, Upgrade, Shipment, Installation, or Appointment Problem

KB-OPS-002

Use this procedure when a customer has a problem with an order, device shipment, upgrade, equipment delivery, technician appointment, installation appointment, or replacement order. Customers may say an order is stuck, tracking has not updated, the wrong item arrived, an appointment was missed, installation was rescheduled, equipment is missing, or the upgrade cannot proceed because the order state is incomplete. The resolution depends on the order lifecycle, inventory or shipping state, appointment scheduling, and whether the service or device has already been activated. Do not create duplicate orders until the state

of the existing order is established. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Locate the order and confirm its current fulfillment, shipment, appointment, or activation state.
- 2 Verify the service address, items, customer contact information, and any prerequisite action.
- 3 Reschedule, correct, or route the order through the supported fulfillment workflow when necessary.
- 4 Avoid duplicate replacement or shipment actions while an active order is unresolved.
- 5 Escalate lost, inconsistent, or stalled order states to the responsible operations team.

Move Service, Cancel Service, Disconnect a Line, or Transfer Service Address

KB-OPS-003

Use this procedure when a customer wants to move home service to a new address, cancel a service, disconnect a line, transfer service, or asks why a cancellation or move has not completed. Customers may need a final bill, equipment return instructions, a future disconnect date, service activation at the new address, or confirmation that old service has ended. Eligibility, equipment, final billing, contract or installment obligations, and service availability at the new location may affect the process. A move or cancellation request is an account/service-management issue rather than a technical outage unless the customer is reporting that service unexpectedly stopped before the requested date. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the requested service, effective date, service address, and authorized account holder.
- 2 Check outstanding equipment, installment, balance, and service-availability requirements.
- 3 Create or confirm the supported move, transfer, disconnect, or cancellation order.
- 4 Provide equipment return or installation instructions where required.
- 5 Confirm the final service date and expected billing treatment.

International Roaming Has No Service, Calls, Texts, or Data

KB-INT-001

Use this procedure when a customer traveling outside the home network cannot obtain roaming service or has only some services working. Customers may report no signal after arriving abroad, calls working but data failing, data roaming disabled, inability to register on a partner network, or service that worked in one country but not another. Successful roaming depends on destination coverage, plan/add-on eligibility, device compatibility, roaming settings, partner-network availability, and account provisioning. Wi-Fi service may continue to work even when cellular roaming is unavailable, and Wi-Fi Calling has separate eligibility and charging rules. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm destination, roaming eligibility, active international feature/plan, and device compatibility.
- 2 Verify roaming and cellular data settings and whether the device can register on an available partner network.
- 3 Refresh network selection/registration using supported steps and compare voice, text, and data separately.
- 4 Check for account blocks or provisioning that would prevent international service.
- 5 Escalate persistent partner-network or roaming-provisioning failures with location and service details.

Unexpected International Roaming or Travel Charges

KB-INT-002

Use this procedure when a customer disputes charges generated while traveling internationally, including data roaming, calls, texts, partner-network usage, or charges that appeared despite an international pass or travel add-on. The investigation should compare the customer's travel dates, roaming feature activation time, plan coverage, partner-network usage records, service type, and whether usage fell

outside included destinations or conditions. Delayed roaming records can appear after travel, and data use may continue through background applications unless roaming is disabled. This article is for charge review; if the customer's current problem is inability to use roaming service, use the international-roaming connectivity procedure. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Verify the customer's travel dates, international plan/add-on, activation time, and covered destinations/services.
- 2 Compare the disputed charges with roaming usage records and partner-network rating.
- 3 Separate included usage, valid out-of-plan usage, and incorrectly rated eligible usage.
- 4 Apply approved billing corrections only when account and usage evidence support them.
- 5 Escalate incomplete or inconsistent partner-network rating data for specialist review.

International Calling or Texting From the Home Country

KB-INT-003

Use this procedure when a customer is at home but cannot place an international call, cannot send an international text, receives an unexpected international rate, or needs clarification about dialing, eligibility, or an international calling feature. Customers may encounter incorrect dialing format, account blocks, plan exclusions, destination restrictions, disabled international calling, or rates that differ by country and service type. Calls to a domestic number whose user happens to be roaming abroad are normally treated differently from calls placed directly to an international number. This article concerns outbound international communication from the home network rather than the customer's own device roaming abroad. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Confirm the destination number, dialing format, and whether the customer is placing the call/text from the home network.
- 2 Verify international calling/texting eligibility, add-ons, blocks, and destination restrictions.
- 3 Check the applicable rate or included allowance before advising the customer to retry.
- 4 Correct supported account blocks or feature provisioning where appropriate.
- 5 Escalate destination-specific or rating anomalies that cannot be explained by the current plan.

Unclassified, Multi-Issue, or Unsupported Customer Complaint

KB-GEN-001

Use this procedure when a complaint does not fit a single documented issue, combines multiple independent problems, describes a new product or failure mode, lacks enough information to classify safely, or produces conflicting evidence. Examples include a customer simultaneously disputing billing and reporting a network outage, an unfamiliar device or newly launched service with no documented procedure, an unusual technical symptom that does not match known patterns, or a very short complaint such as 'nothing works' without an identifiable product. The purpose of this article is not to invent a resolution. It provides a controlled fallback so the support team can clarify the problem, separate multiple issues, preserve evidence, and route the case to the correct owner. This fallback also covers future ticket classes that are not yet represented elsewhere in the manual. The resolution steps for this issue are listed below and should be completed in order unless the observed condition requires escalation.

- 1 Identify the affected product, primary symptom, start time, business/customer impact, and troubleshooting already attempted.
- 2 Separate multiple complaints into distinct issues when they require different owners or resolution paths.
- 3 Search for the closest documented procedure without forcing the case into an unsupported category.
- 4 Collect error messages, timestamps, device/service state, and other evidence required for specialist review.
- 5 Escalate or create a new support classification when no current procedure adequately covers the case.