Brightleaf K2 Smart Kettle

The K2 is a 1.7 litre electric kettle with five temperature presets: 70, 80, 85, 90 and 100 degrees Celsius. It is rated at 2200 W and boils a full kettle in about 4 minutes.

Keep Warm Mode

Press and hold the Warm button for two seconds to keep water at the selected temperature for up to 30 minutes. The ring light turns amber while Keep Warm is active.

Safety Features

The kettle switches off automatically when it boils dry or when it is lifted from the base. Never fill above the MAX line, which is 1.7 litres.

Brightleaf Home is a fictional company. Sample document for a RAG demo.

Descaling

Descale the K2 every 4 weeks in hard water areas and every 8 weeks in soft water areas. Fill to the 1 litre mark with a mix of half water and half white vinegar, boil once, leave for one hour, then rinse three times with clean water.

Error Codes

E1 means the temperature sensor has failed; contact support. E2 means the kettle was switched on empty; let it cool for 10 minutes and refill. E3 means the base is not seated correctly; lift the kettle and place it back on the base.

App Pairing

To pair the K2 with the Brightleaf app, hold the Power and Warm buttons together for five seconds until the ring light flashes blue. Pairing works over Bluetooth only; the kettle does not connect to Wi-Fi.

Brightleaf Home is a fictional company. Sample document for a RAG demo.