ROEHAMPTON AMATEUR RADIO SOCIETY

Your licence and responsible operation

Week 2 | UK Foundation preparation

A 90-minute lesson plus 30 minutes of consolidation. Make practical decisions about call signs, supervision, messages, location and frequency-table restrictions.

By the end of the session

Explain whose licence and call sign apply, identify changes that matter, and read a table restriction before choosing a power setting. Recognise when a plan needs more permission or preparation.

Inside this pack

- Learner guide - explanations and worked situations
- Worksheet - call signs, supervision and the London table challenge
- Knowledge check - 12 original questions
- Explained answers - reasoning and focused follow-up
- Tutor guide - timings, prompts and misconceptions
- Before-you-transmit checklist - classroom reminder
- Sources and scope - references and Foundation coverage

Bring the official reference booklet

The table activities use the current EX307 Foundation reference booklet. It is linked separately, not reproduced here. Complete the worksheet and quiz before opening the answers.

This week uses discussion and role-play, not live transmitting. Read Week 1 first or be comfortable with bands, frequencies and modes. Detailed EMF and station safety are taught later.

Checked 7 October 2026 against the current RSGB and Ofcom references. Independent RARS teaching draft, not an official RSGB, Ofcom or Essex Ham publication. No second video transcript was supplied.

Week 2 learner guide

1. A licence is permission with conditions

Last week we asked what a radio can do. This week we ask what you may do with it.

Imagine RARS has a handheld radio on the table. A new member wants to try it, another suggests a frequency, and a third plans to take it abroad. Each question involves permission, not just the equipment's capabilities.

RSGB administers the examination; Ofcom issues the licence. Passing the exam does not itself authorise unsupervised transmitting. Apply for the licence through the official process, then operate within its conditions. The personal licence levels are Foundation, Intermediate and Full. [S1, S3]

Keep your licence and its associated conditions available. The personal document, conditions booklet and applicable Notice of Coordination work together; a screenshot of a frequency table is not the whole licence. [S3]

Keep the record up to date

Notify Ofcom immediately in writing if your name or recorded address changes. Confirm that your licence details remain valid at least once every five years. This is revalidation: a long-lasting licence is not something you can obtain and then forget. Breaching the conditions can lead to revocation. [S1, S2]

Campus example: moving accommodation may change your recorded address. Do not wait until the next five-year check to report an actual change. Follow Ofcom's current update process and retain confirmation.

2. Your call sign identifies the station

A call sign is the identity assigned through licensing. It is not a nickname you invent for a contact. For example, M7ABC illustrates a Foundation-style call sign; this example must not be used on air unless it is genuinely assigned to the station being operated.

Regional secondary locators

A **regional secondary locator**, or **RSL**, is inserted as the second character to indicate the UK nation or Crown Dependency where the station is operating. It describes the station's location, not the operator's nationality or home address.

Station location	RSL for an individual
England	E
Guernsey	U
Isle of Man	D
Jersey	J
Northern Ireland	I
Scotland	M
Wales	W

An RSL is optional for an ordinary Foundation call sign, but it must be correct if used. The important exception is an Intermediate call sign beginning with **2**, which must include an RSL. [S1, S2]

Using our classroom example, M7ABC can become MW7ABC when an RSL is used in Wales, or MM7ABC in Scotland. An operator who stays in Scotland should not use W merely because they normally live in Wales.

Optional suffixes

A suffix follows a slash, such as /P for portable operation. It is optional, must not obscure identification and must not be offensive. An RSL and a suffix do different jobs: one indicates the region, the other can give additional operating information. Neither extends the licence's permissions. [S1, S3]

When should you identify?

The station must be clearly identifiable at all times. Transmit its call sign as frequently as practicable, using voice or a suitable format for the mode. Do not learn an invented universal rule such as "identification is only needed every 15 minutes". [S2]

For Foundation exam preparation, practise identifying when there is a change of **frequency, mode or digital protocol, supervisor, or RSL if one is being used**. Those changes are specifically highlighted in the syllabus. Begin and finish your classroom contact practice with clear identification as good operating practice. [S1]

3. Letting someone else try the radio

Someone without a licence can operate with permission under the licensee's **direct physical supervision**. The supervisor must be able to take back control, ensure the conditions are followed and remains responsible. Being available by phone or "somewhere on campus" is not the same arrangement. [S2, S3]

Situation	Identity and conditions to use
You operate under your own valid licence	Your own call sign and your own licence conditions
A learner operates under a personal licensee's direct supervision	The supervisor's call sign and licence conditions
A licensed visitor operates independently under their own licence, with equipment permission	The visitor's call sign and licence conditions; borrowing a radio does not upgrade the licence

Example: a Foundation licensee borrows a Full licensee's radio but operates independently with their own call sign. They still have Foundation privileges. A more capable transmitter is not a more capable licence.

If a supervisor leaves and the learner has no independent authority to transmit, stop transmitting. For this week's exercise, use a disconnected microphone or ordinary conversation rather than a live station.

A society name alone is not a club licence. A **Full (Club)** licence has separate operator and supervision provisions involving an authorised Full licensee. Do not assume every member may use a club call sign independently. [S2]

4. Messages: who is the communication for?

The amateur service supports learning, technical investigation and leisure. Using it to dispatch paid work or advertise a commercial service does not fit that purpose.

In ordinary operation, communicate with other amateur stations on permitted amateur frequencies. An initial **CQ** call invites another amateur station to answer. An established **net** is a group conversation involving at least three amateurs, with communication and identification established; it is not a licence to run a public broadcasting station. [S1]

Discuss: why is "CQ, is another amateur station available for a contact?" different from announcing a shop's special offers to everyone within range?

The licence includes specific arrangements for emergencies, User Services, beacons and data stations. These are defined exceptions with conditions, not blanket permission to broadcast. For Foundation, remember that international-disaster messages may be passed internationally on behalf of unlicensed people, and that User Service use has special provisions. Do not turn a casual exercise into an invented emergency exemption. [S1, S2]

Encoding is not automatically encryption

Morse represents characters using a known code. Digital modes also represent information in particular ways. A listener needing the appropriate knowledge or decoder does not, by itself, make a transmission encrypted.

Normal amateur messages must not be encrypted to hide their meaning. The Foundation syllabus identifies exceptions for a direct request by a User Service and for amateur-satellite control. Ordinary private chat does not become an exception because an app offers an encryption button. [S1, S2]

Be considerate of a mixed-age audience. Threats and grossly offensive, obscene or menacing messages are not acceptable. A call sign identifies responsibility; it is not a shield from the rules governing message content. [S3]

5. Taking a station somewhere else

A UK amateur licence authorises operation in and over the UK, the Channel Islands and the Isle of Man, including their territorial seas, subject to its conditions. It also covers suitably registered ships or aircraft in international waters or airspace: the registration must be in the UK, Channel Islands or Isle of Man. [S2]

It does **not** itself authorise operation in another country's territory, territorial waters or airspace. For example, taking a Foundation handheld to France does not carry UK transmitting permission with it. Do not assume that the international arrangements available to Full licensees apply to Foundation.

For a ship or aircraft, permission from the captain or person currently in control is also necessary. That permission does not override frequency, power or geographical restrictions. Airborne operation is limited to permitted primary allocations and the stipulated **500 mW EIRP** limit; it is not the normal ground-operation power allowance. [S1, S2]

This is recognition-level teaching, not an instruction to transmit from an aircraft. Check the applicable conditions and operator's permission before planning any such activity.

6. Read the whole row, not just the power number

Use the current Foundation Licence Parameters in EX307 for exam practice. For a real station, use your actual licence conditions, applicable coordination requirements and current operating band plan.

Ask these questions in order:

1. Is the frequency within an allocation available to this licence?
2. Does the location or type of operation introduce a restriction?
3. What service status and sharing obligations apply?
4. What power limit applies, and how is that power defined?
5. Are the mode, occupied bandwidth and other operating conditions suitable?

The table contains several different power limits. "Foundation means 25 watts everywhere" is therefore a poor rule to learn.

Worked lookup	What the referenced table tells you
144-146 MHz, ordinary terrestrial use	Primary amateur allocation; 25 W maximum PEP
2400-2450 MHz, ordinary terrestrial use	Secondary; 2 W maximum PEP; additional ISM-sharing condition
431-432 MHz within 100 km of Charing Cross	Not available for amateur use under this allocation at that location

Roehampton example: a proposed 431.500 MHz transmission falls inside that restricted range, and Roehampton is within the stated London radius. Reducing the power to 1 W does not remove a location exclusion. The lesson is a paper exercise, not a suggested transmission. [S2, S4]

PEP, **ERP** and **EIRP** are different ways of specifying power. Copy the unit and qualifier along with the number. Where ERP or EIRP is specified, the transmitter's displayed output alone is not sufficient because the antenna system matters. Antenna and power calculations return in later weeks.

Primary status does not necessarily mean exclusive use. Secondary services must protect primary services and cannot demand protection from their legitimate operation. All amateur operation must avoid undue interference.

7. Responsibility continues while you operate

A licensed operator is responsible for avoiding undue interference. If your activity appears to be causing a problem, pause the activity and investigate; do not simply increase power to overcome the complaint.

A person authorised by Ofcom can inspect the licence and equipment and may require modification, restriction or closedown. They may also require a log of specified details for a specified period and in a specified form. Keeping a personal hobby log is useful, but is different from such a requirement. [S1, S2]

EMF exposure, electrical safety and safe antenna installation still matter even when a frequency is permitted. This week flags those duties; the detailed EMF learning point and practical safety checks are scheduled for Week 6. Do not treat this lesson alone as approval for a live demonstration.

8. Put the rules to work

Before a contact, explain **who is operating, under whose licence, from where, on which frequency, with what settings, and for what purpose**. If any answer is uncertain, resolve it before transmitting.

Complete the worksheet and quiz. For every corrected answer, write the reasoning rather than memorising a letter. Bring one question about an unfamiliar licence-table row to the next session.

RARS teaching draft v0.1 | Checked 7 October 2026. Source IDs refer to sources and scope.

Week 2 classroom worksheet

Name: _____ Date: _____

Use the learner guide and the current EX307 Foundation reference booklet. All situations below are discussion exercises. Do not transmit the example call signs or frequencies.

Activity A - Identify the change

An imaginary Foundation station uses the example call sign M7ABC.

1. It operates in Wales and chooses to include an RSL. Write the resulting call sign: _____.
2. It moves to Scotland and keeps using an RSL. What should change? _____.
3. Must an ordinary Foundation call sign always include an RSL? _____.
4. What is the exception for Intermediate call signs beginning with 2? _____.
5. Does adding /P extend the frequency or power permissions? _____.

A licensee changes their recorded address this month. Should they wait for the five-year revalidation date? Explain the action needed.

_____

Activity B - Whose responsibility?

Work in pairs. For each situation, identify the call sign/conditions that apply and the next action.

Situation	Your reasoning
An unlicensed learner operates under a personal licensee's direct physical supervision.	
The supervisor leaves the room and offers to answer questions by phone.	
A Foundation visitor borrows a Full licensee's radio and operates independently with their own call sign.	

During a supervised contact the supervising licensee changes. What identification action should be taken?

_____

Activity C - Purpose, message and place

For each suggestion, state the relevant rule rather than only saying yes or no.

1. Send an initial CQ call to find another amateur to talk to.

2. Send advertisements for a paid repair business on an amateur channel.

3. Use ordinary Morse, then claim that every coded message is forbidden encryption.

4. Operate a UK Foundation station while visiting France, without checking any other permission.

5. Transmit from a permitted aircraft at the usual ground-operation power just because the captain agreed.

Notes: _____

_____

Activity D - The London table challenge

Use EX307. Assume ordinary terrestrial operation and a Foundation licence. Finding a row is only one part of the decision: consider all other conditions before any real operation.

Proposed frequency and place	Table row	Status	Power and qualifier / restriction
145.500 MHz at Roehampton			
2401 MHz at Roehampton			
431.500 MHz at Roehampton			

Why does reducing power not solve the third case?

_____

An authorised Ofcom representative requires a log for a stated period. Is a claim that "amateur logs are optional" a reason to ignore that instruction? Explain.

_____

Exit note

One rule I can explain: _____

One decision I still need help with: _____

Review with the answer key after completing the activities.

Week 2 knowledge check

12 original RARS questions | About 8 minutes

Choose one answer per question. Use the current EX307 booklet for Questions 9 and 10. This is a weekly learning check, not an official exam paper.

1. Your recorded address changes. Which response follows the licence-maintenance requirements?

A. Wait until the next five-year check.
B. Update only a public call-sign website.
C. Notify Ofcom immediately in writing, and also keep up with periodic revalidation.
D. No action is needed once the exam has been passed.

2. Which statement about regional secondary locators is correct?

A. They are normally optional, but mandatory for Intermediate call signs beginning with 2.
B. They are compulsory for every Foundation transmission.
C. They always follow the operator's home address.
D. They are optional only for Full licensees.

3. During an ongoing contact, a station changes from FM to a different mode. What is the Foundation syllabus's identification expectation?

A. Identify only when the operator also changes location.
B. Identify only if another station asks.
C. Wait for a fixed 15-minute interval regardless of the change.
D. Identify the station again when the mode changes.

4. An unlicensed learner operates under a personal licensee's direct supervision. Which applies?

A. The learner can invent a temporary call sign.
B. The supervisor's call sign and licence conditions apply, and the supervisor remains responsible.
C. Club membership gives the learner Full privileges.
D. The radio's maximum advertised power sets the permitted limit.

5. Which use falls outside the normal non-commercial purpose of an amateur licence?

A. Comparing reception reports
B. Dispatching a company's paid delivery jobs
C. Investigating an antenna
D. A hobby conversation with another amateur

6. Which is a permitted initial invitation for another amateur station to establish contact?

A. A commercial advertising broadcast
B. An unlicensed public music service
C. A deliberately anonymous transmission
D. A properly identified CQ call within the applicable operating conditions

7. Why is ordinary Morse not automatically prohibited encryption?

A. It is a known code representing characters, not inherently a method of concealing meaning.
B. Every amateur message is permitted to be encrypted.
C. Morse cannot carry words.
D. Licence rules apply only to speech.

8. A Foundation licensee takes a radio to France. What does the UK Foundation licence itself authorise there?

A. Unrestricted use of all UK amateur bands
B. Any transmission below 25 W
C. It does not itself authorise operation in another country's territory.
D. Any transmission with /P added

9. Use EX307. A Foundation operator proposes 431.500 MHz from Roehampton, within 100 km of Charing Cross. Which conclusion is correct?

A. It is always available at 25 W.
B. It becomes available by selecting FM.
C. The location restriction makes that allocation unavailable there; reducing power does not remove it.
D. It is available whenever the frequency sounds quiet.

10. Use EX307. What maximum PEP is listed for Foundation ordinary terrestrial operation in 2400-2450 MHz?

A. 100 W
B. 2 W
C. 10 W
D. 25 W

11. An Ofcom-authorised person requires a specified operating log. Which response is correct?

A. Keep any informal notes instead of the specified record.
B. Ignore the instruction because hobby logs are usually voluntary.
C. Keep a log only if the instruction also closes the station.
D. Keep the record in the required form and for the required period.

12. For permitted airborne amateur operation, which statement is correct?

A. Captain/person-in-control permission is needed, and primary-allocation and 500 mW EIRP restrictions also apply.
B. The normal terrestrial power limit always applies.
C. A Foundation licence permits operation over every country.
D. An optional suffix removes the airborne power limit.

Your choices

1: ____ 2: ____ 3: ____ 4: ____ 5: ____ 6: ____

7: ____ 8: ____ 9: ____ 10: ____ 11: ____ 12: ____

Mark your answers using the explained key. Note any correct answers that were guesses.

Week 2 explained answers

Try the activities before reading this file. These are explanations for RARS exercises, not official exam marking instructions.

Quiz answers

Question	Answer	Why
1	C	An actual name/address change must be notified promptly as required; the five-year confirmation requirement is not permission to delay it.
2	A	RSLs identify station location. They are generally optional, with the specified exception for 2-series Intermediate call signs.
3	D	A mode change is one of the identification triggers highlighted by the Foundation syllabus.
4	B	Supervised operation uses the supervisor's call sign and conditions; responsibility does not transfer to the beginner.
5	B	Paid delivery dispatch is business traffic, not amateur self-training or leisure.
6	D	CQ is an initial invitation to establish amateur communication; it is not a general broadcasting permission.
7	A	A known representation of characters is different from encryption used to obscure meaning.
8	C	UK Foundation permission does not automatically extend to another country's territory.
9	C	431.500 MHz falls inside 431-432 MHz, with its stated London-area exclusion.
10	B	That row specifies 2 W, not the 25 W found in many other Foundation rows.
11	D	The specific instruction creates a requirement to keep the stated record.
12	A	Permission and applicable location, allocation and power conditions must all be satisfied. The power qualifier is EIRP.

RARS teaching target: 10/12, plus an explanation of corrected mistakes. This is not the official pass mark or a full-exam readiness assessment. Revisit any uncertainty about supervision, geographical authority or the London restriction regardless of total score.

Worksheet answers

Activity A - Identify the change

1. MW7ABC, as a classroom illustration only.
2. Use the Scotland RSL M if continuing to include an RSL: MM7ABC.
3. No. It is optional for an ordinary Foundation call sign, but must be accurate if used.
4. A 2-series Intermediate call sign must include the appropriate RSL.
5. No. A suffix changes neither power nor frequency permission.

Notify Ofcom immediately in writing of the recorded-address change. Periodic revalidation and reporting an actual change are separate responsibilities.

Activity B - Whose responsibility?

- The unlicensed learner uses the supervisor's call sign and conditions, with permission and direct physical supervision.

- If that supervision is no longer present, stop the unlicensed learner's transmitting. Telephone availability does not replace the required arrangement.
- An independently operating Foundation visitor remains within Foundation conditions and uses their own assigned call sign, even on borrowed Full-level equipment.
- When the supervising licensee changes, identify using the new supervisor's call sign and apply that supervisor's conditions. Complete the handover before continuing.

Activity C - Purpose, message and place

1. An initial CQ call is allowed to seek a contact, provided the station is properly identified and all other conditions are met.
2. Commercial advertising is outside the amateur licence's purpose.
3. Morse is a known code, not inherently encryption. The claim that every coded message is forbidden is wrong. Normal amateur encryption intended to hide meaning is restricted, with specific exceptions explained in the guide.
4. A UK Foundation licence does not by itself give authority to transmit from France. Check the foreign authority's arrangements before operating.
5. Captain's permission does not remove airborne restrictions: use only permitted primary allocations, the stipulated 500 mW EIRP limit and the allowed geographical context.

Activity D - London table challenge

Proposed frequency	Row	Status	Result of the lookup
145.500 MHz	144-146 MHz	Primary	25 W maximum PEP for ordinary terrestrial operation
2401 MHz	2400-2450 MHz	Secondary	2 W maximum PEP; accept interference from ISM users
431.500 MHz	431-432 MHz	Secondary	Not available within the specified 100 km London radius

A geographical exclusion is not merely a power cap. Lowering the power does not make the third example available. A valid frequency-row lookup also does not settle every other operating requirement.

The Ofcom-authorised logging instruction must be followed. The fact that a voluntary hobby log is otherwise optional is not a reason to refuse it.

Focused follow-up

- If RSLs were confusing, explain the difference between the station's present location and the operator's home address.
- If supervision was confusing, rehearse a handover without a working transmitter: say whose call sign and limits apply at each stage.
- If the table was confusing, read the restriction column aloud before reading the power column.
- If identification was confusing, explain why clear identification is an ongoing responsibility, not a single fixed timer.

The reference-sensitive answers were checked against the current sources listed in sources.md on 7 October 2026. Recheck them before a new cohort.

Week 2 tutor guide

Your licence and responsible operation | 90 minutes

The aim is to turn rules into sensible decisions. Use discussion and role-play, not live transmitting. Read the learner guide and source notes before delivery.

Prepare

- Provide the current EX307 reference booklet, worksheet and quiz.
- Have the current Ofcom conditions available for questions; the course summary is not the licence itself.
- Put the seven individual RSLs on a board or printed cards.
- Use a disconnected microphone or ordinary spoken role-play for supervision examples.
- Label all sample call signs as illustrations. Do not invent an RARS club call sign or assume the society already holds a Full (Club) licence.

Session plan

Minutes	Topic	Learner activity
0-8	Retrieve Week 1 ideas	Explain frequency, band and mode; recall the non-commercial purpose.
8-20	Licence upkeep and RSLs	Complete Activity A; explain location versus home address.
20-32	Identification and supervision	Complete Activity B with a mock supervisor handover.
32-42	Messages and encoding	Discuss the first three situations in Activity C.
42-47	Break	Invite quiet questions.
47-57	Geographical limits	Finish Activity C; separate captain's permission from licence conditions.
57-72	Table reading and responsibilities	Complete Activity D and discuss the logging instruction.
72-83	Knowledge check	Allow about eight minutes for the quiz, then collect uncertain answers.
83-90	Explain and consolidate	Review high-impact mistakes and set homework.

If the group needs longer on table reading, review the remaining quiz answers as homework. Do not squeeze an unplanned live contact into the remaining time.

Prompts and likely misconceptions

"I passed, so I can transmit." Ask which organisation issues the licence. Have learners say the separate steps aloud.

"I only update my address every five years." Put a house move and periodic revalidation on different cards. Ask what triggers each action.

"The operator lives in Wales, so W always applies." Move the imaginary station to Scotland. The optional RSL follows the operating location.

"I borrowed a better radio, so I have more power." Change the equipment card but leave the operator's licence card in place. The radio does not upgrade the licence.

"The supervisor is reachable by phone." Ask whether they can physically take back control. Stop the mock contact and rehearse a proper handover.

"Every digital signal is encrypted." Separate representation/encoding from intentional concealment of meaning. Avoid claiming that every digital system is suitable for amateur use.

"25 W is the Foundation limit everywhere." Compare 144-146 MHz, 2400-2450 MHz and the restricted London row. Require the full qualifier, not just the number.

"A quiet channel is permission." Ask what a silent receiver tells you about the licence. It cannot remove a restriction.

Assessment and scope

Use 10/12 plus explained corrections as a RARS learning target, not an official threshold. The worksheet checks additional reasoning that a twelve-question quiz cannot cover on its own.

The source map records licensing points taught and remaining coverage. The detailed EMF topic is deliberately deferred to Week 6 and must be taught before claiming full Section 1 coverage. Identification and message handling should be practised again in Week 7.

Homework - 30 minutes

- 10 minutes: correct the quiz and explain each correction.
- 10 minutes: reproduce the seven RSLs, then check and correct them.
- 5 minutes: repeat the three table lookups and read each restriction aloud.
- 5 minutes: use the station checklist to explain a hypothetical contact to a partner.

Ask the learner to return with one question, especially if a licence phrase is unfamiliar. Offer verbal explanations of the worksheet as well as written answers.

Before you transmit

RARS classroom reminder | Week 2

This is a prompt for checking the applicable rules, not a replacement for the licence or a complete live-station safety assessment.

Check	Ask yourself
Operator	Who is operating, and what valid licence or authorised supervision covers them?
Identity	Whose call sign applies? Is any RSL correct for the station's location?
Place	Is this location within the licence's authority? Do ship/aircraft permissions or restrictions apply?
Frequency	Is the full transmitted signal within an allowed allocation? Have I read the row's restrictions?
Power	What limit applies here, and is it expressed as PEP, ERP or EIRP?
Purpose	Is the communication appropriate for amateur radio? Who is the intended recipient?
Settings	Are mode, bandwidth and operating arrangements suitable?
Sharing	Have I listened and checked the applicable band plan and coordination requirements?
Safety	Have relevant electrical, antenna and EMF checks been completed?
Control	Can operation be stopped promptly? If supervised, is the responsible supervisor present?

During the contact, keep the station identifiable and remain alert to interference. If supervision, settings or circumstances change, reassess before continuing.

If you cannot explain a check, pause and ask. A frequency that sounds quiet, a low power setting or membership of a society is not sufficient permission on its own.

Use this checklist for role-play this week. Detailed technical and safety preparation continues in later modules.

Checked 7 October 2026. See sources and scope.

Sources, coverage and review notes

Checked: 7 October 2026. **Module:** teaching draft v0.1.

Source register

ID	Primary reference	Used for
S1	RSGB v1.6b, March 2026 revision	Foundation Section 1 and exam identification expectations
S2	Ofcom licence conditions OFW611	Conditions 1, 2, 4, 6, 7 and 8; Schedule 1 Table A
S3	Ofcom licensee guidance, 14 October 2025	Licence documents, direct physical supervision, RSLs and suffixes
S4	EX307, 22 January 2026	Foundation parameter-table exercises

Current entry points: RSGB specification, RSGB exam forms, and Ofcom amateur information. Check these before reusing dated PDFs.

Foundation coverage map

Items refer to the Foundation column, inspected separately from Intermediate and Full. Teaching a point does not establish learner mastery.

Point	Treatment in Week 2	Practice / follow-up
1A1	Purpose and geographical authority	Activity C; Q5, Q8, Q12
1A2	Levels, RSLs, suffixes and ship/aircraft restrictions	Activity A/C; Q2, Q12
1A3	Name/address changes, five-year confirmation and revocation	Activity A; Q1
1A4	Identification and changes highlighted for the exam	Activity B; Q3; revisit Week 7
1B1	Direct supervision and identity; User Service exception introduced	Activity B; Q4
1C1	Amateur messages, CQ, nets and disaster exception	Activity C; Q5/Q6; revisit Week 7
1C2	Encryption and its specified exceptions	Activity C; Q7
1D1	Interference, inspection, modification, restriction and closedown	Discussion; detailed EMC work in Week 6
1F1	A log when required by an authorised Ofcom person	Activity D; Q11
1G1	Awareness only; not completed	EMF thresholds, people protected and records belong in Week 6
1H1	Status, varied limits and geographical restrictions	Activity D; Q9/Q10; further rows still need practice

There is no Foundation learning point under the empty 1E1 column in this revision.
Remote/unattended station construction and special-station operation are not taught by this module.

Editorial decisions

- No second Essex Ham transcript was supplied. This is original RARS teaching based directly on the official references, not a claim to have watched or transcribed another video.
- Call signs in the exercises are illustrative. They must not be adopted as actual transmitting identities.
- Identification examples distinguish the general licence obligation from specific changes highlighted in the exam syllabus. No fixed 15-minute rule has been invented.
- The guidance document's section 3.4 says "ERP" for the airborne 500 mW figure, while the formal OFW611 Schedule 1 Table A and EX307 specify **EIRP**. The lesson follows the formal conditions and exam reference: EIRP. These qualifiers are not interchangeable.
- The 431-432 MHz restriction is taught as a location exclusion, not a lower power allowance. Roehampton falls within the 100 km radius around Charing Cross.
- The three table examples do not constitute an authorisation for a live activity. The classroom session is non-transmitting.
- Quiz questions, scenarios and the station checklist are newly authored, not copied examination questions. Official documents are linked rather than redistributed in the pack.

Tutor review before delivery

Check the reference versions, work every table exercise, and read all model answers. Revisit partial items before declaring licensing coverage complete. For actual station operation, the current licence and applicable coordination requirements control; a course summary or specimen exam band plan is not a substitute.