Time series: ARMA forecasting

Andrey Pepelyshev

MA3508, MA4508, MAT508
Lecture notes 12

MATHS, Cardiff
Spring semester, 2026

The homework is provided on the last slide

Forecasting ARMA processes

Since an ARMA process is a stationary process, we can apply the algorithm of forecasting stationary processes for forecasting ARMA processes, see Lecture 6.

Let $x_1, \ldots, x_n$ be a time series, h be a positive integer and $R(k)$ be a given covariance function.

1. Compute $\hat{\mu} = (x_1 + x_2 + \ldots + x_n)/n$.
2. Construct the time series $y_i = x_i - \hat{\mu},\ i = 1, \ldots, n$.
3. Compute the matrix $\Gamma = \Big(R(i-j)\Big)_{i,j=1}^{n}$ and the vector $b_h = (R(h+n-1), \ldots, R(h+1), R(h))^T$.
4. Compute the vector $\gamma_h = \Gamma^{-1} b_h$.
5. Compute $\hat{y}_{n+h} = \gamma_h^T Y$, where $Y = (y_1, y_2, \ldots, y_n)^T$.
6. Compute $\hat{x}_{n+h} = \hat{\mu} + \hat{y}_{n+h}$ and $\hat{\sigma}^2_{n+h;x} = R(0) - b_h^T \Gamma^{-1} b_h$.

Forecasting AR(1) processes

Task. Let $x_1, \ldots, x_n$ be a time series from an AR(1) process $x_t = ax_{t-1} + \epsilon_t$. Compute h-step ahead forecast.

From slide 5 of Lecture 9, we have

$$R(k) = \sigma^2 \frac{a^{|k|}}{1 - a^2}.$$

Then the equation $\Gamma\gamma_h = b_h$ has the form

The solution is

Forecasting AR(1) processes

Now the predictor $\hat{x}_{n+h}$ has the form

$$\hat{x}_{n+h} = (x_1, \ldots, x_n)^T \gamma_h = 0 \cdot x_1 + 0 \cdot x_{n-1} + a^h x_n = a^h x_n.$$

and the variance of the predictor is

$$\hat{\sigma}^2_{n+h;x} = R(0) - b_h^T \Gamma^{-1} b_h = \frac{\sigma^2}{1-a^2} - a^{2h} \frac{\sigma^2}{1-a^2} = \sigma^2 \frac{1-a^{2h}}{1-a^2}.$$

Theorem. For a time series $x_1, \ldots, x_n$ from an AR(1) process $x_t = a x_{t-1} + \epsilon_t$, the h-step ahead predictor is

$$\hat{x}_{n+h} = a^h x_n,$$

and the MSE of $\hat{x}_{n+h}$ is $\mathrm{MSE}(\hat{x}_{n+h}) = \sigma^2 \frac{1-a^{2h}}{1-a^2}$. If ϵ_t is Gaussian, then the prediction bound for x_{n+h} is

$$\left(\hat{x}_{n+h} - z_{1-\alpha/2} \sigma \sqrt{\frac{1-a^{2h}}{1-a^2}}, \hat{x}_{n+h} + z_{1-\alpha/2} \sigma \sqrt{\frac{1-a^{2h}}{1-a^2}} \right).$$

Example on forecasting AR(1)

Task. Let $x_1, \ldots, x_{100}$ be a time series from an AR(1) process $x_t - \mu = a(x_{t-1} - \mu) + \epsilon_t$ with $\mu = 9$, $a = 0.6$, $\sigma^2 = 0.1^2$; and let $x_{100} = 8.9$. Compute the predictors $\hat{x}_{101}, \hat{x}_{102}, \hat{x}_{103}$ and prediction bounds.

The given process is causal since $|a| < 1$. Then we have

$\hat{x}_{101} = \mu + a\,(x_{100} - \mu) =$

$\hat{x}_{102} = \mu + a^2(x_{100} - \mu) =$

$\hat{x}_{103} = \mu + a^3(x_{100} - \mu) =$.

The prediction bounds for x_{101}, x_{102}, x_{103} are

x_{101} : $($ $\quad - z_{1-\alpha/2}0.1 \quad ,$ $\quad + z_{1-\alpha/2}0.1)$

x_{102} : $\left(\quad - z_{1-\alpha/2}0.1\sqrt{\frac{1-0.6^4}{1-0.6^2}}, \quad + z_{1-\alpha/2}0.1\sqrt{\frac{1-0.6^4}{1-0.6^2}} \right)$

x_{103} : $\left(\quad -z_{1-\alpha/2}0.1\sqrt{\frac{1-0.6^6}{1-0.6^2}}, \quad +z_{1-\alpha/2}0.1\sqrt{\frac{1-0.6^6}{1-0.6^2}} \right)$

Forecasting a causal ARMA process

Let $x_1, \ldots, x_n$ be a time series from a causal ARMA(p, q) process $a(B)x_t = b(B)\epsilon_t$, i.e.

$$x_t - a_1 x_{t-1} - \ldots - a_p x_{t-p} = \epsilon_t + b_1 \epsilon_{t-1} + \ldots + b_q \epsilon_{t-q}.$$

Since x_t is causal, there are the coefficients $c_0, c_1, c_2, \ldots$ such that elements of the time series can be represented as

$$x_n = \sum_{i=0}^{\infty} c_i \epsilon_{n-i}, \quad j = 1, 2, 3, \ldots,$$

and $c_0 = 1$, see slide 7 of Lecture 8 and slide 4 of Lecture 9. Now we want to construct the predictor $\hat{x}_{n+h}$ in the form

$$\hat{x}_{n+h} = \sum_{j=0}^{\infty} \tau_{h+j} \epsilon_{n-j}$$

where optimal τ_{h+i}, $i = 0, 1, 2, \ldots$ minimize the MSE.

MSE of predictor for ARMA process

The mean square error (MSE) of $\hat{x}_{n+h}$ is

$$\mathbf{E}(x_{n+h}-\hat{x}_{n+h})^2 = \mathbf{E}(\sum_{i=0}^{\infty} c_i \epsilon_{n+h-i} - \sum_{j=0}^{\infty} \tau_{h+j} \epsilon_{n-j})^2$$

$$=$$

$$=$$

$$=$$

$$=$$

The minimum of MSE is attained for $\tau_j = c_j$, $j = h, h+1, \ldots$.

Forecasting of ARMA processes via MA

Theorem. For a time series $x_1, \ldots, x_n$ from a causal ARMA(p, q) process $a(B)x_t = b(B)\epsilon_t$, which can be written as $x_j = \sum_{i=0}^{\infty} c_i \epsilon_{j-i}$, where ϵ_t is a white noise process with variance σ^2, the h-step ahead predictor is

$$\hat{x}_{n+h} = \sum_{i=0}^{\infty} c_{i+h} \epsilon_{n-i},$$

and the MSE is $\mathrm{MSE}(\hat{x}_{n+h}) = \sigma^2 \sum_{i=0}^{h-1} c_i^2$. If ϵ_t is Gaussian, then the prediction bound for x_{n+h} is

$$\left(\hat{x}_{n+h} - z_{1-\alpha/2}\sigma \sqrt{\sum_{i=0}^{h-1} c_i^2}, \hat{x}_{n+h} + z_{1-\alpha/2}\sigma \sqrt{\sum_{i=0}^{h-1} c_i^2} \right).$$

Forecasting AR(p) process via MA

Let $x_1, \ldots, x_n$ be a time series from a causal AR(p) process $x_t = a_1 x_{t-1} + \ldots + a_p x_{t-p} + \epsilon_t$, which can be written in the MA form $x_j = \sum_{i=0}^{\infty} c_i \epsilon_{j-i}$, $c_0 = 1$.

From the previous slide, for $h = 1$, we have

Forecasting/predictor of AR process

Theorem. For a time series $x_1, \ldots, x_n$ from a causal AR(p) process $a(B)x_t = \epsilon_t$, which can be written as $x_j = \sum_{i=0}^{\infty} c_i \epsilon_{j-i}$, where ϵ_t is a white noise process with variance σ^2,
the h-step ahead predictor is

$$\hat{x}_{n+h} = \begin{cases} \sum_{j=1}^{h-1} a_j \hat{x}_{n-j+h} + \sum_{j=h}^{p} a_j x_{n-j+h} & h = 1, 2, \ldots, p \\ \sum_{j=1}^{p} a_j \hat{x}_{n-j+h} & h = p+1, p+2, \ldots, \end{cases}$$

and the MSE is $\mathrm{MSE}(\hat{x}_{n+h}) = \sigma^2 \sum_{i=0}^{h-1} c_i^2$.

Example on forecasting AR(2)

Task. Let 46,45,48,46 be a time series from an AR(2) process $x_t - 47 = 1.3(x_{t-1} - 47) - 0.7(x_{t-2} - 47) + \epsilon_t$. Compute the predictors $\hat{x}_5, \hat{x}_6, \hat{x}_7, \hat{x}_8$.

The given AR(2) process is causal since coefficients $a_1 = 1.3$ and $a_2 = -0.7$ satisfy $a_2 + a_1 < 1$, $a_2 - a_1 < 1$, $|a_2| < 1$, see slide 9 of Lecture 9.

Since the mean $\mu = 47$ is given, we find $y_1 = x_1 - 47 = -1$, $y_2 = 45 - 47 = -2$, $y_3 = 1$, $y_4 = -1$. Then we have

$\hat{y}_5 = 1.3y_4 - 0.7y_3 =$

$\hat{y}_6 = 1.3\hat{y}_5 - 0.7y_4 =$

$\hat{y}_7 = 1.3\hat{y}_6 - 0.7\hat{y}_5 =$

$\hat{y}_8 = 1.3\hat{y}_7 - 0.7\hat{y}_6 =$

Finally, $\hat{x}_5 = \hat{y}_5 + 47 =$.

R code for forecasting AR(2)

Task. Let 46,45,48,46 be a time series. Assume that an AR(2) process $x_t - 47 = 1.3(x_{t-1} - 47) - 0.7(x_{t-2} - 47) + \epsilon_t$ is appropriate for forecasting. Depict the time series and the predictors $\hat{x}_5, \ldots, \hat{x}_{40}$.

```
® x=c(46,45,48,46); n=length(x);
a=c(1.3,-0.7); p=length(a);
mu=47; h=40-n;
x=c(x,rep(0,h));
for(i in (1:h))
  x[n+i]=mu+sum(a*(x[seq(n+i-1,n+i-p,by=-1)]-mu));
plot((1:(n+h)),x,pch=19,main="time series (blue) and
forecast")
points((1:n),x[1:n],pch=19,col="blue")
```

Learning Lecture 12 with AI

Try these prompts.

Conceptual Mastery

Prompt: "Explain the intuition behind the h-step ahead predictor $\hat{x}_{n+h} = a^h x_n$ for an AR(1) process. Why does the forecast decay toward the mean as h increases?"

Algorithmic Practice

Prompt: "Walk me through the recursive forecasting algorithm for an AR(2) process. If $y_n = -1$ and $y_{n-1} = 1$ with $a_1 = 1.3, a_2 = -0.7$, show me how to calculate $\hat{y}_{n+1}$ and $\hat{y}_{n+2}$ step-by-step."

Coding with R

Task: Ask an AI to explain how the R loop on slide 12 handles indices to ensure it uses previous forecasts ($\hat{x}$) when the lag exceeds the available data points (n).