PETTRAKR CRATE ATTACHMENT - FULL GUIDE



YOU WILL NEED

- 1 x PetTrakr Device
- 1 x Cordless Drill
- 1 x 4mm Drillbit
- 1 x PetTrakr Positioning Guide
- 2 x 3.6mm x 280mm Cable Ties
- 1 x Marker Pen




A NOTE ON CHARGING

Plug in the device the day before departure and keep it charging. <u>Unplug and secure</u> the device no earlier than 30 minutes before placing the pet in the crate.

POSITION THE DEVICE ON THE CRATE

- Use the grid to identify and mark the correct hole on the back of the crate.
 Insert the camera barrel into marked PPTO/PPTO
- hole and position the device vertically.





MARK THE DEVICE'S POSITION

- **3.** Hold the device vertically with the camera barrel in the marked hole in place.
- 4. Draw a line down each side of the device





MARK THE POSITION OF HOLES TO DRILL

- **5.** Place the PetTrakr Postioning Guide between the marked lines with the bottom of the guide on the plastic rim of the crate.
- **6.** Follow the arrows for the appropriate crate and mark four holes, two on each side.





DRILL Y X HOLES + PREPARE CABLE TIES

- 7. Drill a hole at each of the four marked positions.
- **8.** Thread two 3.6mm x 280mm cable ties through each pair of drilled holes horizontally from right to left.

Put the device back on charge.





PetTrakr



PETTRAKE CRATE ATTACHMENT - FULL GUIDE

PREPARE THE RETURN SATCHEL

- **9.** Ensure the return satchel has the shipping label on the front
- **10.** Ensure that the customs documents are on the back.





ATTACH THE DOCULOPE

- **11.** Fold and place the satchel into the adhesive doculope labeled 'Att: Receiving agent PetTrakr return'.
- **12.** Stick the doculope to the crate's shoulder, remove the sealing strip, and seal it.





CONTINUE STEP 13 NO LESS THAN 30 MINUTES BEFORE PLACING PET INTO CRATE.

SECURE DEVICE TO CRATE

- **13.** Position the device with the camera barrel in the privously marked hold and feed the cable ties through the channel on the device.
- **14.** Pull the cable ties tight to secure the device firmly against the crate, ensure no slack inside the crate. Trim the ends of the cable ties





GOOD TO GO

- **15.** The device is now ready to go.
- 16. Have a cup of tea.





GETTING HELP

If you have any difficulties or have any questions please call Gus Currie on xxxxx

PetTrakr

