

Dundee Terrace

Circuit Chart – CU Apartment



Issue Record

Revision	Section No.	By	Checked By	Date
01	Issued for Tender	KB	CS	29.08.25
02	Issued for Tender	KB	CS	16.09.25
03	Issued for tender	KB	CS	29.09.25

Job Number	423.033.00
Document Reference	DUN-RYB-XX-XX-SP-E-CU



The details below are included for pricing purposes only – Final Circuit Charts to be developed by Contractor on completion of installation.

Board Identity: Consumer Unit (General Apartment) No of Ways: 8 DB Incomer Device Rating/Type: 63A Switched Disconnecter			Ring	Radial	Protection (At Design Stage)			Conductor (At Design Stage)			
Way	Phase	Circuit Description			CPD Rating(A)	CPD Type	RCD Rating (mA)	Phase Conductor (mm ²)	Sep CPC (mm ²)	Cable Type	Installation Method
1	L1	Pod		✓	10A	MCB (C)	30mA	1.5	Integral	LSZH Twin & Earth	Clipped Direct
2	L1	Lighting		✓	6A	MCB (C)	30mA	1.5	Integral	LSZH Twin & Earth	Clipped Direct
3	L1	Mech (MEV & Panel Heater)		✓	20A	MCB (C)	n/a	4	Integral	LSZH Twin & Earth	Clipped Direct
4	L1	Bedroom Ring, Sockets / Fridge, Extract Fan /	✓		32A	MCB (C) +AFDD	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
5	L1	Hob		✓	20A	MCB	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
6	L1	Oven		✓	20A	MCB	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
7	L1	Spare									
8	L1	Spare									

Board Identity: Consumer Unit (Cluster Bedroom) No of Ways: 8 DB Incomer Device Rating/Type: 63A Switched Disconnecter			Ring	Radial	Protection (At Design Stage)			Conductor (At Design Stage)			
Way	Phase	Circuit Description			CPD Rating(A)	CPD Type	RCD Rating (mA)	Phase Conducto r (mm ²)	Sep CPC (mm ²)	Cable Type	Installation Method
1	L1	Pod		✓	10A	MCB (C)	30mA	1.5	Integral	LSZH Twin & Earth	Clipped Direct
2	L1	Lighting		✓	6A	MCB (C)	30mA	1.5	Integral	LSZH Twin & Earth	Clipped Direct
3	L1	Mech (MEV & Panel Heater)		✓	20A	MCB (C)	n/a	4	Integral	LSZH Twin & Earth	Clipped Direct
4	L1	Bedroom Ring, Sockets	✓		32A	MCB (C) +AFDD	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
5	L1	Spare									
6	L1	Spare									
7	L1	Spare									
8	L1	Spare									

Board Identity: Consumer Unit (Cluster Kitchen) No of Ways: 8 DB Incomer Device Rating/Type: 63A Switched Disconnecter			Ring	Radial	Protection (At Design Stage)			Conductor (At Design Stage)			
Way	Phase	Circuit Description			CPD Rating(A)	CPD Type	RCD Rating (mA)	Phase Conductor (mm ²)	Sep CPC (mm ²)	Cable Type	Installation Method
1	L1	Spare									
2	L1	Lighting		✓	6A	MCB (C)	30mA	1.5	Integral	LSZH Twin & Earth	Clipped Direct
3	L1	Panel Heater		✓	20A	MCB (C)	n/a	4	Integral	LSZH Twin & Earth	Clipped Direct
4	L1	Kitchen Ring, Sockets / Fridge, Extract Fan	✓		32A	MCB (C) +AFDD	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
5	L1	Hob		✓	32A	MCB	30mA	6	Integral	LSZH Twin & Earth	Clipped Direct
6	L1	Oven		✓	20A	MCB	30mA	4	Integral	LSZH Twin & Earth	Clipped Direct
7	L1	Spare									
8	L1	Spare									

Note * for second floor kitchen, allow for 10A RCBO to feed LED strip lighting within the brickwork, via 2.5mm T+E