




syncSuite

Max Package and Max for Live devices for complex multimedia synchronization

Design and programming: Agustín Issidoro

Installation and Contents

If you're reading this document, it means you've already probably downloaded and unzipped the package successfully.



The **/ableton-project** can be kept where it is most convenient for you. It contains several Ableton Live Sessions with examples as well as some linked media.

The **/m4l-devices** contains all the Max4Live devices. This you can also keep where it is most convenient to you, although it is recommended to keep all your Max4Live devices together.


The **/max-package** folder needs to be copied inside Max's **/Packages** folder. Usually, this is:

/Documents/Max 9/Packages

Package Usage

This document will cover the basic usage of the Max4Live devices. You can find comprehensive information about the Max Package in the objects' help files as well as in the tutorial series.

CueSync




This device allows gets all markers in your Session and allow to easily and rapidly jump between them. Useful when needing to jump through cues.

- 1 Add a CueSync device to your Session.
- 2 Add Markers to your Session.
- 3 Double click on any item in the list.
- 4 You can map the "Next" and "Previous" buttons for more intuitive control.

Tutorial:

/ableton-project/syncSuite-tutorial-cuesync.als

LiveSync



This device allows to send Transport information from your Live Session as well as receiving Transport and Cue controls via UDP.


Very useful for cueing Live from external software as well as connecting Transport information (bar and beat) with the Score devices.

- 1 Add a LiveSync device to a MIDI track in your session.
- 2 Set the “receive port” for controlling Live from external software, for example, 8080.
- 3 Set the target IP for sending Transport information to external controlling software. If the software is in the same computer, you can enable “send to localhost” and set a port (different from the receive port!)
- 4 Enable the information you want to send.
- 5 You can enable “stop on MIDI note” and set a MIDI note value. Then add that MIDI note in the Arrangement View and Live will stop the Transport as soon as it hits that note.

Tutorial:

Follow the Tutorial in the Max Package “Controlling Live with UDP” and open `/ableton-project/syncSuite-tutorial3.als`

OSCSync



This device allows to send Transport information from your Live Session as well as receiving Transport and Cue controls via UDP.

Very useful for cueing Live from external software as well as connecting Transport information (bar and beat) with the Score devices.

- 1 Add a OSCSync device to a MIDI track in your session.
- 2 Set the target IP for sending Transport information to external controlling software. If the software is in the same computer, you can enable “send to localhost”.

- 3** In the Arrangement View add a MIDI clip (CMD + Shift + M)
- 4** Open the clip and add a random note (any note, any length).
You only need to do this the first time to activate the device.
- 5** Move the clip in the Arrangement View just a few beats and then put it back on its place. *You only need to do this the first time to activate the device.*
- 6** Select the clip. Go to the device and type any message. Press Enter to confirm the message. You can send several messages with the same clip, just separate them with a comma (do not do a line break!).
- 7** Play the Transport. Your message will be sent as soon as the playhead triggers the MIDI note.

Tutorial:

Follow the Tutorial in the Max Package “Using Live To Send UDP In Sync” and open
`/ableton-project/syncSuite-tutorial-OSCSync.als`

ScoreSync.server



This device allows to create and start a server in your local network to display and stream scores (or any .pdf file).

Any device connected to the network can access the scores and control them.

Additionally, the server allows rendering useful information such as text overlays, metronome, bar information, and more.


This device works together with ScoreSync.part

- 1** Add a ScoreSync.server in a MIDI track
- 2** Start the server. The status toggle should go green and you should receive an IP address and port where the server is running.
- 3** Load a ScoreSync.part in a MIDI track and load a .pdf file. A single server instance can host many parts – but they should be located in different MIDI tracks!

Tutorial:

`/ableton-project/syncSuite-tutorial-score.als`

ScoreSync.part



This device connects to ScoreSync.server and allows you to load a .pdf file to display in a browser. Additionally, you can render other graphical information.

In practice, this is a remote page turner that you can open in any device.

Page turns, text overlays, warning flashes and all information can be automated in Live.

This device works together with ScoreSync.server

- 1 Add a ScoreSync.part in a MIDI track. The generated webpage will take the name of the track, so be careful!
- 2 Be sure that the server is running (check the status toggle, it should be green). If not, start the server in the ScoreSync.server device.
- 3 Load a score and then open the browser. Your score should be displayed.
- 4 Open the "config" menu to customize the layout and add other information to the display.
- 5 Save the Session to save the loaded score.

To access the score from an external device, you need to be sure that the other device is in the exact same network as your computer. Then, open a browser and enter the exact same address displayed at the bottom of the device.

Tutorial:

/ableton-project/syncSuite-tutorial-score.als

SubSync



This device connects to a syncSuite.video.context object in Max and allows to render graphical text using clips in the Arrangement View in Live.

Additionally, you can customize styles and automate them in Live.

- 1 Add a SubSync device to a MIDI track.
- 2 You can load a .txt file and every line will be converted into a separate MIDI clip in the Session View, which you can drag and position anywhere in the Arrangement View.
- 3 You can also write the text manually in the Arrangement View by creating a MIDI clip, changing its name (cmd + r) to the desired text and adding a random MIDI note in the clip. The length of the clip determines the duration of the rendered text.
- 4 The first time you're creating a subtitle, you need to input a note and change the clip's position to activate the device. This is no longer needed after and you can just duplicate the clips and rename them as you need.

This device works together with a `syncSuite.video.context` object in Max.

Tutorial:

Please, follow the tutorial in the `syncSuite.video.subs` help file in Max.

VideoSync




This device connects either to a `syncSuite.video.context` object in Max or to a VideoSyncOutput device in Live.

It allows to import videos into audio tracks and synchronize them with the Live Transport. In this way, it is possible to use powerful and complex rendering software together with Live's Transport.

This device creates a folder in the Live project folder called `videoSync`. Don't delete this folder nor change its contents!

- 1 Insert a VideoSync device in an empty audio track. The track should only host this device and there cannot be any other audio effect in the chain. Don't change any of the track's mixer parameters. The track will auto-mute.
- 2 Use the import buttons to load videos. These will appear as individual clips in the Session View. Don't change their names!
- 3 Place the clips in the same track in the Arrangement View. You can copy, duplicate, cut and trim. Do not warp, add fades nor modify the clip's gain or name.
- 4 Connect to a VideoSyncOutput device or to a `syncSuite.video.context` object in Max.
- 5 Play the Session.

VideoSyncOutput



This device creates a video rendering context that allows for complex pixel-space video mapping and multivideo compositing.

This device works together with other VideoSync devices.

- 1** Insert a VideoSyncOutput device in any empty track.
- 2** Use the menus to select your video sources, i.e., the tracks where you have VideoSync devices.
- 3** Enable the sources using the toggle at the bottom.
- 4** Enable and make the Window visible using the main controls in the left panel. The video window should appear.
- 5** Play the Session.

Tutorial:

/ableton-project/syncSuite-tutorial-video.als