ORB Strategy Architecture & Flow

NIFTY 50 Intraday 1-Minute Precision Trading Algorithm

Timezone: IST (UTC+5:30)

09:15 – 09:45

1. Opening Range Aggregation (ORB)

Collect 1-min candles. Calculate ORB High, Low, Midpoint, and Range % relative to Open.

↓

09:50 – 12:00

2. Breakout Scanning Window

Scan 1-min candles for price breach. Piercing both sides in 1 candle is ignored as ambiguous.

↓

BUY Signal Triggered

High > ORB High before 12:00. State set to BUY. Wait for 14:00 entry.

SELL Signal Triggered

Low < ORB Low before 12:00. State set to SELL. Wait for 14:00 entry.

No Breakout

Price stays inside ORB range. Flagged as "No Breakout" — Skip Day.

↓

14:00

3. Delayed Trade Execution & SL Assignment

Enter at 14:00 candle Close price. Assign Stop Loss based on entry position relative to ORB range.

↓

14:00 – 15:00

4. Stepped Trailing SL Management

Monitor holding candles. Target 1 (0.3x ORB range) moves SL to breakeven. Every +0.1x steps SL up.

↓

15:00 OR SL

5. Position Exit & Logging

Exit on Trailing SL hit (intraday Close) OR EOD Square-off at 15:00. Record total net points.

Execution Rules Matrix

Parameter	BUY Setup	SELL Setup
Breakout Condition	Candle High > ORB High	Candle Low < ORB Low
Entry Price	14:00 Candle Close	14:00 Candle Close
Initial Stop Loss	• Midpoint (if Entry > ORB High) • ORB Low (if Entry ≤ ORB High)	• Midpoint (if Entry < ORB Low) • ORB High (if Entry ≥ ORB Low)
Target 1 Activation	Move ≥ Entry + (0.3 × ORB Range)	Move ≤ Entry − (0.3 × ORB Range)
T1 Stop Loss Action	Move Stop Loss to Break-even (Entry)	Move Stop Loss to Break-even (Entry)
Stepped Trailing	For each +0.1 tier past T1, Lock In: Entry + (Tier − 0.3) × ORB Range	For each +0.1 tier past T1, Lock In: Entry − (Tier − 0.3) × ORB Range
Exit Condition	1-min Close ≤ Current Stop Loss OR 15:00	1-min Close ≥ Current Stop Loss OR 15:00