



## Specifications

System type	12-volt negative ground
-------------	-------------------------

### Alternator

Regulated voltage (at 1500 rpm engine speed with no electrical equipment switched on)	13.5 to 14.2 volts
---	--------------------

### Starter motor

Current draw	
Four-cylinder models	140 amps maximum
Six-cylinder models	170 amps maximum

	Ft-lbs (unless otherwise indicated)
--	-------------------------------------

### Torque specifications

Starter motor-to-transmission nuts and bolts	37
Starter motor support bracket-to-starter motor nuts	48 in-lbs
Starter motor support bracket-to-engine bolts	35