ProSlot® 6000 Machine Options (MO)

#	OPTION	SETTING	DESCRIPTION
27	Bet Mode	(0001)	Credit game
		0003	Coin to credit (Default if Mkt. Code=16)
26	Rebet-Autospin	0000	No rebet, no autospin
		(0001)	No rebet, autospin at maximum credits
		0002	No rebet, autospin at maximum coins or credits
		0003	Rebet, no autospin
		0004	Rebet, autospin at maximum credits
		0005	Rebet, autospin at maximum coins or credits
09	Jackpot Bell	0000	No bell
		0001	Bell rings on all wins
		0002	Rings on wins of 20 or more
		0003	Rings on wins of 50 or more
		0004	Rings on wins of 100 or more
		0005	Rings on wins of 200 or more
		(0006)	Rings on wins causing lockup
10	Coin Denomination (View only - configured by DIP Switch DS2 Market Code and Main)	0000	500
		0001	250
		0002	100
		0003	50
		0004	25
		0005	20
		0006	10
		0007	5
		0008	2
		0009	1
		0010	0.5
		0011	0.25
		0012	0.2
		0013	0.1
		0014	0.05
		0015	0.01
		0016	4
		0017	2.5
11	Change Coin/Credit	0000	Coins from hopper
		(0001)	Credits to CREDIT meter
02	Progressive Type	(0000)	OFF - Lockup jackpots for awarding prizes
		0001	SPL - Serial Progressive Link
		0002	PPL - Parallel Progressive Link
		0003	MAPS® - Multi-Area Progressive System
		0004	S/MPI - Serial/Multiplex Progressive Interface
		0005	MPI - Multiplex Progressive Interface
		0006	SAS® - Progressive v3.xx
		0007	OTT - Over the Top
		0008	SAS® - Progressive v4.xx
07	Number of External Jackpots	(0000)	None
		0001	One
		0002	Two
		0003	Three
		0004	Four
18	Jackpot 4 Signal	(0000)	Combination of 2 & 3
		0001	Combination of 1 & 2
		0002	Combination of 1 & 3
		0003	Combination of 1, 2, & 3
		0004	Discrete serial (Mikohn®)
80	Test 2 & 10 Enable	(0000)	Off
		0001	Test 2, Output to Electro-Mechanical Meter, or Test 10, External Jackpot Signal
01	Tournament Minutes	(0000)	Off
		0001-0099	Minutes for tournament
47	Attract Feature	0000	Off
		(0001)	On
38	Reel Stop Sound	(0000)	Sound from speaker
		(0001	Handle solenoid click
48	Tower Configuration	(0000)	This option has specialized settings. Please see
		0001-0007	Module 2 - Setup and Operations
50Hi	Machine ID	(0000)	Upper four digits of eight-digit identification num-
		0000-9999	ber.
50Lo	Machine ID	(0000)	Lower four digits of eight-digit identification
		0000-9999	number.
54	Coin Hopper Pay Amount	(0000)	Amount paid from the hopper upon a lockup under
		0000-9999	the settings of Option 56, Credit Lockup and Option 51, Credit Limit
56	Credit Collect Lockup	(0800)	Number of credits for a lockup upon any collect.
		0000-9999	If MC=16, default is 4999.
62	Tournament Kitty	(0000)	Starting amount of credits for tournament
		0000-9999	operation.
63	Reset Prog. Amt.	(0000)	Credits added to the counter upon progressive
		0000-9999	jackpot reset (MC=3 or MC=4).
78Hi	Primary SAS® ID	(0000)	None
		0001-9997	SAS® 3.x, 4.x, and 5.x/GRIPS®
		9998	Coin free (MC=6)
		9999	Non-cashable credits
78Lo	Machine Number	(0001)	S/MPI Identification Number
		0000-9999	(Must match progressive controller)
79Hi	Secondary SAS® ID	(0000)	None
		0001-9997	SAS® 3.x, 4.x, and 5.x/GRIPS®
		9998	Coin free (MC=6)
		9999	Non-cashable credits
79Lo	N/A	0	-
04	Even Handpay Collect Lockup	(0000)	Off
		0001	Even handpay by 10s
		0002	Even handpay by 100s
		0003	Even handpay by 1000s
		0004	Machine pays to next 1.00
51	Credit Top Limit	(0800)	Maximum number of credits allowed on the CREDIT meter. Follows Option 56, Credit Collect Lockup, by default.
		0000-9999	IF MC=16, default is 4999.
03	Tournament Seconds	(0000)	Seconds for tournament.
		0001-0059	
22*	Tokenization (All Markets except 16 - see below)	(0000)	Off
		0001	1.0 Token
	Second Coin Denomination (MC=16 Only)	(0001)	1.0 Wager Coin (1:1)
		0002	0.50 Wager Coin (1:2)
		0003	0.20 Wager Coin (1:5)
		0004	0.10 Wager Coin (1:10)
		0005	0.05 Wager Coin (1:20)
	Tokenization (MC=30)	0001	$2 Token
		0002	$5 Token
		0003	$10 Token
		0004	$100 Token
	Tokenization (MC=31)	0001	$1 Token - supports 1¢ - 50¢
		0002	$10 Token - supports 1¢ - $5
	Tokenization (MC=21)	0001	$1000 Token - supports all denomination values for MC=21
15	Residual Credits	(0000)	Residual credits must be played.
		0001	Residual credits forced to Attendant pay.
70 71 72	MAPS® Progressive Cabinet ID	0000	The ID can be represented as XXXXYYYYZZZZ, where Option 70=XXXX, Option 71=YYYY, and Option 72=ZZZZ
58	Win Lockup	(0800)	Amount of win for a Lockup. Follows Option 56, Credit Collect Lockup by default. Must be greater than Option 57, SAS® Lockup, if SAS® is enabled. If MC=16, default is 4999.
		0000-9999	
06	Progressive Group ID	(0000)	SAS® Progressive v4.xx Group ID
		0000-0255	

#	OPTION	SETTING	DESCRIPTION
57	SAS® Lockup (MC=6)	(0800)	A win that is less than the setting of Option 58 and
		(0000)-9999	greater or equal to the setting of Option 57 causes a win lockup that is released by the Host Accounting System. Option 90, Host Remote Jackpot Release, must be set to enable this option.
12	Win Lockup Credit Release	(0000)	Off
		0000-9999	Win lockup credits lower than the setting of Option 12 which are added to CREDIT meter by actuation of a second key switch.
90	Host Remote Jackpot Release	(0000)	Off
		0001	Lockups may be released by Host.
91	Host Queue	(0000)	No queue.
		0001	Multiple lockups queued for processing.
95	Voucher Denomination Mismatch	(0000)	Redeemable vouchers must be evenly divisible by the machine's denomination to be accepted by the machine. Machine accepts all vouchers and prints a change voucher for the odd amount.
		0001	
73	Voucher Validation Level	0000	Standard validation
		0001	Host enhanced validation
		0002	Host secure enhanced validation
		(0003)	Host system validation
76	Voucher Receipt Enable	(0000)	Printer dispenses only redeemable vouchers.
		0001	Printer dispenses redeemable vouchers and informational receipts.
61	Machine Directed Payment Configuration	(0001)	Hopper
		0002	Seiko® PSA™ printer
		0003	Seiko® PSA™ printer and hopper
81	Coin Acceptor Enable	0000	No coin acceptor
		(0001)	Coin acceptor enabled
74	Voucher Expiration	0000	No expiration
		(0030)-0255	Days before voucher expires
	Mkt Code 00	0000	No expiration
		(0030-0255)	Days before voucher expires
64	Minimum Voucher Pay	8000	Fewest credits paid by a voucher.
		(0000)-9999	
67	Maximum Voucher Pay	(8000)	Most credits paid by a voucher.
		0000-9999	
14	Even Voucher Pay	(0000)	Off
		0001	Even voucher pay by 1.00
		0002	Even voucher pay by 2.00
		0003	Even voucher pay by 5.00
		0004	Even voucher pay by 10.00
		0005	Even voucher pay by 20.00
		0006	Even voucher pay by 50.00
		0007	Even voucher pay by 100.00
		0008	Even voucher pay by 200.00
		0009	Even voucher pay by 500.00
		0010	Even voucher pay by 1000.00
77A 77B 77C	Site Location Label	(01.00)	Allows the Operator to enter three (3) lines of
		0000-0047	address to be printed on the vouchers.
08	Credit Snap	(0000)	Wins added incrementally to CREDIT meter.
		0001	Wins more than 20 added as a sum to the CREDIT meter.
05	Even Hand Pay - Win Lockup	(0000)	Off
		0001	Even handpay by 10s
		0002	Even handpay by 100s
		0003	Even handpay by 1000s
		0004	Machine pays to next 1.00
20	Extra Coin	(0000)	Extra coins returned to the Player.
		0001	Extra coins applied to BET for next game (Default if MC=16).
66	PRD Sound Enable	(0000)	Reel stop sound enabled.
		0001	Reel stop sound disabled.
68	Game Sounds	0000	Internal device.
		(0001)	External sound board (ProSound I or II)
23	GRIPS® Host	(0000)	No GRIPS® Host or MC=28 without EFT.
		0001	GRIPS® Host (also 78Hi>0000)
92	SAS® Bonusing	(0000)	Disabled
		0001	SAS® 5.01 bonusing
		0002	AFT bonusing
		0003	SAS® 5.01 and AFT bonusing enabled (also 78Hi>0000)
98	Primary Host	(0000)	Host disabled
		0001	SAS® Host (also 78Hi>0000)
		0002	SDS® Host
99	Secondary Host	(0000)	Host disabled
		0001	SAS® Host (also 78Hi>0000)
		0002	SDS® Host
69	Coin Acceptor	(0000)	CC-16
		0001	IDX X-20 dual denomination coin acceptance (default if MC=16)
19Hi	Asset Number	(0000)	Upper four digits of an eight digit asset number
		0000-9999	(House ID).
19Lo	Asset Number	(0000)	Lower four digits of an eight digit asset number
		0000-9999	(House ID).
75	Coins to Dispense	(0125)	Number of coins to dispense for diagnostic (float
		0000-1024	level). Market Code 16 only.
93	Bank Meter Transfer	(0000)	No transfer to bank meter.
		0001	Transfers 2£ from bank to credit each time a transfer button is pressed. Mkt Code 16 only.
17	SAS® Version	(0000)	SAS® 5.01
		0001	SAS® 6.01
29	Operator Initiated AFT Registration Request	0000	Exit option.
		0001	Initiate EFT registration cycle.
		0002	Cancel EFT registration cycle. (Available when Options 19Hi and 19Lo are set to non-zero values, and Option 98, Primary Host, and Option 99, Secondary Host)
79	VLC Identification	0000-(4000)	The ID can be represented by numbers 0000-4000. VLC only.
24	Print Promotional/ Restricted Vouchers	(0000)	Disallow printing of Promotional/Restricted Vouchers.
		0001	Allow printing of Promotional/Restricted Vouchers. (Option 61 must be set to 0002 or 0003).
30Hi	Game Serial Number Upper	(0000)	The upper four digits of the Game Serial Number
		0000-9999	are sent to the SAS® Host in a 54 Long Poll Response. VLC only.
30Lo	Game Serial Number Lower	(0000)	The lower four digits of the Game Serial Number
		0000-9999	are sent to the SAS® Host in a 54 Long Poll Response. VLC only.
82	Machine Control Functionality	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
83	AFT/EFT Functionality	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
84	Progressive	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
85	Legacy Bonusing	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
86	Validation (TITO)	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
87	Tournament	(0001)	Assigned to Primary Host
		0002	Assigned to Secondary Host
88	SAS® Busy Timing	(0001)	Enabled
		0000	Disabled
96	Filtering of SAS® Control Polls	(0001)	Enabled
		0000	Disabled

*Option 22, Tokenization, is displayed only if appropriate DIP switch is enabled.

| - New/Revised setting. Items in Parentheses () are the machine default settings. Some options may not be available in all jurisdictions.

©2006 Bally Technologies

ProSlot® 6000 Malfunction and Game Codes

#	Code
20	Coin in jam
21	Inappropriate coin in
22	Invalid coin
23	Coin not sensed
24	Coin reverse
50-26$_1$	Bill paused
50-27$_1$	Bill jam
50-29$_1$	Bill acceptor communication error
30	Hopper overpay
31	Hopper coin-out jam
32	Hopper empty
33	Reset during payout
5$_2$-36$_1$	Printer failure
5$_2$-37$_1$	Printer jammed
5$_2$-38$_1$	Printer empty
5$_2$-39$_1$	Printer low
40	Reel initialization error
41	Reel #1 improper spin
42	Reel #2 improper spin
43	Reel #3 improper spin
44	Reel #4 improper spin
45	Reel #5 improper spin
50	Slot door open
51	Belly door open

#	Code
52	Bill acceptor stacker access
53	Lower door open (slant)
54	Drop door open
55	Bill acceptor stacker access
60	Reset during bill change
65	Mechanical meter disconnect
70	Door open during reel spin
71	Reel #1 movement
72	Reel #2 movement
73	Reel #3 movement
74	Reel #4 movement
75	Reel #5 movement
77	Secondary device comm. fault during game
80$_3$	ROM checksum error
81$_3$	Battery low
82	Door open with power off
83$_3$	SafeRAM™ error
83-6	Personality SafeRAM™
83-7	Game History
83-8	Option Table
83-9	Bill Record
83-A	EFT History
83F	SafeRAM™ format error
83F-0	Invalid SafeRAM™ EPROM

#	Code
83F-1	Invalid main EPROM
83F-3	Invalid coin denomination
84$_3$	RAM Error
85	MPU removed with power off
86	Secondary device communication fault during game after failure of the second attempt to reestablish communication.
87-x	Memory Failure during Win Evaluation
88	Catastrophic failure
89	AFT cashout to Host failed
90	Display error
91	Communication error
91-0	No communication
91-1	Serial checksum error
91-2	Optioning error
91-4	Mystery machine pay timing error
91-5	Jackpot missing
91-7	Game error lockout
91-8	Host defined lockout in configuration
91-9	Game in host configuration
91-A	Game not configured

#	Code
91-B	Game in host disabled
91-E	Event log full
91-FF	Feature fault
91nC	No communication
91JP/Pd	The result from a key switch activation after a code 86 lockup condition.
EP	Awards available but not acknowledged by controller.
HP	
HdiS	Communication lost
99	Server Failure (recoverable)
WIN PAID 1 2 3 4	
Position 1	System Reset (no malfunction)
Position 2	Door Opened/Closed
Position 3	Malfunction during Reel Spin/ Replay
Position 4	Bill Transaction

1 - The door codes are 50 = Main Door, 51 - Belly Door, 52 = Bill Acceptor Cash Box Door, 53 = Slant Lower Door, 54 = Drop Door, and 55 = Bill Acceptor Cash Box.
2 - Malfunction codes with prefix "5x" appear only while the door is open.
3 - Malfunction codes 80, 81, 83, and 84 are part of the machine self-test during power ON or a System Reset. Upon an error, all of the machine's lamps flash. The lamps flash one or more times per second, depending on the problem.

DIP Switch Selections

DS 1 Functions

DS1 Secondary Device Protocol								
System	sw1	sw2	sw3	sw4	sw5	sw6	sw7	sw8
BSG (Requires PRD Enabled	*	*	*	OFF	ON	OFF	*	*
Secondary Device$_1$	*	*	*	ON	OFF	ON	*	*
None	*	*	*	ON	ON	ON	*	*
DS1 Other Functions								
5-Digit Display	OFF	*	*	*	*	*	*	*
Tokenization avail. as M.O. 22	*	OFF	*	*	*	*	*	*
Win Eval Mem Corrupt Tilt Lock recoverable 87-x exception	*	*	OFF	*	*	*	*	*
HW Exception Lock, release to 99 Code	*	*	*	*	*	*	OFF	*

* - Setting does not matter, leave ON.
1- Requires wheel control chip G23S0100S0RCU-01 or above.

DS2 Sw1 - Sw4 Denomination

Market Codes 0 - 17, 22$_1$, 24, 25, 28, 29, 30, 31, 32$_2$					
Sw1	Sw2	Sw3	Sw4	Value	Denom.
ON	ON	ON	ON	0000	500
OFF	ON	ON	ON	0001	250
ON	OFF	ON	ON	0002	100
OFF	OFF	ON	ON	0003	50
ON	ON	OFF	ON	0004	25
OFF	ON	OFF	ON	0005	20
ON	OFF	OFF	ON	0006	10
OFF	OFF	OFF	ON	0007	5
ON	ON	ON	OFF	0008	2
OFF	ON	ON	OFF	0009	1
ON	OFF	ON	OFF	0010	0.50
OFF	OFF	ON	OFF	0011	0.25
ON	ON	OFF	OFF	0012	0.20
OFF	ON	OFF	OFF	0013	0.10
ON	OFF	OFF	OFF	0014	0.05
OFF	OFF	OFF	OFF	0015	0.01
ON	ON	ON	ON	0016	4 (MC=07)
ON	ON	ON	ON	0017	2.5 (Int'l)

1 - MC 22 does not support denominations less than 2.00.
2 - MC 32 only supports 500 and 100 denominations.

Market Codes 18, 20					
Sw1	Sw2	Sw3	Sw4	Value	Denom
ON	ON	ON	ON	0000	5000
ON	OFF	ON	ON	0002	1000
OFF	OFF	ON	ON	0003	500
OFF	ON	OFF	ON	0005	200

Market Code 19					
Sw1	Sw2	Sw3	Sw4	Value	Denom
ON	ON	ON	ON	0000	1000
OFF	ON	ON	ON	0001	500
ON	OFF	ON	ON	0002	250
ON	ON	OFF	ON	0004	50
OFF	ON	OFF	ON	0005	25

Market Code 21					
Sw1	Sw2	Sw3	Sw4	Value	Denom
ON	ON	ON	ON	0000	1000
OFF	ON	ON	ON	0001	500
ON	OFF	ON	ON	0002	250
OFF	OFF	ON	ON	0003	200
ON	ON	OFF	ON	0004	100

Market Code 23					
Sw1	Sw2	Sw3	Sw4	Value	Denom
ON	ON	ON	ON	0000	500
ON	OFF	ON	ON	0002	100
OFF	OFF	ON	ON	0003	50
ON	ON	OFF	ON	0004	25
ON	OFF	OFF	ON	0006	10
OFF	OFF	OFF	ON	0007	5
ON	ON	ON	OFF	0008	1
OFF	ON	ON	OFF	0009	0.50
ON	OFF	ON	OFF	0010	0.25
OFF	OFF	ON	OFF	0011	0.20
ON	ON	OFF	OFF	0012	0.10
OFF	ON	OFF	OFF	0013	0.05
ON	OFF	OFF	OFF	0014	0.02
OFF	OFF	OFF	OFF	0015	0.01

DS2 Sw1 - Sw4 Denomination continued

Market Codes 26$_1$, 27					
Sw1	Sw2	Sw3	Sw4	Value	Denom
ON	OFF	OFF	ON	0006	5
OFF	OFF	OFF	ON	0007	2
ON	ON	ON	OFF	0008	1
OFF	ON	ON	OFF	0009	0.50
ON	OFF	ON	OFF	0010	0.25
OFF	OFF	ON	OFF	0011	0.20
ON	ON	OFF	OFF	0012	0.10
OFF	ON	OFF	OFF	0013	0.05
ON	OFF	OFF	OFF	0014	0.02

1- MC 26 supports denominations greater than 5.00, see MC 0.

DS2 Sw5 - Sw6 Bill Acceptor

DS2 Sw5 - Sw6 Bill Acceptor			
Sw5	Sw6	Value	Bill Acceptor
ON	ON	00	No Bill Acceptor
OFF	ON	01	GPT/ARDAC
ON	OFF	02	JCM WBA
OFF	OFF	03	MARS

DS2 Sw7 - Sw8 Special Features

DS2 Sw7 - Sw8 Special Features	
SW7	**Game Feature**
ON	Normal Reel Spin
OFF	Crazy Reel Spin
Sw8 and MC = 01 or 13	**EFT Support**
ON	Not Present
OFF	Present

DS3 Sw1 - Sw4, Sw7, and Sw8 Market Code (MC)

sw1	sw2	sw3	sw4	sw7	sw8	Value	Market
ON	ON	ON	ON	ON	ON	00	Nevada, VLC, WV, DE, ME
OFF	ON	ON	ON	ON	ON	01	New Jersey
ON	OFF	ON	ON	ON	ON	02	Deadwood, SD; Quebec, Canada
OFF	OFF	ON	ON	ON	ON	03	France - Nominal%
ON	ON	OFF	ON	ON	ON	04	France - Basic%
OFF	ON	OFF	ON	ON	ON	05	Puerto Rico
ON	OFF	OFF	ON	ON	ON	06	South Africa
OFF	OFF	OFF	ON	ON	ON	07	Special Denom (AZ, Int'l)
ON	ON	ON	OFF	ON	ON	08	Indiana
OFF	OFF	OFF	OFF	OFF	OFF	09	Reserved
ON	OFF	ON	OFF	ON	ON	10	Colorado
OFF	OFF	ON	OFF	ON	ON	11	USAF
ON	ON	OFF	OFF	ON	ON	12	OLGC
OFF	ON	OFF	OFF	ON	ON	13	Mississippi
ON	OFF	OFF	OFF	ON	ON	14	Germany
OFF	OFF	OFF	OFF	ON	ON	15	New Mexico
ON	ON	ON	ON	OFF	ON	16	England
OFF	ON	ON	ON	OFF	ON	17	Portugal
ON	OFF	ON	ON	OFF	ON	18	Italy
OFF	OFF	ON	ON	OFF	ON	19	Greece
ON	ON	OFF	ON	OFF	ON	20	Russia
OFF	ON	OFF	ON	OFF	ON	21	Chile
ON	OFF	OFF	ON	OFF	ON	22	Venezuela
OFF	OFF	OFF	ON	OFF	ON	23	Estonia
ON	ON	ON	OFF	OFF	ON	24	Philippines
OFF	ON	ON	OFF	OFF	ON	25	Finland
ON	OFF	ON	OFF	OFF	ON	26	Ireland
OFF	OFF	ON	OFF	OFF	ON	27	Euro
ON	ON	OFF	OFF	OFF	ON	28	Switzerland
OFF	ON	OFF	OFF	OFF	ON	29	Manitoba
ON	OFF	OFF	OFF	OFF	ON	30	Hong Kong/Macau
OFF	OFF	OFF	OFF	OFF	ON	31	Uruguay
ON	ON	ON	ON	ON	OFF	32	Korea

DS3 Sw5 - Sw6 Reel Map/Win Table

DS3 Sw5 - Sw6 Reel Map/Win Table	
Sw5	Sw6
ON	ON

| - New/Revised Setting

©2006 Bally Technologies