

Ultimate MCR Master Pinout Matrix

Connector-Pin	Standard MCR Function	Solar Fox (MCR-1)	Kick / Kickman (MCR-1)	Tron (MCR-2)	Satan's Hollow (MCR-2)	Kozmik Krooz'r (MCR-2)	Wacko (MCR-2)	Domino Man (MCR-2)	Tapper (MCR-3)	Journey (MCR-3)	Timber (MCR-3)	Discs of Tron (MCR-3)	Spy Hunter (MCR-3)	Crater Raider (MCR-3)
J2-1	P1 Up	P1 Up	N/C	P1 Up	P1 Left	N/C	P1 Up	P1 Up	P1 Up	P1 Up	P1 Up	P1 Up	Machine Gun	N/C
J2-2	P1 Down	P1 Down	N/C	P1 Down	P1 Right	N/C	P1 Down	P1 Down	P1 Down	P1 Down	P1 Down	P1 Down	Missiles	N/C
J2-3	P1 Left	P1 Left	N/C	P1 Left	N/C	N/C	P1 Left	P1 Left	P1 Left	P1 Left	P1 Left	P1 Left	Oil Slick	P1 Left
J2-4	P1 Right	P1 Right	N/C	P1 Right	N/C	N/C	P1 Right	P1 Right	P1 Right	P1 Right	P1 Right	P1 Right	Smoke Screen	P1 Right
J2-5	P1 Button 1	Fire / Turbo	Kick	Fire (Trigger)	Fire (Trigger)	Fire	N/C	Place / Strike	Pour / Serve	Fire	N/C	Fire (Trigger)	Weapons Van	Fire
J2-6	P1 Button 2	N/C	Catch	N/C	Shield	N/C	N/C	N/C	N/C	N/C	N/C	Deflect	N/C	Shield
J2-13	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground
J5-1	P2 Mux / Data Bit 0 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D0)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-2	P2 Mux / Data Bit 1 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D1)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-3	P2 Mux / Data Bit 2 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D2)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-4	P2 Mux / Data Bit 3 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D3)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-5	P2 Mux / Data Bit 4 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D4)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-6	P2 Mux / Data Bit 5 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D5)	No J5	N/C	N/C	N/C	N/C	N/C	N/C
J5-15	P2 Up / Data Bit 6 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D6)	No J5	P2 Up	N/C	P2 Up	Aim Up	N/C	N/C
J5-16	P2 Down / Data Bit 7 (Opt Y)	No J5	No J5	No J5	No J5	No J5	Trackball Y-Axis (D7)	No J5	P2 Down	N/C	P2 Down	Aim Down	N/C	N/C
J5-17	P2 Left	No J5	No J5	No J5	No J5	No J5	N/C	No J5	P2 Left	N/C	P2 Left	N/C	N/C	N/C
J5-18	P2 Right	No J5	No J5	No J5	No J5	No J5	N/C	No J5	P2 Right	N/C	P2 Right	N/C	N/C	N/C
J5-19	P2 Button 1	No J5	No J5	No J5	No J5	No J5	N/C	No J5	P2 Pour	N/C	N/C	N/C	N/C	N/C
J3-1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1	Coin 1
J3-2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2	Coin 2
J3-3	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1	Start 1
J3-4	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	Start 2	N/C	Start 2
J3-5	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt	Tilt
J4-1	Data Bit 0 (Opt X)	Data Bit 0	Spinner X (D0)	Opt/Main (D0)	Data Bit 0	Spinner X (D0)	Trackball X-Axis (D0)	Data Bit 0	Data Bit 0	Data Bit 0	Data Bit 0	Rotary (D0)	Steer/Gas (D0)	Data Bit 0
J4-2	Data Bit 1 (Opt X)	Data Bit 1	Spinner X (D1)	Opt/Main (D1)	Data Bit 1	Spinner X (D1)	Trackball X-Axis (D1)	Data Bit 1	Data Bit 1	Data Bit 1	Data Bit 1	Rotary (D1)	Steer/Gas (D1)	Data Bit 1
J4-3	Data Bit 2 (Opt X)	Data Bit 2	Spinner X (D2)	Opt/Main (D2)	Data Bit 2	Spinner X (D2)	Trackball X-Axis (D2)	Data Bit 2	Data Bit 2	Data Bit 2	Data Bit 2	Rotary (D2)	Steer/Gas (D2)	Data Bit 2
J4-4	Data Bit 3 (Opt X)	Data Bit 3	Spinner X (D3)	Opt/Main (D3)	Data Bit 3	Spinner X (D3)	Trackball X-Axis (D3)	Data Bit 3	Data Bit 3	Data Bit 3	Data Bit 3	Rotary (D3)	Steer/Gas (D3)	Data Bit 3
J4-5	Data Bit 4 (Opt X)	Data Bit 4	Spinner X (D4)	Opt/Main (D4)	Data Bit 4	Spinner X (D4)	Trackball X-Axis (D4)	Data Bit 4	Data Bit 4	Data Bit 4	Data Bit 4	Rotary (D4)	Steer/Gas (D4)	Data Bit 4
J4-6	Data Bit 5 (Opt X)	Data Bit 5	Spinner X (D5)	Opt/Main (D5)	Data Bit 5	Spinner X (D5)	Trackball X-Axis (D5)	Data Bit 5	Data Bit 5	Data Bit 5	Data Bit 5	Rotary (D5)	Steer/Gas (D5)	Data Bit 5
J4-7	Data Bit 6 (Opt X)	Data Bit 6	Spinner X (D6)	Opt/Main (D6)	Data Bit 6	Spinner X (D6)	Trackball X-Axis (D6)	Data Bit 6	Data Bit 6	Data Bit 6	Data Bit 6	Rotary (D6)	Steer/Gas (D6)	Data Bit 6
J4-8	Key	Key	Key	Key	Key	Key	Key	Key	Key	Key	Key	Key	Key	Key
J4-9	Data Bit 7 (Opt X)	Data Bit 7	Spinner X (D7)	Opt/Main (D7)	Data Bit 7	Spinner X (D7)	Trackball X-Axis (D7)	Data Bit 7	Data Bit 7	Data Bit 7	Data Bit 7	Rotary (D7)	Steer/Gas (D7)	Data Bit 7
J4-10	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground	Ground
Video - Pin 1	Red	Red	Red	Red	Red	Red	Red	Red	Red	Red	Red	Red	Red	Red
Video - Pin 2	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND
Video - Pin 3	Green	Green	Green	Green	Green	Green	Green	Green	Green	Green	Green	Green	Green	Green
Video - Pin 4	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND	Video GND

[illegible]