

## 1N4099-1N4135, 1N4614-1N4627

#### 500mW LOW NOISE ZENER DIODES

#### **FEATURES**

- Available as "HR" (high reliability) screened per MIL-PRF-19500, JANTX level. Add "HR" suffix to base part number.
- Available as non-RoHS (Sn/Pb plating), standard, and as RoHS by adding "-PBF" suffix.

#### **MAXIMUM RATINGS**

Junction and Storage Temperatures:	-65°C to +200°C	
DC Power Dissipation:	500mW	
Power Derating:	4.0mW/°C above 50°C in DO-35	
Forward Voltage @ 200mA:	1.1 Volts 1N4099-1N4135	
@ 100mA:	1.0 Volts 1N4614-1N4627	

### **ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C unless otherwise specified)

Part number	Nominal Zener Voltage Vz @ I <sub>ZT</sub> (Note 1)	Zener Test Current I <sub>zī</sub>	Maximum Zener Impedance Z <sub>ZT</sub> (Note 2)	Maximum Reverse Current Iz @ V <sub>R</sub>		Maximum Noise Density N <sub>D</sub> @ I <sub>ZT</sub>	Maximum Zener Current I <sub>ZM</sub> (Note 3)	Maximum Temp. Coeff. Of Zener Voltage α <sub>VZ</sub>
	Volts	μΑ	Ohms	μΑ	Volts	μV/VHZ	mA	%/°C
1N4614	1.8	250	1200	7.5	1	1	120	-0.075
1N4615	2.0	250	1250	5.0	1	1	110	-0.075
1N4616	2.2	250	1300	4.0	1	1	100	-0.075
1N4617	2.4	250	1400	2.0	1	1	95	-0.075
1N4618	2.7	250	1500	1.0	1	1	90	-0.075
1N4619	3.0	250	1600	0.8	1	1	87	-0.075
1N4620	3.3	250	1650	7.5	1.5	1	85	-0.075
1N4621	3.6	250	1700	7.5	2	1	83	-0.065
1N4622	3.9	250	1650	5.0	2	1	80	-0.060
1N4623	4.3	250	1600	4.0	2	1	77	-0.050
1N4624	4.7	250	1550	10.0	3	1	75	-0.050+0.020
1N4625	5.1	250	1500	10.0	3	2	70	-0.045+0.030
1N4626	5.6	250	1400	10.0	4	4	65	-0.020+0.040
1N4627	6.2	250	1200	10.0	5	5	61	-0.010+0.050
1N4099	6.8	250	200	10.0	5.17	40	56	0.060
1N4100	7.5	250	200	10.0	5.70	40	51	0.065
1N4101	8.2	250	200	1.0	6.24	40	46	0.070
1N4102	8.7	250	200	1.0	6.61	40	44	0.075
1N4103	9.1	250	200	1.0	6.92	40	42	0.080
1N4104	10	250	200	1.0	7.60	40	38	0.080
1N4105	11	250	200	.05	8.44	40	35	0.080
1N4106	12	250	200	.05	9.12	40	32	0.080
1N4107	13	250	200	.05	9.87	40	29	0.080
1N4108	14	250	200	.05	10.65	40	27	0.085



## 1N4099-1N4135, 1N4614-1N4627

#### 500mW LOW NOISE ZENER DIODES

Part number	Nominal Zener Voltage Vz @ IzT (Note 1)  Volts	Zener Test Current Ι <sub>Ζτ</sub> μΑ	Maximum Zener Impedance Z <sub>ZT</sub> (Note 2) Ohms	Maximum Reverse Current I <sub>Z</sub> @ V <sub>R</sub>		Maximum Noise Density N <sub>D</sub> @ I <sub>ZT</sub>	Maximum Zener Current I <sub>ZM</sub> (Note 3)	Maximum Temp. Coeff. Of Zener Voltage α <sub>VZ</sub>
				μΑ	Volts	μV/√HZ	mA	%/°C
1N4109	15	250	100	.05	11.40	40	25	0.085
1N4110	16	250	100	.05	12.15	40	24	0.085
1N4111	17	250	100	.05	12.92	40	22	0.090
1N4112	18	250	100	.05	13.67	40	21	0.090
1N4113	19	250	150	.05	14.44	40	20	0.090
1N4114	20	250	150	.01	15.20	40	19	0.090
1N4115	22	250	150	.01	16.72	40	17	0.090
1N4116	24	250	150	.01	18.25	40	16	0.090
1N4117	25	250	150	.01	19.00	40	15	0.090
1N4118	27	250	150	.01	20.45	40	14	0.090
1N4119	28	250	200	.01	21.28	40	14	0.095
1N4120	30	250	200	.01	22.80	40	13	0.095
1N4121	33	250	200	.01	25.08	40	12	0.095
1N4122	36	250	200	.01	27.38	40	11	0.095
1N4123	39	250	200	.01	29.65	40	9.8	0.095
1N4124	43	250	250	.01	32.65	40	8.9	0.095
1N4125	47	250	250	.01	35.75	40	8.1	0.095
1N4126	51	250	300	.01	38.76	40	7.5	0.100
1N4127	56	250	300	.01	42.60	40	6.7	0.100
1N4128	60	250	400	.01	45.60	40	6.4	0.100
1N4129	62	250	500	.01	47.10	40	6.1	0.100
1N4130	68	250	700	.01	51.68	40	5.6	0.100
1N4131	75	250	700	.01	57.00	40	5.1	0.100
1N4132	82	250	800	.01	62.32	40	4.6	0.100
1N4133	87	250	1000	.01	66.12	40	4.4	0.100
1N4134	91	250	1200	.01	69.16	40	4.2	0.100
1N4135	100	250	1500	.01	76.00	40	3.8	0.100

Note 1: No suffix shows a standard tolerance of +/- 5% on the nominal zener voltage. Also available in 2% and 1% tolerance, suffix C and D respectively. Vz is measured with the diode in

thermal equilibrium in 25°C still air.

Note 2: Zener impedance is derived by superimposing on  $I_{ZT}$ , a 60Hz rms a.c. current equal to 10% of  $I_{ZT}$  (25 $\mu$ A a.c.)

Note 3: Based upon 400mW maximum power dissipation at 75°Clead temperature, allowance has been made for the higher voltage associated with operation at higher currents.




# 1N4099-1N4135, 1N4614-1N4627

500mW LOW NOISE ZENER DIODES

### MECHANICAL CHARACTERISTICS

Case:	DO-35
Marking	Alpha-numeric
Polarity:	Cathode band



	DO-35						
	Inc	hes	Millimeters				
	Min	Max	Min	Max			
BD	0.055	0.090	1.400	2.290			
BL	0.120	0.200	3.050	5.080			
LD	0.018	0.022	0.460	0.560			
LL	1.000	1.500	25.400	38.100			



## 1N4099-1N4135, 1N4614-1N4627

500mW LOW NOISE ZENER DIODES

