

RESTRICTED

Code No. XXXXXX

THE INFORMATION GIVEN IN THIS DOCUMENT IS NOT TO BE PUBLISHED OR COMMUNICATED, EITHER DIRECTLY OR INDIRECTLY TO THE PRESS OR ANY PERSON NOT HOLDING AN OFFICIAL POSITION IN THE SERVICE OF THE GOVERNMENT OF INDIA



Technical Manual

Ruggedized Field Telephone Set (RFT1001)

Part IV: Manufacturer's Parts List - Illustrations

(Vol 2 of 2)

Doc ID: 1551/6-DPAR002014

Rev.: PA1

()

THIS HANDBOOK DOES NOT CONSTITUTE AUTHORITY FOR REPAIRS OR REPLACEMENT OF COMPONENTS BY USERS. REPAIRS BY DIFFERENT AGENCIES WILL ONLY BE CARRIED OUT AS LAID DOWN IN PERMISSIBLE REPAIR SCHEDULES PUBLISHED AS EMERs OR EQUIVALENT FROM TIME TO TIME.

Prepared & Published by

Elcom Innovations (P) Ltd.

Ground Floor, Tower D, Bhutani Techno Park, Sector 127,

Noida - 201313 (U.P.), India.

web: www.elcom-group.com

Dec, 2013

INDIA

RESTRICTED

RECORD OF CHANGES

Change Notice No.	Authority	Incorporated by “Name and Rank” in Block letters	Initials with date
(1)	(2)	(3)	(4)

ASSOCIATED HANDBOOKS

Technical Literature for **FIELD TELEPHONE SET RFT1001** comprises of the followings:

- USER HANDBOOK
- TECHNICAL MANUAL

PART I TECHNICAL INFORMATION

Volume 1 Technical Description

Volume 2 Drawings

PART II MAINTENANCE

PART III OVERHAUL AND RECONDITIONING INSTRUCTIONS

PART IV MANUFACTURER'S PARTS LIST

Volume 1 Parts List

Volume 2 Illustrations

SAFETY WARNING

**The voltages employed in this Equipment are
sufficiently high to endanger human life.**

**POWER
MUST BE SWITCHED OFF
before servicing the equipment
&**

**GREAT CARE
taken when making internal adjustments etc.**

FOR FIRST AID IN CASE OF ELECTRIC SHOCK SEE OVERLEAF

FIRST AID IN CASE OF ELECTRIC SHOCK

FIG. 1.



FIG. 2.



FIG. 3.



FIG. 4.



1.	SWITCH OFF. If this is not possible, PROTECT YOURSELF with dry insulating material and pull the victim clear of the conductor. DO NOT TOUCH THE VICTIM WITH YOUR BARE HANDS until he is clear of the conductor, but DO NOT WASTE TIME.
2.	(a) Place the victim in the supine position. (b) Keep the air passages clear by turning the head to one side, opening the patient's mouth and clearing it of water, saline, mucus or blood, a lot of which might have accumulated in the back of the throat.(Figure 1).
3.	If the jaw is rigid try to force the mouth open by pressure on the gum behind the last molar tooth of the lower jaw. When the upper air passages are thus cleared, tilt the head backward and force the jaw forwards from the angles of the jaw in front of the ears. This would prevent mechanical obstructions to the upper air passages.(Figure 2-3)
4.	(a) Then hold the chin up and forward with one hand and pinch the nostrils of the victim with the other.(Figure 4) (b) Take a very deep breath and apply your mouth to that of the victim and blow into his mouth, until the chest of the victim moves up indicating filling of the lungs. (NEVER ALLOW THE CHIN TO SAG).(Figure 4)
5.	When the chest has moved up, withdraw your mouth and allow the chest to sink back. REPEAT this process every three to four seconds until the victim begins to breathe again or until he is taken over by a medical attendant. This method can be continued in an ambulance during transit of the patient from the site of accident to the nearest medical centre.
HAVE SOMEONE ELSE AND SEND FOR A DOCTOR. KEEP PATIENT WARM AND LOOSEN HIS CLOTHING. DO NOT GIVE LIQUIDS UNTIL THE PATIENT IS CONSCIOUS.	

DEMOLITION OF MATERIAL TO PREVENT ENEMY USE

(A) General

The demolition procedure outlined below will be used to prevent the enemy from using or salvaging this equipment. **DEMOLITION OF THE EQUIPMENT WILL BE DONE ONLY ON ORDER OF THE COMMANDER.**

(B) Methods of Destruction

Use any or all the following methods to destroy the equipment.

- (i) Smash - Smash the crystals, controls semiconductors, coil, switches, transformers and handset. Use sledges, hand axes, pickaxes, hammers crowbars and heavy tools.
- (ii) Cut - Cut the cords, headsets and wiring. Use axes, hands axes or hatchets.
- (iii) Burn - Burn the cords, resistors, capacitors, coils, wiring, technical manuals. Use gasoline, kerosene, oil, flamethrowers or incendiary.
- (iv) Bend - Bend the panels, cabinet and chassis.
- (v) Explosives - If explosives are necessary, use firearms, grenades or TNT.
- (vi) Disposal - Bury or scatter the destroyed parts in slit trenches, fox holes or throw them into streams.

CHANGE NOTICE

TITLE OF PUBLICATION	CODE NO. AND DATE	PREVIOUS CHANGE	CHANGE NOTICE NO. AND DATE

No. of Pages:

Enclosures:

Sheets:

CODES FOR INCORPORATION OF CHANGES	NOTE
(R) By replacement / addition of sheet(s)	This document should be filled / pasted in the copy of the publication before the CONTENTS page. After carrying out (R), (H) or (P), entry should be made in Record of changes Page.
(H) By Hand – correction	
(P) By pasting enclosed matter	
(A) Additional information – only to be filled in publication	

Table

1 Scope	13
1.1 Reference Document	13
1.2 Intended Audience	13
1.3 Abbreviations Used	13
2 Part List of RFT1001	15
2.1 Part List Hierarchy.....	Error! Bookmark not defined.
2.2 Part List of RFT1001 (Top Level).....	17
2.3 Part List of Electronics Cards	21
2.3.1 EBA30058, Control Card	21
2.3.2 EBA30059, Ringer Card.....	29
2.3.3 EBA30060, Ringer Micro Switch Card.....	32
2.3.4 EBA30062, System Switch Card.....	33
2.3.5 EBA30063, BAT MON Switch Card	34
2.3.6 EBA30065, Volume Switch Card.....	35
2.4 Part List of Wire Harnesses	36
2.4.1 66071, 'LN' Line Cable Harness	36
2.4.2 66072, 'BT' Battery Box Harness	37
2.4.3 66073, 'TRV' Volume Switch Harness	38
2.4.4 66074, 'BZ' Buzzer Harness.....	39
2.4.5 66075, 'BZV' Buzzer Volume Harness.....	40
2.4.6 66076, 'RG' Ringer PCB Cable Harness.....	41
2.4.7 66077, 'LD' LED Display (BAT. MON.) Cable Harness	43
2.4.8 66078 'RS' Ringer Switch Harness	44
2.4.9 66079, Hook Switch Harness	46
2.4.10 66080, 'SS' System Switch Harness.....	47
2.4.11 66081, 'KP' Keypad Cable Harness	48
2.4.12 66082, 'EB' Ext. Battery Cable Harness	50
2.4.13 66083, 'Battery Box Assembly Harness-2	51
2.4.14 66084, 'Battery Box Assembly Harness-3	52
2.5 Part List of Mechanical Sub-Assemblies.....	53
2.5.1 66085, Battery Box Assembly	53
2.5.2 66086, Volume Switch Assembly	54
2.5.3 66087, Buzzer Assembly	55
2.5.4 66088, Buzzer Volume Assembly	56
2.5.5 66089, BAT MON Switch Assembly	57
2.5.6 66090, BAT MON Switch Assembly	58
2.5.7 66091, Keypad Assembly	59
2.5.8 66092, Handset 'HNST' Harness Assembly.....	60

Note:

1 Scope

- a) This document (1551/6-DPAR002014) is one of the technical document which covers assembling drawings of various sub-assemblies of RFT1001.
- b) Changes/additions which may have to be incorporated from time to time as supplement to this Technical Manual Part IV- Vol 2 of 2 (to be called as Illustrations) will be issued by **M/s. Elcom Innovations Pvt. Ltd** covering:
 - a. Identification details of Sub-Assemblies which were not available at the time of preparations.
 - b. Allotment of DS/ Service Catalogue and Part nos. not included earlier.
 - c. Changes in the equipment due to modifications/ Updation.
- c) User should amend this book and record details of changes in the Record of Changes page.

1.1 Reference Document

[1] User Handbook	1553-DPAR002014
[2] Technical Manuals,	
PART I - Technical Information, Description (Vol 1 of 2)	1551/1-DPAR002014
Technical Information, Drawings (Vol 2 of 2)	1551/2-DPAR002014
PART II - Maintenance	1551/3-DPAR002014
PART III - Overhaul & Reconditioning Instructions	1551/4-DPAR002014
PART IV - Manufacturers's Parts List – Part Lists (Vol 1 of 2)	1551/5-DPAR002014
Manufacturers's Part List – Illustrations (Vol 2 of 2)	1551/6-DPAR002014

1.2 Intended Audience

The intended audience of this document is the trained technical personnel on Field Telephone Set RFT1001.

1.3 Abbreviations Used

EBA	-	Electronic Board Assembly
SA	-	Sub Assembly
WHA	-	Wire Harness Assembly

Notes:

2 Assemblies / Sub-Assemblies of RFT1001

Top Level Part List			Refer Chapter 2.1
	Electronics Cards	EBA30058, Control Card	Refer Chapter 2.2.1
		EBA30059, Ringer Card	Refer Chapter 2.2.2
		EBA30062, System Switch Card	Refer Chapter 2.2.4
	Wire Harnesses	66071, 'LN' Line Cable Harness	Refer Chapter 2.3.1
		66076, 'RG' Ringer PCB Cable Harness	Refer Chapter 2.3.6
		66079, Hook Switch Harness	Refer Chapter 2.3.9
		66080, 'SS' System Switch Harness	Refer Chapter 2.3.10
		66082, 'EB' Ext. Battery Cable Harness	Refer Chapter 2.3.12
	Mech Sub-Assemblies	66085, Battery Box Assembly	Refer Chapter 2.4.1 & 2.3.2
		66072, 'BT' Battery Box Harness	Refer Chapter 2.3.13
		66083, 'Battery Box Assembly Harness-2	Refer Chapter 2.3.14
		66084, Battery Box Assembly Harness-3	
		66086, Volume Switch Assembly	Refer Chapter 2.4.2 & 2.2.6
		EBA30065, Volume Switch Card	Refer Chapter 2.3.3
		66073, 'TRV' Volume Switch Harness	
		66087, Buzzer Assembly	Refer Chapter 2.4.3 & 2.3.4
		66074, 'BZ' Buzzer Harness	
		66088, Buzzer Volume Assembly	Refer Chapter 2.4.4 & 2.2.6
		EBA30065, Volume Switch Card	Refer Chapter 2.3.5
		66075, 'BZV' Buzzer Volume Harness	
		66089, BAT MON Switch Assembly	Refer Chapter 2.4.5 & 2.2.5
		EBA30063, BAT. MON. Switch Card	Refer Chapter 2.3.7
		66077, 'LD' BAT MON Cable Harness	
		66090, BAT MON Switch Assembly	Refer Chapter 2.4.6 & 2.2.3
		EBA30060, Ringer Micro Switch Card	Refer Chapter 2.3.8
		66078, 'RS' Ringer Switch Harness	
		66091, Keypad Assembly	Refer Chapter 2.4.7 & 2.3.11
		66081, 'KP' Keypad Cable Harness	
		66092, Handset 'HNST' Harness Assy	Refer Chapter 2.4.8

Note : BOM Hierarchy shows only Sub-Assemblies, there will be some child parts also. Refer respective BOM for detailed part lists.

Notes:

2.1 Part List of RFT1001 (Top Level)

The top level part list of RFT1001 covers all the child parts at top level along with all the sub-assemblies such as Mechanical Sub-Assemblies, Elex Cards Assemblies & Wire Harnesses Assemblies as shown below.

DPAR002014-R1A Field Telephone Set with Magneto And Auto Mode (RFT1001)				Document No.: 13132-DPAR002014			Rev.: A	
				Author: Sandeep Sharma			Date: 2026-04-10	
				Approved: Prafulla Sarode				
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*	Sub Assy
1	1	P46100302	Top Housing for RFT1001 (ABS)	1	EA	PTPL	P46100302	-
2	2	P46100303	Bottom Cover for RFT1001 (ABS)	1	EA	PTPL	P46100303	-
3	4	P46011421	Logo Sticker for RFT1001	1	EA	Woer	P46011421	-
4	5	P46011418	Ringer Dome Membrane for RFT1001	1	EA	Woer	P46011418	-
5	6	P46011419	BAT.MON. Sticker for RFT1001	1	EA	Woer	P46011419	-
6	7	P78001258	Wiring Diagram and Instruction for RFT1001	1	EA	Woer	P78001258	-
7	8	P78001260	Marking / Sr. Number Plate for RFT1001	1	EA	PTPL	P78001260	-
8	9	P78001259	Handset Guard for RFT1001	1	EA	PTPL	P78001259	-
9	10	P78001261	Ball catch for Handset for RFT1001	1	EA	PTPL	P78001261	-
10	11	P78001272	Binding Post Red for RFT1001	2	EA	PTPL	P78001272	-
11	12	P78001273	Binding Post Black for RFT1001	2	EA	PTPL	P78001273	-
12	13	P46011454	Rubber O Ring ID-6.2mm x OD-8.6mm x Thickness-1.2mm for RFT1001 Binding Post	4	EA	Smart Solutions	P46011454	-

DPAR002014-R1A Field Telephone Set with Magneto And Auto Mode (RFT1001)				Document No.: 13132-DPAR002014		Rev.: A		
				Author: Sandeep Sharma		Date: 2026-04-10		
				Approved: Prafulla Sarode				
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*	Sub Assy
13	15	P46100304	Ringer Volume Switch Knob for RFT1001	1	EA	PTPL	P46100304	-
14	16	P78001037	System Switch Knob	1	EA	New Plastic & Metal	P78001037	-
15	17	P78001274	Speech Switch Knob for RFT1001	1	EA	New Plastic & Metal	P78001274	-
16	18	P46100308	Battery Box Cap for RFT1001	1	EA	PTPL	P46100308	-
17	19	P46002216	PTR Rubber Square Washer	1	EA	New Plastic & Metal	P46002216	-
18	20	P46002138	PTR Rubber O Ring, 38 x 2.5	2	EA	New Plastic & Metal	P46002138	-
19	21	P78001275	Buzzer Nut for RFT1001	1	EA	PTPL	P78001275	-
20	23	P78001276	Magneto Plastic Plunger for RFT1001	1	EA	PTPL	P78001276	-
21	24	P78001277	Cradle Switch Cap. For RFT1001	1	EA	PTPL	P78001277	-
22	25	P78001278	Cover Plate for Cradle Switch Cap for RFT1001	1	EA	PTPL	P78001278	-
23	26	P78001262	L Bracket for Cradle Switch RHS for RFT1001	1	EA	PTPL	P78001262	-
24	27	P78001271	L Bracket for Cradle Switch LHS for RFT1001	1	EA	PTPL	P78001271	-
25	28	P72113349	Handset for RFT1001	1	EA	PTPL	P72113349	-
26	31	P78000983	O Ring ID-9.8mm x OD-13mm x Thickness-1.8mm for System Switch (RCP203-3-9-4-17F-21146)	3	EA	Chiefdom Electronic	P78000983	-
27	32	P46011439	Silicon Gasket (NE-5270), Solid O Shaped, Soft, Dia 1.9mm, ± 0.1mm, Shore 50 ± 5A	258	mm	Smart Solutions	NE-5270	-

DPAR002014-R1A Field Telephone Set with Magneto And Auto Mode (RFT1001)				Document No.: 13132-DPAR002014		Rev.: A		
				Author: Sandeep Sharma		Date: 2026-04-10		
				Approved: Prafulla Sarode				
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*	Sub Assy
28	33	P46011439	Silicon Gasket (NE-5270), Solid O Shaped, Soft, Dia 1.9mm, ± 0.1 mm, Shore 50 $\pm$ 5A	630	mm	Smart Solutions	NE-5270	-
29	34	P78000804	Screw M3x15, SS, PH, CSK	4	EA	Kundan	P78000804	-
30	35	P78000447	Screw 6x12, SS, PH, CSK	1	EA	SK Industries	P78000447	-
31	36	P78000601	Screw M3x4, Brass, Slotted without head, Black	3	EA	Classic Auto	P78000601	-
32	37	P78001026	Screw 2.5x8, SS, PH, CSK	8	EA	SK Industries	P78001026	-
33	38	P78001281	Screw M2.5x6, SS, PH, PAN	21	EA	Classic Auto	P78001281	-
34	40	P78001282	Captive Screw M3x12, PH, PAN	12	EA	Kundan	P78001282	-
35	41	P46000437	Loctite248	5	g	Henkel	LOCTITE - 248	-
36	42	P46011189	Hitlock 533	5	g	Hitlock	P46011189	-
37	44	P78000039	Nut 2.5 mm	2	EA	Kndan	NUT000003	-
38	45	P78000026	Euro Screw 2.5x15, SS, Sloted Cheese Head	2	EA	Kndan	SCRW020527	-
39	46	P78000877	Screw 2x4, SS304, PH, PAN, Flange, Black	2	EA	Kndan	P78000877	-
40	A1	EBA30058	EBA30058, RFT1001 Control Card	1	SA	Elcom	EBA30058	EBA
41	A2	EBA30059	EBA30059, RFT1001 Ringer Card	1	SA	Elcom	EBA30059	EBA
42	A4	EBA30062	EBA30062, RFT1001 System Switch Card	1	SA	Elcom	EBA30062	EBA

DPAR002014-R1A Field Telephone Set with Magneto And Auto Mode (RFT1001)				Document No.: 13132-DPAR002014		Rev.: A		
				Author: Sandeep Sharma		Date: 2026-04-10		
				Approved: Prafulla Sarode				
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*	Sub Assy
43	S1	66085	RFT1001 Battery BOX Assembly	1	SA	Elcom	66085	SA
44	S2	66086	RFT1001 'TRV' TX_RX Volume Switch Assembly	1	SA	Elcom	66086	SA
45	S3	66087	RFT1001 Buzzer Assembly	1	SA	Elcom	66087	SA
46	S4	66088	RFT1001 'BZV' Buzzer Volume Assembly	1	SA	Elcom	66088	SA
47	S5	66089	RFT1001 BAT. MON. Switch Assembly	1	SA	Elcom	66089	SA
48	S6	66090	RFT1001 Ringer Micro Switch Assembly	1	SA	Elcom	66090	SA
49	S7	66091	RFT1001 Keypad Assembly	1	SA	Elcom	66091	WHA
50	S8	66071	LN' Line Cable Harness for RFT1001	1	SA	Elcom	66071	WHA
51	S12	66076	RG' Ringer PCB Cable Harness for RFT1001	1	SA	Elcom	66076	WHA
52	S15	66079	HS' Hook Switch Harness for RFT1001	1	SA	Elcom	66079	WHA
53	S16	66080	SS' System Switch Harness for RFT1001	1	SA	Elcom	66080	WHA
54	S18	66082	EB' Ext. Battery Cable Harness for RFT1001	1	SA	Elcom	66082	WHA
55	S19	66092	RFT1001 Handset 'HNST' Harness Assembly	1	SA	Elcom	66092	WHA

* Or equivalent

2.2 Part List of Electronics Cards

2.2.1 EBA30058, Control Card

EBA30058-R1A RFT1001 Control Card					Document No.: 13132-EBA30058		Rev.: A
					Author: Sandeep Sharma		Date: 2026-04-09
					Approved: Prafulla Sarode		
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P1/600209R0	PCB RFT1001 CONTROL CARD Rev. 1.00	1	EA	Incircuit Innovations	P1/600209R0
2	BT, BZ, HS, LN	P42400108	2 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	4	EA	WE	62000211622
3	BD1	P71100003	Bridge 200V RMB2S 200V,0.5A SMD	1	EA	VISHAY	RMB2S-E3/80
4	BZ-VOL_(BZV)	P42400109	3 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62000311622
5	C1 C2	P71401021	Chip Capacitor 33P +-5% 50V 0805	2	EA	AVX	08055A330JAT2A
6	C3 C22 C24	P71450150	Multilayer Ceramic Capacitors MLCC, XR7, 475P, +-10%, 100V, 1210	3	EA	KYOCERA AVX	KAM32LR72A475KU
7	C4	P71450146	Chip Capacitor 225P +-10% 100V 1210	1	EA	AVX	12101C225KAT
8	C5 C7	P71401074	Chip Capacitor 106P +-10% 50V 0805	2	EA	AVX	08055C106KAT2A
9	C6 C11	P71401061	Chip Capacitor 104P +-10% 50V 0805	2	EA	AVX	08055C104KAT2A

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
10	C8 C12 C30 C31	P71411061	Chip Capacitor 104P +-10% 25V 0603	4	EA	AVX	06033D104KAT2A
11	C9 C29	P71405057	Chip Aluminum 100U +-20 25V Smd	2	EA	NICHICON	UUX1E101MNR1GS
12	C10 C17 C36 C37 C38	P71411091	Chip Capacitor 102P +-5% 50V 0603	5	EA	AVX	06035A102JAT
13	C13 C14 C18 C28	P71420002	Chip Capacitor 102P +-10% 2000V 1206	4	EA	AVX	102-2000-1206-X7R-K
14	C15	P71411029	Chip Capacitor 100P +-10% 25V 0603	1	EA	AVX	06033D101KAT2A
15	C16 R44 R45	P72211005	Chip Resistance 0E 1% 0.125W,100V 0805	3	EA	VISHAY	CRCW08050000Z0EA
16	C19	P71411035	Chip Capacitor 330P +-10% 25V 0603	1	EA	AVX	06033D331KAT2A
17	C20	P71411108	Chip Capacitor, X7R 332P +-10% 50V 0603	1	EA	YAGEO	CC0603KRX7R9BB332
18	C21	P71404004	Chip Aluminum Low ESR 4U7 +-20% 35V Smd	1	EA	NICHICON	UUD1V4R7MCL1GS
19	C23 C32 C33 C34 C39	P71401072	Chip Capacitor 105P +-10% 50V 0805	5	EA	AVX	08055C105KAT2A
20	C25	P71411054	Chip Capacitor 103P +-10% 25V 0603	1	EA	AVX	06033D103KAT2A

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
21	C26	P71401087	Chip Capacitor 225P $\pm$ 10% 16V 0805	1	EA	KEMET	C0805C225K4RAC
22	C27	P71401041	Chip Capacitor 102P $\pm$ 5% 50V 0805	1	EA	AVX	08055A102JAT2A
23	C40	P71410029	Chip Capacitor 100P $\pm$ 10% 100V 1206	1	EA	AVX	
24	C41	P71411063	Chip Capacitor 224P $\pm$ 10% 25V 0603	1	EA	AVX	06033D224KAT2A
25	D1 D7	P71000001	Small Signal Diode LL4148 100V, 200mA MMELF	2	EA	Fairchild	LL4148
26	D3	P71000008	Schottky Barrier, 1N5819HW-7-F, 1A, 40V, SOD-123-2	1	EA	Diodes Incorporated	1N5819HW-7-F
27	HANDSET_(HNST) KEYPAD_(K)	P42400114	8 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	2	EA	WE	62000811622
28	L1	P71701219	2 Line Common Mode Choke Surface Mount-4P 7x6mm 1k? ω 100MHz, DCR 15m Ω , 3A SMD	1	EA	PROD Tech	PCAQ7060MW-102
29	L2	P71701220	10uH, 1.1A, Shielded Power Inductor, DCR-180m Ω , 4x4mm, SMD	1	EA	Bourns	SRN4012T-100M
30	L3 L6 L7	P71701077	Smd Ferrite Bead WE-CBF,2700 ohm,200mA,DCR=0.60 ohm 0805	3	EA	WE	742792095
31	L4 L5	P71701208	WE-TPC Shielded Drum Core Wirewound Inductor, 4.7uH, 900mA, DCR-90 m Ω , $\pm$ 30%, SMD	2	EA	WE	744031004

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
32	L8 L9	P71701213	Wire Wound SMD Power Inductor, 10mH, 75mA, DCR-45 Ohm, $\pm 20\%$, SMD	2	EA	Cjiang	FNR5040S103MT
33	L10	P71701013	Power Choke WE-PD2,3U3,2A,DCR=0.041ohm SMD 1812	1	EA	WE	744773033
34	LED_DISPLAY_(LD)	P42400112	6 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62000611622
35	Q1	P71300013	N, VCE 50V, 150 mA 2SC1815 50V SOT23	1	EA	ONSEMI/ PHILIPS	2SC1815
36	Q2	P71300014	VCE 160V, 600mA MMBT5551 160V, 600mA SOT23	1	EA	FAIRCHILD	MMBT5551
37	Q3	P71301013	PNP Silicon Epitaxial Transistor, -600 mA MMBT5401 -150V, -600mA SOT23	1	EA	FAIRCHILD	MMBT5401
38	R1	P72217136	Chip Resistance 560K 1% 0.25W, 200V 1206	1	EA	VISHAY	CRCW12065603FRT1
39	R2 R9	P72200107	Chip Resistance 100K 1% 0.125W,100V 0805	2	EA	VISHAY	CRCW08051003FRT1
40	R3	P72217039	Chip Resistance 100E 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206101JRT1
41	R4	P72200116	Chip Resistance 270K 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08052703FRT1
42	R5	P72217153	Chip Resistance 1M 1% 0.25W,200V 1206	1	EA	YAGEO	RC1206FR-071ML

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
43	R6	P72217107	Chip Resistance 100K 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206104JRT1
44	R7 R10	P72217108	Chip Resistance 120K 5% 0.25W, 200V 1206	2	EA	VISHAY	CRCW1206124JRT1
45	R8 R13	P72200065	Chip Resistance 1K 1% 0.125W,100V 0805	2	EA	VISHAY	CRCW08051001FRT1
46	R11 R31 R34	P72201072	Chip Resistance 2K7 5% 0.125W,100V 0805	3	EA	VISHAY	CR0805-JW-272
47	R12	P72217150	Chip Resistance 620E 1% 0.25W, 200V 1206	1	EA	VISHAY	CRCW12066200FRT1
48	R14	P72200096	Chip Resistance 33K 1% 0.125W, 100V 0805	1	EA	Bourns	CR0805-FX-3302
49	R15	P72202071	Chip Resistance 2K2 5% 0.125W,100V 1206	1	EA	VISHAY	CRCW1206222JRT1
50	R16	P72200026	Chip Resistance 22E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW080522R0FRT1
51	R17	P72201059	Chip Resistance 620E 5% 0.1W,100V 0805	1	EA	VISHAY	CRCW0805621JRT1
52	R20 R32	P72219109	Chip Resistance 130K 1% 0.1W,100V 0603	2	EA	VISHAY	CRCW06031303FRT1
53	R21	P72219085	Chip Resistance 10K 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06031002FRT1

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
54	R22	P72219104	Chip Resistance 82K 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06038202FRT1
55	R23	P72219065	Chip Resistance 1K 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06031001FRT1
56	R24	P72220023	Chip Resistance 3K92 1% 0.1W,100V 0603	1	EA	VISHAY	
57	R28	P72200053	Chip Resistance 360E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08053900FRT1
58	R29	P72219102	Chip Resistance 68K 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06036802FRT1
59	R30	P72211023	Chip Resistance 3K92 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08053921FRT1
60	R33	P72219042	Chip Resistance 130E 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06031300FRT1
61	R35	P72200020	Chip Resistance 10E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW080510R0FRT1
62	R36	P72220030	Chip Resistance 6K2 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06038201FRT1
63	R37	P72219084	Chip Resistance 9K1 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06039101FRT1
64	R38 R40	P72219107	Chip Resistance 100K 1% 0.1W,100V 0603	2	EA	VISHAY	CRCW06031003FRT1

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
65	R39	P72200047	Chip Resistance 220E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08052200FRT1
66	R41	P72200040	Chip Resistance 110E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08051100FRT1
67	R42	P72200050	Chip Resistance 300E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08053000FRT1
68	R43 R47	P72211079	Chip Resistance 0E 1% 0.25W,100V 1206	2	EA	VISHAY	CRCW12060000Z0EA
69	R46	P72200085	Chip Resistance 10K 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08051002FRT1
70	R48	P72219091	Chip Resistance 20K 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06032002FRT1
71	R49	P72219063	Chip Resistance 820E 1% 0.1W,100V 0603	1	EA	VISHAY	CRCW06038200FRT1
72	RING_PCB_(RG)	P42400111	5 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62000511622
73	RING_SW_(RS)	P42400116	10 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62001011622
74	SYSTEM_SW_(SS)	P72107261	2x8, 16 Position, Double Row, BTB, Male, 2.54mm, Vertical Box Header, Leaded	1	EA	WE	612016235121
75	TVS1	P71201049	TVS Diode, Bi-directional, SMBJ250CA, 250V, DO-214AA	1	EA	Little Fuse	SMBJ250CA

EBA30058-R1A RFT1001 Control Card				Document No.: 13132-EBA30058		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-09	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
76	TX/RX-VOL_(TRV)	P42400113	7 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62000711622
77	U1	P71550006	Tone/Pulse Dialler with Flash Function IL91214AD 5V SOIC16	1	EA	IK Semiconductor	IL91214AD
78	U2	P71580201	Telephone Tone Ringer with Bridge Diode IL2418D SOP8	1	EA	IK Semiconductor	IL2418D
79	U3	P71513101	Low Voltage Telephone Transmission Circuit with Dialler Interface, TEA1062ANG-S16-R, SOIC\16	1	EA	UTC	TEA1062ANG-S16-R
80	U4	P71513095	AP3012KTR-E1, High Power Step-Up Boost Switching Regulator IC, Positive, Adjustable, 500mA, SOT-23-5	1	EA	Diodes Incorporated	AP3012KTR-E1
81	XT1	P71601004	Crystal 3.579545MHz 10ppm 5V HC-49/S	1	EA	AEL	49S2HFM110P003M57 9545
82	ZPD1	P71200006	Zener 5V1 TZM5231BGS08 5% 5V1 MMELF	1	EA	VISHAY	TZM5231BGS08
83	ZPD2	P71201050	TVS Diode, Uni-directional, SMBJ15A, 15V, DO-214AA	1	EA	Little Fuse	SMBJ15A
84	C35 D2 R18 R19 R25 R26 R27	P99999999	DO_NOT_MOUNT	7	EA		P99999999

* Or equivalent

2.2.2 EBA30059, Ringer Card

EBA30059-R1A RFT1001 Ringer Card				Document No.: 13132-EBA30059		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-07	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P2/600209R0	PCB RFT1001 RINGER CARD Rev. 1.00	1	EA	Incircuit Innovations	P2/600209R0
2	B2 EB	P42400108	2 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	2	EA	WE	62000211622
3	BR1	P71100003	Bridge 200V RMB2S 200V,0.5A SMD	1	EA	VISHAY	RMB2S-E3/80
4	C1 C6	P71420004	Chip Capacitor 103P +-10% 500V 1210	2	EA	AVX	12107C103KAT2A
5	C2 C3 C5 C11	P71420002	CHIP Capacitor 102P +-10% 2000V 1206	4	EA	AVX	102-2000-1206-X7R-K
6	C4 C9	P71401054	CHIP Capacitor 103P +-10% 50V 0805	2	EA	AVX	08055C103KAT2A
7	C7 C10 DC3 DC4	P71401061	CHIP Capacitor 104P +-10% 50V 0805	4	EA	AVX	08055C104KAT2A
8	C8	P71403077	Chip Tantalum Capacitor 220U +-10% 16V 7343H	1	EA	AVX	TAJE227K016RNJ
9	C12 C13	P71490065	Multilayer Chip Ceramic Capacitor 334P +-10% 500V 1812	2	EA	KEMET	C1812C334KCRACU
10	CONN1	P42400109	3 Pin, 2mm, Single Row, Plug, Pin (Male), Vertical Shrouded Header, 2A, 125 VAC, Leaded	1	EA	WE	62000311622
11	D1 D2 D3 D5	P71000001	Small Signal Diode LL4148 100V, 200mA MMELF	4	EA	Fairchild	LL4148
12	D6 D7	P71000022	Surface Mount Fast Avalanche Rectifiers AR1PM 1000V,1A DO-220AA (SMP)	2	EA	VISHAY	AR1PMHM3/84A

EBA30059-R1A RFT1001 Ringer Card				Document No.: 13132-EBA30059		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-07	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
13	D8	P71000002	Diode Rectifier SM4007 700V,1A MELF	1	EA	DIOTEC	SM4007
14	L4 L6 L7	P71701076	Smd Ferrite Bead WE-CBF,300 ohm,3000mA,DCR=0.05 ohm 0805	3	EA	WE	742792031
15	L8 L9	P71701069	Smd Ferrite Bead WE-CBF, 600 ohm, 3000mA 1812	2	EA	WE	742792514
16	OP_TR2	P71300024	Transistor NPN, ZXTN4004KTC, 150V, 1A, hFE 100 , TO252 (DPAK)	1	EA	DIODES	ZXTN4004KTC
17	P1	P72209019	5 mm Square Surface Mount Miniature Trimmers Single-Turn Cermet 200K 5mm 10% 0.25W,200V SMD	1	EA	VISHAY	TS5YJ204KR10
18	R1 R3	P72217059	Chip Resistance 620E 5% 0.25W, 200V 1206	2	EA	VISHAY	CRCW1206621JRT1
19	R2	P72217063	Chip Resistance 820E 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206821JRT1
20	R4	P72217099	Chip Resistance 47K 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206473JRT1
21	R5	P72200094	CHIP Resistance 27K 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08052702FRT1
22	R6 R7 R8	P72200071	CHIP Resistance 2K2 1% 0.125W,100V 0805	3	EA	VISHAY	CRCW08052201FRT1
23	R9	P72200063	Chip Resistance 820E 1% 0.125W,100V 0805	1	EA	VISHAY	CRCW08058200FRT1
24	R11 R12	P72211079	Chip Resistance 0E 1% 0.25W,100V 1206	2	EA	VISHAY	CRCW12060000Z0EA
25	T1	P45010066	AFT1001 Ringer Transformer SMD	1	EA	PULSE	P45010066
26	TR1	P71300011	VCE 40V , 200mA MMBT3904LT1G 40V SOT23	1	EA	ONSEMI	MMBT3904LT1G

EBA30059-R1A RFT1001 Ringer Card				Document No.: 13132-EBA30059		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-04-07	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
27	TR3	P71301014	High Voltage PNP Silicon Power Transistor, 1A MJD5731T4G 350V, 1A DPAK	1	EA	ONSEMI	MJD5731T4G
28	TR4 TR5	P71300015	High Voltage Power Transistor, 1A MJD47G 250V, 1A DPAK	2	EA	ONSEMI	MJD47G
29	U1	P71580105	Timer (Industrial) SA555D 5V SOP-8	1	EA	FAIRCHILD	SA555D
30	U2	P71580117	LOW POWER MONOSTABLE/ASTABLE MULTIVIBRATOR CD4047BM96 SOIC14	1	EA	TI	CD4047BM96
31	C14 PS1 R10 TR2	P99999999	DO_NOT_MOUNT	4	EA		P99999999

* Or equivalent

2.2.3 EBA30060, Ringer Micro Switch Card

EBA30060 RFT1001 Ringer Micro Switch Card					Document No.: 13132-EBA30060		Rev.: A
					Author: Sandeep Sharma		Date: 2026-03-16
					Approved: Prafulla Sarode		
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P3/600209R0	PCB RFT Ringer Micro Switch Card Rev. 1.00	1	EA	Incircuit Innovations	P3/600209R0
2	A, B, C, D	P72108049	KW10-CZ0P075, Mini Micro Switch SPDT, No Lever, Black, OFF-(ON), 3Pin, 1A 250VAC / 3A 125VAC, PCB Terminal, Leaded	4	EA	Evelta / Daier	KW10-CZ0P075
3	J1	P99999999	DO_NOT_MOUNT	1	EA		

* Or equivalent

2.2.4 EBA30062, System Switch Card

EBA30062 System Switch Card				Document No.: 13132-EBA30062		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-16	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P5/600209R0	PCB RFT System Switch Card Rev. 1.00	1	EA	Incircuit Innovations	P5/600209R0
2	SW1	P72108053	System Switch SS6P4T, 6 Pole, 4 Pos. for RFT1001	1	EA		SS6P4T
3	J1	P72107261	2x8, 16 Position, Double Row, BTB, Male, 2.54mm, Vertical Box Header, Leaded	1	EA	WE	6.12016E+11

* Or equivalent

2.2.5 EBA30063, BAT MON Switch Card

EBA30063 BAT. MON. Switch Card				Document No.: 13132-EBA30063			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-16
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P6/600209R0	PCB RFT1001 BAT MON Switch Card Rev. 1.00	1	EA	Incircuit Innovations	P6/600209R0
2	D1, D2, D3, D4, D5, D6	P71000001	Small Signal Diode LL4148 100V, 200mA MMELF	6	EA	Fairchild	LL4148
3	D7, D8	P71000002	Diode Rectifier SM4007 700V,1A MELF	2	EA	DIOTEC	SM4007
4	G	P72100001	LED 3mm Green 5V Leaded	1	EA	Kwality	KL-33 GD
5	R, P	P72100002	LED 3mm Red 5V Leaded	2	EA	Kwality	KL-33 HD
6	RV, P\$2F\$T	P72100010	LED 3mm Yellow 5V Leaded	2	EA	Kwality	KL-33 YD
7	Q1	P71300001	VCE 65V,100MA BC846A 65V SOT23	1	EA	NXP	BC846A,235
8	R1	P72217039	Chip Resistance 100E 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206101JRT1
9	R2, R4	P72202051	Chip Resistance 330E 5% 0.125W,100V 1206	2	EA	VISHAY/Walsin/Uni-royal/FH	CRCW1206331JRT1
10	R3	P72217076	Chip Resistance 3K9 5% 0.25W, 200V 1206	1	EA	VISHAY	CRCW1206392JRT1
11	R5	P72202047	Chip Resistance 220E 5% 0.125W,100V 1206	1	EA	VISHAY/Walsin/Uni-royal/FH	CRCW1206221JRT1
12	SW	P72108046	Tact Switch, SMT Type, SPST, 6x6, Hight 7mm, 50mA, 12V DC SMD	1	EA	XUNPU	TS-1002S-07026C

* Or equivalent

2.2.6 EBA30065, Volume Switch Card

EBA30065 Volume Switch Card				Document No.: 13132-EBA30065		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-16	
				Approved: Prafulla Sarode			
S/N	REF. DES	ITEM ID	DESCRIPTION	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	15	P8/600209R0	PCB RFT Volume Switch Card Rev. 1.00	1	EA	Incircuit Innovations	P8/600209R0
2	SW1	P72108054	Volume Switch SS2P3T, 2 Pole, 3 Pos. for RFT1001	1	EA		SS2P3T
3	J1	P99999999	DO_NOT_MOUNT	1	EA		

* Or equivalent

2.3 Part List of Wire Harnesses

2.3.1 66071, 'LN' Line Cable Harness

66071 'LN' Line Cable Harness				Document No.: 13132-66071			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000487	Receptacle Housing, 1x2, 2mm	1	EA	WE	620 002 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	2	EA	WE	620 001 137 22
3	3	P46011440	Marking Sleeve, LN, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011440
4	4	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Color	90	mm	RJ Industrial Corp.	P46002206
6	6	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Color	90	mm	RJ Industrial Corp.	P46002208
7	7	P46000536	Zero Clip 4mm	2	EA	SK Industries / PTPL	P46000536
8	8	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499
9	9	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499

* Or equivalent

2.3.2 66072, 'BT' Battery Box Harness

66072 'BT' Battery Box Harness				Document No.: 13132-66072		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000487	Receptacle Housing, 1x2, 2mm	1	EA	WE	620 002 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	2	EA	WE	620 001 137 22
3	3	P46011441	Marking Sleeve, BT, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011441
4	4	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Color	70	mm	RJ Industrial Corp.	P46002206
6	6	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Color	70	mm	RJ Industrial Corp.	P46002208
7	7	P46000536	Zero Clip 4mm	2	EA	SK Industries / PTPL	P46000536
8	8	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499
9	9	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499

* Or equivalent

2.3.3 66073, 'TRV' Volume Switch Harness

66073 'TRV' TX_RX Volume Switch Harness				Document No.: 13132-66073			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000596	7 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 007 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	7	EA	WE	620 001 137 22
3	3	P46011442	Marking Sleeve, TX/RX-VOL, Yellow, 4mm Dia, Length-25mm	1	EA	Woer	P46011442
4	4	P46000413	Shrink Sleeve - 5 mm, Transparent	35	mm	Woer	P46000415
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	100	mm	RJ Industrial Corp.	RJ050130111S-0
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	100	mm	RJ Industrial Corp.	RJ050130111S-1
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	100	mm	RJ Industrial Corp.	RJ050130111S-2
8	8	P46002209	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Orange Colour	100	mm	RJ Industrial Corp.	RJ050130111S-3
9	9	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	100	mm	RJ Industrial Corp.	RJ050130111S-4
10	10	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	100	mm	RJ Industrial Corp.	RJ050130111S-5
11	11	P46002212	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, White Colour	100	mm	RJ Industrial Corp.	RJ050130111S-9

* Or equivalent

2.3.4 66074, 'BZ' Buzzer Harness

66074 'BZ' Buzzer Harness				Document No.: 13132-66074			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000487	Receptacle Housing, 1x2, 2mm	1	EA	WE	620 002 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	2	EA	WE	620 001 137 22
3	3	P46011443	Marking Sleeve, BZ, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011443
4	4	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	150	mm	RJ Industrial Corp.	P46002206
6	6	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	150	mm	RJ Industrial Corp.	P46002208

* Or equivalent

2.3.5 66075, 'BZV' Buzzer Volume Harness

66075 'BZV' Buzzer Volume Harness				Document No.: 13132-66075		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000488	3 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 003 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	3	EA	WE	620 001 137 22
3	3	P46011444	Marking Sleeve, BZ-VOL, Yellow, 3.2mm Dia, Length-20mm	1	EA	Woer	P46011444
4	4	P46000415	Transparent Shrink Sleeve Dia 4 mm	30	mm	Woer	P46000415
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	100	mm	RJ Industrial Corp.	RJ050130111S-0
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	100	mm	RJ Industrial Corp.	RJ050130111S-1
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	100	mm	RJ Industrial Corp.	RJ050130111S-2

* Or equivalent

2.3.6 66076, 'RG' Ringer PCB Cable Harness

66076 'RG' Ringer PCB Cable Harness				Document No.: 13132-66076			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000859	5 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 005 113 322
2	2	P78000487	2 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 002 113 322
3	3	P78000488	3 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 003 113 322
4	4	P78000273	Crimp Contact, Female, 2mm	10	EA	WE	620 001 137 22
5	5	P46011445	Marking Sleeve, RG, Yellow, 3.2mm Dia, Length-20mm	1	EA	Woer	P46011445
6	6	P46011446	Marking Sleeve, CONN1, Yellow, 2.5mm Dia, Length-25mm	1	EA	Woer	P46011446
7	7	P46011447	Marking Sleeve, B2, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011447
8	8	P46000415	Transparent Shrink Sleeve Dia 4 mm	30	mm	Woer	P46000415
9	9	P46000497	Transparent Shrink Sleeve Dia 3 mm	35	mm	Woer	P46000497
10	10	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
11	11	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	220	mm	RJ Industrial Corp.	RJ050130111S-0
12	12	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	220	mm	RJ Industrial Corp.	RJ050130111S-2

66076 'RG' Ringer PCB Cable Harness				Document No.: 13132-66076		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
13	13	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	220	mm	RJ Industrial Corp.	RJ050130111S-4
14	14	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	220	mm	RJ Industrial Corp.	RJ050130111S-5
15	15	P46002213	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Blue Colour	220	mm	RJ Industrial Corp.	RJ050130111S-6

* Or equivalent

2.3.7 66077, 'LD' LED Display (BAT. MON.) Cable Harness

66077 'LD' LED Display (BAT. MON.) Cable Harness				Document No.: 13132-66077			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000595	6 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 006 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	6	EA	WE	620 001 137 22
3	3	P46011448	Marking Sleeve, LED-DISPLAY., Yellow, 4mm Dia, Length-35mm	1	EA	Woer	P46011448
4	4	P46000413	Shrink Sleeve - 5 mm, Transparent	40	mm	Woer	P46000415
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	90	mm	RJ Industrial Corp.	RJ050130111S-0
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	90	mm	RJ Industrial Corp.	RJ050130111S-1
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	90	mm	RJ Industrial Corp.	RJ050130111S-2
8	8	P46002209	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Orange Colour	90	mm	RJ Industrial Corp.	RJ050130111S-3
9	9	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	90	mm	RJ Industrial Corp.	RJ050130111S-4
10	10	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	90	mm	RJ Industrial Corp.	RJ050130111S-5

* Or equivalent

2.3.8 66078 'RS' Ringer Switch Harness

66078, 'RS' Ringer Switch Harness				Document No.: 13132-66078			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000489	10 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 010 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	10	EA	WE	620 001 137 22
3	3	P46011449	Marking Sleeve, RS, Yellow, 5mm Dia, Length-20mm	1	EA	Woer	P46011449
4	4	P46000480	Transparent Shrink Sleeve Dia 6 mm	30	mm	Woer	P46000480
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	80	mm	RJ Industrial Corp.	RJ050130111S-0
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	80	mm	RJ Industrial Corp.	RJ050130111S-1
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	80	mm	RJ Industrial Corp.	RJ050130111S-2
8	8	P46002209	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Orange Colour	80	mm	RJ Industrial Corp.	RJ050130111S-3
9	9	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	80	mm	RJ Industrial Corp.	RJ050130111S-4
10	10	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	80	mm	RJ Industrial Corp.	RJ050130111S-5
11	11	P46002212	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, White Colour	80	mm	RJ Industrial Corp.	RJ050130111S-9

66078, 'RS' Ringer Switch Harness				Document No.: 13132-66078		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
12	12	P46002213	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Blue Colour	80	mm	RJ Industrial Corp.	RJ050130111S-6
13	13	P46002214	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Violet Colour	80	mm	RJ Industrial Corp.	RJ050130111S-7
14	14	P46002215	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Pink Colour	80	mm	RJ Industrial Corp.	RJ050130111S-Pink

* Or equivalent

2.3.9 66079, Hook Switch Harness

66079 'HS' Hook Switch Harness Assembly				Document No.: 13132-66079		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P72108055	Cradle Switch for RFT1001	1	EA	P72108055	Sun Micro
2	2	P78000487	Receptacle Housing, 1x2, 2mm	1	EA	WE	620 002 113 322
3	3	P78000273	Crimp Contact, Female, 2mm	2	EA	WE	620 001 137 22
4	4	P46011450	Marking Sleeve, HS, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011450
5	5	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
6	6	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	120	mm	RJ Industrial Corp.	P46002206
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	120	mm	RJ Industrial Corp.	P46002208
8	8	P46000499	Transparent Shrink Sleeve Dia 2 mm	20	mm	Woer	P46000499
9	9	P46000499	Transparent Shrink Sleeve Dia 2 mm	20	mm	Woer	P46000499

* Or equivalent

2.3.10 66080, 'SS' System Switch Harness

66080 'SS' System Switch Harness				Document No.: 13132-66080		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P42670104	16 Pin (2x8) FRC Socket (Female) Connector, Pitch-2.54mm, Cable Mount	2	EA	WE	61201623021
2	2	P46000069	16 Core Ribbon Flat Cable (FRC), Pitch-1.27mm	100	mm	WE	63911615521

* Or equivalent

2.3.11 66081, 'KP' Keypad Cable Harness

66081 'KP' Keypad Cable Harness				Document No.: 13132-66081		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000272	8 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 008 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	8	EA	WE	620 001 137 22
3	3	P46011451	Marking Sleeve, KP, Yellow, 5mm Dia, Length-20mm	1	EA	Woer	P46011451
4	4	P46000480	Transparent Shrink Sleeve Dia 6 mm	30	mm	Woer	P46000480
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	80	mm	RJ Industrial Corp.	RJ050130111S-0
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	80	mm	RJ Industrial Corp.	RJ050130111S-1
7	7	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	80	mm	RJ Industrial Corp.	RJ050130111S-2
8	8	P46002209	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Orange Colour	80	mm	RJ Industrial Corp.	RJ050130111S-3
9	9	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	80	mm	RJ Industrial Corp.	RJ050130111S-4
10	10	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	80	mm	RJ Industrial Corp.	RJ050130111S-5
11	11	P46002212	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, White Colour	80	mm	RJ Industrial Corp.	RJ050130111S-9

66081 'KP' Keypad Cable Harness				Document No.: 13132-66081		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
12	12	P46002213	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Blue Colour	80	mm	RJ Industrial Corp.	RJ050130111S-6

* Or equivalent

2.3.12 66082, 'EB' Ext. Battery Cable Harness

66082 'EB' Ext. Battery Cable Harness				Document No.: 13132-66082		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P78000487	Receptacle Housing, 1x2, 2mm	1	EA	WE	620 002 113 322
2	2	P78000273	Crimp Contact, Female, 2mm	2	EA	WE	620 001 137 22
3	3	P46011452	Marking Sleeve, EB, Yellow, 2.5mm Dia, Length-20mm	1	EA	Woer	P46011452
4	4	P46000497	Transparent Shrink Sleeve Dia 3 mm	30	mm	Woer	P46000497
5	5	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	220	mm	RJ Industrial Corp.	P46002206
6	6	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	220	mm	RJ Industrial Corp.	P46002208
7	7	P46000536	Zero Clip 4mm	2	EA	SK Industries	P46000536
8	8	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499
9	9	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499

* Or equivalent

2.3.13 66083, 'Battery Box Assembly Harness-2

66083 'Battery Box Assembly Harness-2				Document No.: 13132-66083		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P46000392	Zero Clip 3mm	2	EA	Connectwell	P46000392
2	2	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	110	mm	RJ Industrial Corp.	P46002206
3	3	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499
4	4	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499

* Or equivalent

2.3.14 66084, 'Battery Box Assembly Harness-3

66084 'Battery Box Assembly Harness-3				Document No.: 13132-66084		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P46000392	Zero Clip 3mm	2	EA	Connectwell	P46000392
2	2	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	50	mm	RJ Industrial Corp.	P46002208
3	3	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499
4	4	P46000499	Transparent Shrink Sleeve Dia 2 mm	25	mm	Woer	P46000499

* Or equivalent

2.4 Part List of Mechanical Sub-Assemblies

2.4.1 66085, Battery Box Assembly

66085 Battery BOX Assembly				Document No.: 13132-66085			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P46100309	Battery Box for RFT1001	1	EA	PTPL	P46100309
2	2	66072	'BT' Battery Box Harness for RFT1001	1	SA	Elcom	66072
3	3	66083	'Battery Box Assembly Harness-2 for RFT1001	1	SA	Elcom	66083
4	4	66084	Battery Box Assembly Harness-3 for RFT1001	1	SA	Elcom	66084

* Or equivalent

2.4.2 66086, Volume Switch Assembly

66086 Volume Switch Assembly				Document No.: 13132-66086		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	EBA30065	RFT1001 Volume Switch Card	1	SA	Elcom	EBA30065
2	2	66073	'TRV' TX_RX Volume Switch Harness for RFT1001	1	SA	Elcom	66073

* Or equivalent

2.4.3 66087, Buzzer Assembly

66087 Buzzer Assembly				Document No.: 13132-66087			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P46100312	Buzzer for RFT1001	1	EA	Sun Micro	P46100312
2	2	66074	'BZ' Buzzer Harness for RFT1001	1	SA	Elcom	66074

* Or equivalent

2.4.4 66088, Buzzer Volume Assembly

66088 Buzzer Volume Assembly				Document No.: 13132-66088			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	EBA30065	RFT1001 Volume Switch Card	1	SA	Elcom	EBA30065
2	2	66075	'BZV' Buzzer Volume Harness for RFT1001	1	SA	Elcom	66075

* Or equivalent

2.4.5 66089, BAT MON Switch Assembly

66089 BAT MON Switch Assembly				Document No.: 13132-66089			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	EBA30063	RFT1001 BAT. MON. Switch Card	1	SA	Elcom	EBA30063
2	2	66077	'LD' LED Display (BAT. MON.) Cable Harness for RFT1001	1	SA	Elcom	66077

* Or equivalent

2.4.6 66090, BAT MON Switch Assembly

66090 Ringer Micro Switch Assembly				Document No.: 13132-66090		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	EBA30060	RFT1001 Ringer Micro Switch Card	1	SA	Elcom	EBA30060
2	2	66078	'RS' Ringer Switch Harness for RFT1001	1	SA	Elcom	66078

* Or equivalent

2.4.7 66091, Keypad Assembly

66091 Keypad Assembly				Document No.: 13132-66091		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P7/600209R0	PCB RFT Keypad 4X4 Card Rev. 1.00	1	EA	Incircuit Innovations	P7/600209R0
2	F1, F2, K0, K1, K2, K3, K4, K5, K6, K7, K8, K9, K#, K*, P, R	P72108047	12.2-4-LEG-D-280, 4 Leg Metal Dome Switch, Stainless Steel with Single-Side Gold-Plated, Dia-12mm, Thickness-0.1mm	16	EA	QTS	12.2-4-LEG-D-280
3	2	P46011453	Cello Tape, Transparent, Width 0.5 inch	250	mm	Generic	-
4	3	P46011420	4x4 Keypad Sticker for RFT1001	1	EA	Woer	P46011420
5	4	66081	KP' Keypad Cable Harness for RFT1001	1	SA	Elcom	66081
6	5	P46100306	Keypad Plate for RFT1001	1	EA	PTPL	P46100306
7	6	P46011189	Hitlock 533	5	g	Hitlock	P46011189

* Or equivalent

2.4.8 66092, Handset 'HNST' Harness Assembly

66092 Handset 'HNST' Harness Assembly				Document No.: 13132-66092			Rev.: A
				Author: Sandeep Sharma			Date: 2026-03-31
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
1	1	P46002141	FT 8 Pin Circular Socket Male for handset Socket Assembly	1	EA	Gillard Electronics	984 - P8RM
2	2	P78000272	8 Pin 2mm Female Terminal Housing WR-WTB	1	EA	WE	620 008 113 322
3	3	P78000273	Crimp Contact, Female, 2mm	8	EA	WE	620 001 137 22
4	4	P46011456	Marking Sleeve, HNST, Yellow, 5mm Dia, Length-25mm	1	EA	Woer	P46011456
5	5	P46000480	Transparent Shrink Sleeve Dia 6 mm	30	mm	Woer	P46000480
6	6	P46002207	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Brown Colour	80	mm	SSI Cables	267SET6_1
7	7	P46002211	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Green Colour	80	mm	SSI Cables	267SET6_5
8	8	P46002208	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Red Colour	80	mm	SSI Cables	267SET6_2
9	9	P46002206	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Black Colour	80	mm	SSI Cables	267SET6_0
10	10	P46002213	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Blue Colour	80	mm	SSI Cables	267SET6_6
11	11	P46002212	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, White Colour	80	mm	SSI Cables	267SET6_9
12	12	P46002210	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Yellow Colour	80	mm	SSI Cables	267SET6_4
13	13	P46002227	PTFE Insulated Silver Plated Copper Conductor Wire, AWGm26/7/34 OR 7/0.16 mm, ET Type, Gray Colour	80	mm	SSI Cables	267SET6_8
14	14	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499

66092 Handset 'HNST' Harness Assembly				Document No.: 13132-66092		Rev.: A	
				Author: Sandeep Sharma		Date: 2026-03-31	
				Approved: Prafulla Sarode			
S/N	Ref. Des.	Item Id	Description	QTY	UOM	Manufacturer*	Manuf. Part No.*
15	15	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
16	16	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
17	17	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
18	18	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
19	19	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
20	20	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499
21	21	P46000499	Shrink Sleeve - 2mm, Transparent	15	mm	Woer	P46000499

* Or equivalent

Notes: