

SITE PROCEDURE SOP-ELEC-07 REV 4
ELECTRICAL ISOLATION AND MCC ACCESS

1. SCOPE

This procedure applies to all work on motor control centers (MCC), including opening any MCC bucket, resetting breakers, and inspecting motor starters or drives.

2. LOCKOUT/TAGOUT (LOTO) - MANDATORY

Lockout/Tagout is required before opening any MCC bucket.

Steps:

- 2.1 Obtain a LOTO permit from the shift supervisor.
- 2.2 Identify the isolation point on the drawing (breaker or disconnect).
- 2.3 Open, lock and tag the breaker. Apply personal lock.
- 2.4 Verify zero energy with a rated tester at the bucket terminals.
- 2.5 Record permit number and isolation verification on the permit.

3. RESET AND RE-ENERGIZATION

- 3.1 Breaker or drive resets require supervisor authorization.
- 3.2 A completed LOTO permit must be attached to the work order.
- 3.3 After reset, monitor the first start from a safe position.

4. ESCALATION

If a fault trips again after one authorized reset, stop work and escalate to the reliability engineer. Do not attempt repeated resets.