# Home Work #1

#### Ali BaniAsad 401209244

November 18, 2022

# 1 Question 1

$$f_X(x) = \frac{ab}{b^2 + x^2}, \quad b > 0$$

## 1.1 part a

$$\int_{-\infty}^{+\infty} f(x)dx = 1 \quad \to \quad \int_{-\infty}^{+\infty} \frac{ab}{b^2 + x^2} dx = 1 \to a \arctan(\frac{x}{b}) \Big|_{-\infty}^{+\infty} = 1 \to a\pi = 1 \to a = \frac{1}{\pi}$$
$$f_X(x) = \frac{1}{\pi} \frac{b}{b^2 + x^2}, \quad b > 0$$

#### 1.2 part b

$$E(X) = \mu_X = \int_{-\infty}^{+\infty} x f(x) dx$$

Because xf(x) is an odd function, the result of the integrator between  $\infty$  and  $-\infty$  is zero.

$$\int_{-\infty}^{+\infty} x f(x) dx = 0 \to \mu_X = 0$$

$$\sigma_X^2 = E((X - \mu)^2) = \int_{-\infty}^{+\infty} (x - \mu)^2 f(x) dx = \int_{-\infty}^{+\infty} x^2 f(x) dx = \left. \frac{b}{\pi} (x - b \arctan(\frac{x}{b})) \right|_{-\infty}^{+\infty} \neq \text{finite}$$

# 2 Question 3

A positive test is A event: P(A), Having the flu is B event: P(B) = 0.05

Ali BaniAsad 401209244 2.1 part a

#### 2.1 part a

The probability of a positive test if someone has flu:

$$P(A|B) = 0.99$$

The probability of a positive test if someone doesn't have flu:

$$P(A|\bar{B}) = 0.01$$

$$P(A) = P(A \cap B) + P(A \cap \bar{B}) = P(A|B)P(B) + P(A|\bar{B})P(\bar{B}) = 0.99 \times 0.05 + 0.01 \times 0.95 = 0.059$$

$$P(A|B)P(B) = P(B|A)P(A) \to P(B|A) = \frac{P(A|B)P(B)}{P(A)} = 0.84$$

### 2.2 part b

C is the event when two positive tests happen. The probability of two positive tests if someone has flu:

$$P(B)P(A|B)P(A|B) = 0.049$$

The probability of two positive tests if someone doesn't have flu:

$$P(\bar{B})P(A|\bar{B})P(A|\bar{B}) = 9.5 \times 10^{-5}$$

$$P(C) = P(B)P(A|B)P(A|B) + P(\bar{B})P(A|\bar{B})P(A|\bar{B}) = 0.0491$$

$$P(B|C) = \frac{P(B \cap C)}{P(C)} = 0.998$$

# 3 Question 4

Assumed that the random variables  $A \phi$  are independent and  $\phi$  is uniform in the interval  $[0, 2\pi)$ , mean and variance of  $\phi$  is 0 and  $\sigma^2$ , respectively.

$$x(t) = A\cos(\omega t + \phi)$$

3.1 part a

$$E\left[x(t)\right] = E\left[A\cos(\omega t + \phi)\right] \xrightarrow{uncorrelated} E\left[x(t)\right] = E[A]E\left[\cos(\omega t + \phi)\right] = 0 \xrightarrow{E[A]=0} E\left[x(t)\right] = 0$$

3.2 part b

$$R_X(t_1, t_2) = E[x(t_1)x(t_2)] = \frac{1}{2}E[A^2]E[\cos\omega(t_1 - t_2) + \cos(\omega t_1 + \omega t_2 + 2\phi)]$$
$$E[\cos(\omega t_1 + \omega t_2 + 2\phi)] = \frac{1}{2\pi} \int_0^{2\pi} \cos(\omega t_1 + \omega t_2 + 2\phi)d\phi = 0$$
$$R_X(t_1, t_2) = \frac{\sigma^2}{2}\cos\omega(t_1 - t_2)$$

Ali BaniAsad 401209244 3.3 part c

#### 3.3 part c

$$A[x(t)] = \lim_{T \to \infty} \frac{1}{2T} \int_{-T}^{T} x(t)dt \to A[x(t)] = \frac{1}{2\pi} \int_{0}^{2\pi} A\cos(\omega t + \phi)dt = \left. \frac{A\sin(\phi + \omega t)}{\omega} \right|_{0}^{2\pi}$$
$$A[x(t)] = \frac{A\sin(\phi + 2\pi\omega)}{\omega}$$

### 3.4 part d

$$R[x(t),\tau] = A[x(t)x(t+\tau)] = \lim_{T\to\infty} \frac{1}{2T} \int_{-T}^T x(t)x(t+\tau)dt = \frac{1}{2\pi} \int_0^{2\pi} A^2 \cos(\omega t + \phi) \cos(\omega (t+\tau) + \phi)dt$$

$$\int \cos(\omega t + \phi) \cos(\omega (t + \tau) + \phi) dt = \begin{cases} A^2 t \cos(\phi)^2 & \text{if } \omega = 0\\ \frac{A^2 t \cos(\omega \tau)}{2} + \frac{A^2 \sin(2\phi + 2\omega t + \omega \tau)}{4\omega} & \text{if } \omega \neq 0 \end{cases}$$

$$\int_{0}^{2\pi} \cos(\omega t + \phi) \cos(\omega (t + \tau) + \phi) dt = \begin{cases} 2\pi A^{2} \cos(\phi)^{2} & \text{if } \omega = 0 \\ \frac{A^{2} \left(\sin\left(2\phi + 4\pi\omega + \omega\tau\right) - \sin\left(2\phi + \omega\tau\right)\right)}{4\omega} + \pi A^{2} \cos(\omega\tau) & \text{if } \omega \neq 0 \end{cases}$$

$$R[x(t),\tau] = \begin{cases} 1 A^2 \cos\left(\phi\right)^2 & \text{if } \omega = 0 \\ 0.5 A^2 \cos\left(\omega\,\tau\right) - \frac{0.04 \,A^2 \left(1\,\sin\left(2\,\phi + \omega\,\tau\right) - \sin\left(12.5\,\omega + 2\,\phi + \omega\,\tau\right)\right)}{\omega} & \text{if } \omega \neq 0 \end{cases}$$

#### 3.5 part e

For a WSS process:

$$R_X(0) = E[x(t)x(t)]$$
  
$$R_X(\tau) = R_X(-\tau)$$

where  $R_X(\tau)$ :

$$R_X(\tau) = E\left[x(t+\frac{\tau}{2})x^*(t-\frac{\tau}{2})\right]$$

That is true in this stochastic process.

An ergodic process is a stationary random process for which:

$$A[x(t)] = E[x(t)]$$
  
$$R[x(t,\tau)] = R_X(\tau)$$

$$A[x(t)] \neq E[x(t)]$$

so this stochastic process is not ergodic.

# 4 Question 5

$$\begin{cases} \dot{x}_1(t) = x_2(t) \\ \dot{x}_2(t) = -\omega_n^2 x_1(t) - 2\zeta \omega_n x_2(t) + w(t) \end{cases}$$

where  $\omega_n = 10$ ,  $\zeta = 0.3$  and w(t) is with power  $\sigma^2$  and step time  $0.01_{\rm sec}$  ( $\sigma^2 = 1$ ).

#### 4.1 part a

## 4.2 part b

Assume:

$$A[x(t)] = \lim_{T \to \infty} \frac{1}{2T} \int_{-T}^{T} x(t)dt = \frac{1}{2T} \sum_{i=0}^{n} x(t_i) \Delta t = 0.0008$$

#### 4.3 part c

All parameters are calculated in the code (Q5/c.m).

$$mean = -0.0373$$

$$variance = 0.1255$$

#### 4.4 part d

All parameters are calculated in the code (Q5/d.m).

$$\mathrm{mean} = -0.0964$$

$$variance = 0.2509$$

#### 4.5 extra

In this section, the function was simulated 1000 times instead of 50 times to see the difference and improvement.

• part c extra

$$mean = -0.0023$$

$$variance = 0.1489$$

• part d extra

$$mean = 0.0361$$

$$variance = 0.3924$$

## 5 Question 6

$$\begin{bmatrix} \Delta \dot{x}_1 \\ \Delta \dot{x}_2 \\ \Delta \dot{x}_3 \\ \Delta \dot{x}_4 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 3n^2 & 0 & 0 & 2nr_n \\ 0 & 0 & -\frac{2n}{r_n} & 0 \end{bmatrix} \begin{bmatrix} \Delta x_1 \\ \Delta x_2 \\ \Delta x_3 \\ \Delta x_4 \end{bmatrix} + \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 1 & 0 \\ 0 & -\frac{1}{r_n} \end{bmatrix} \begin{bmatrix} w_r \\ w_\theta \end{bmatrix}$$
$$\begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ x_4 \end{bmatrix} = \begin{bmatrix} r \\ \theta \\ \dot{r} \\ \dot{\theta} \end{bmatrix}$$

## 5.1 part a

$$C = \begin{bmatrix} 1 & 0 & 0 & 0 \end{bmatrix}$$

$$\operatorname{rank}\left(\begin{bmatrix} C \\ CA \\ CA^2 \\ CA^3 \end{bmatrix}\right) = 3$$

System is not observable.

## 5.2 part b

$$C = \begin{bmatrix} 0 & 1 & 0 & 0 \end{bmatrix}$$

$$\operatorname{rank}\left(\begin{bmatrix} C \\ CA \\ CA^2 \\ CA^3 \end{bmatrix}\right) = 4$$

System is observable.

#### 5.3 part c

$$C = \begin{bmatrix} 1 & 1 & 0 & 0 \end{bmatrix}$$

$$\operatorname{rank} \left( \begin{bmatrix} C \\ CA \\ CA^2 \\ CA^3 \end{bmatrix} \right) = 4$$

System is observable.

## 5.4 part d

For subsection 5.2 we have:

Singular Value = 
$$\begin{bmatrix} 1 \\ 1 \\ 0 \\ 0 \end{bmatrix}$$

Ali BaniAsad 401209244 5.4 part d

For subsection 5.3 we have:

Singular Value = 
$$\begin{bmatrix} 15.3452 \\ 1.4142 \\ 0.9979 \\ 0 \end{bmatrix}$$

Observability is more straightforward in case 2 because the singular value is higher.

# Contents

1	Question 1    .1 part a     .2 part b	
2	Question 3	1
	.1 part a	
	.2 part b	. 2
3	Question 4	2
	.1 part a	. 2
	.2 part b	. 2
	.3 part c	. 3
	.4 part d	. 3
	.5 part e	. 3
4	Question 5	4
	.1 part a	. 4
	.2 part b	. 4
	.3 part c	
	.4 part d	
	.5 extra	
5	Question 6	5
	• .1 part a	. 5
	.2 part b	
	.3 part c	
	4 part d	5

# List of Figures

Ali BaniAsad 401209244 LIST OF TABLES

# List of Tables