

- Short discriminator is **3**, long discriminator is **840**.
- Vendor ID is **123**, Product ID is **456**.
- Commissioning Mode is **2**, indicating the Commissionee is currently in Commissioning Mode due to the **OpenCommissioningWindow** command.
 - Had the Commissionee been in Commissioning Mode due to the **OpenJointCommissioningWindow** command, a **CM=3** TXT key would have been published instead.
- Device type is **266** which is a smart plug (On/Off Plugin Unit, Device Type Identifier 0x010A).
- Device name is **Kitchen Plug**.
- Pairing hint is **256** which indicates that the Commissionee's reset button must be held down for 5 seconds to enter Commissioning Mode where the value 5 is obtained by reading the value of the PI key.
- Pairing instruction is **5**.

Avahi only sends a single AAAA record. To force the link-local address to be used, use avahi-publish-address. For example:

```
avahi-publish-address B75AFB458ECD.local fe80::f515:576f:9783:3f30
```

The DNS-SD service registration commands shown above results in the creation of the following Multicast DNS records:

_matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_S3._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_L840._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_V123._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_CM._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_T81._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
DD200C20D25AE5F7._matterc._udp.local.	TXT	"D=840" "VP=123+456" "CM=1" "DT=81"
"DN=Kitchen Plug" "PH=256" "PI=5"		
DD200C20D25AE5F7._matterc._udp.local.	SRV	0 0 11111 B75AFB458ECD.local.
B75AFB458ECD.local.	AAAA	fe80::f515:576f:9783:3f30

The port number 11111 is given here purely as an example. One of the benefits of using DNS-SD is that services are not constrained to use a single predetermined well-known port. The port, along with the IPv6 address, is discovered by Commissioners at run time.

A Commissioner can discover all available Commissionees awaiting commissioning:

```
dns-sd -B _matterc._udp
```

or