

9.14.6.7. PauseActionWithDuration Command

This command is used to pause an action with a duration.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ActionID	uint16	all			M
1	InvokeID	uint32	all			O
2	Duration	uint32	all		MS	M

This command pauses an ongoing action, and SHALL change the action's state to Paused. After the specified Duration, the ongoing action will be automatically resumed, which SHALL change the action's state to Active.

Example: pause a dynamic lighting effect (the lights stay at their current color) for 10 minutes (Duration=600).

The difference between Pause/Resume and Disable/Enable is on the one hand semantic (the former is more of a transitional nature while the latter is more permanent) and on the other hand these can be implemented slightly differently in the implementation of the action (e.g. a Pause would be automatically resumed after some hours or during a nightly reset, while an Disable would remain in effect until explicitly enabled again).

Duration Field

This field SHALL indicate the requested duration in seconds.

9.14.6.8. ResumeAction Command

This command is used to resume an action.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ActionID	uint16	all			M
1	InvokeID	uint32	all			O

This command resumes a previously paused action, and SHALL change the action's state to Active.

The difference between ResumeAction and StartAction is that ResumeAction will continue the action from the state where it was paused, while StartAction will start the action from the beginning.

Example: resume a dynamic lighting effect (the lights' colors will change gradually, continuing from the point they were paused).

9.14.6.9. EnableAction Command

This command is used to enable an action.