

clients to register themselves or other monitoring nodes to receive Check-In messages from an ICD. A client that needs to be able to interact with a [Long Idle Time ICDs](#) SHALL invoke the [Register-Client](#) command against it, typically during commissioning, or have the commissioner or some other existing client send the RegisterClient command on its behalf.

The [RegisterClient](#) command supplies the following parameters to the server:

1. An [ICDToken](#) (Key) which is used to encrypt the Check-In messages sent by the server.
2. A node identifier which specifies the node that will receive the Check-In messages.
3. A subject-id used to determine if a particular client has an active subscription.
4. The type of the client registering, permanent or ephemeral (e.g. mobile).

When a client registers with multiple servers, it SHALL use unique keys since the key is used to identify which server sent the Check-In message. Check-In messages do not have an originator address. Therefore, successfully decrypting a Check-In message with a key and having that key correspond to a specific server is the only way to identify which server sent the Check-In message.

If the commissioner is ephemeral and a separate stationary controller exists in the network, the commissioner SHOULD register the stationary controller in the [ICD Management cluster](#). Because an ICD is only required to provide one guaranteed client slot per fabric, clients SHOULD self-limit commissioning time registration.

Commissioner Self-Registration

A commissioner that is also a controller can register itself with the ICD during the device configuration portion of the commissioning process. This is the simplest client registration scenario, where a commissioner registers itself during commissioning. At the end of the commissioning process, the commissioner and ICD are **coupled**.

This diagram shows one possible process a commissioner can use to register itself with an ICD. Other processes are also possible such as a Commissioner which registers itself right after the **Add NOC** step and before the **Operational Discovery** step.