

11.10.5.3. NetworkRecoveryReasonEnum Type

This data type is derived from [enum8](#), however, the maximum value of the enumeration SHALL be less than 15.

This enumeration is used by the NetworkRecoveryReason attribute and may be embedded in the beacons advertising the need for Network Recovery.

Value	Name	Summary	Conformance	P
0	Unspecified	Unspecified / unknown reason of network failure	M	P
1	Auth	Credentials for the configured operational network are not valid	M	P
2	Visibility	Configured network cannot be found (e.g. the device cannot see the configured Wi-Fi SSID, Thread end-node is unable to find a parent router on the PAN)	M	P
15 - 255	DoNotUse		M	X

11.10.5.4. BasicCommissioningInfo Type

This structure provides some constant values that MAY be of use to all commissioners.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	FailSafe-ExpiryLengthSeconds	uint16	all				M
1	MaxCumulative-Fail-safeSeconds	uint16	desc				M