

5.2.6.18.8. ExpiringUser Value

This value SHALL indicate the user has the ability to open lock for ExpiringUserTimeout attribute minutes after the first use of the PIN code, RFID code, Fingerprint, or other credential. After ExpiringUserTimeout minutes the corresponding user record UserStatus value SHALL be set to OccupiedDisabled automatically by the lock. The lock SHALL persist the timeout across reboots such that the ExpiringUserTimeout is honored.

5.2.6.18.9. ScheduleRestrictedUser Value

This value SHALL indicate the user access is restricted by Week Day and/or Year Day schedule.

When UserType is set to ScheduleRestrictedUser, user access SHALL be restricted as follows:

- If no WeekDaySchedules and no YearDaySchedules are set for the user, then access SHALL be denied
- If one or more WeekDaySchedules are set, but no YearDaySchedules are set for the user, then user access SHALL be equivalent to the WeekDayScheduleUser UserType
- If one or more YearDaySchedules are set, but no WeekDaySchedules are set for the user, then user access SHALL be equivalent to the YearDayScheduleUser UserType
- If one or WeekDaySchedules are set AND one or more YearDaySchedules are set, then user access SHALL be granted if and only if the current time falls within at least one of the Week-DaySchedules AND the current time falls within at least one of the YearDaySchedules.

5.2.6.18.10. RemoteOnlyUser Value

This value SHALL indicate the user access and PIN code is restricted to remote lock/unlock commands only. This type of user might be useful for regular delivery services or voice assistant unlocking operations to prevent a PIN code credential created for them from being used at the keypad. The PIN code credential would only be provided over-the-air for the lock/unlock commands.

5.2.6.19. LockStateEnum Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0	NotFullyLocked	Lock state is not fully locked	M
1	Locked	Lock state is fully locked	M
2	Unlocked	Lock state is fully unlocked	M
3	Unlatched	Lock state is fully unlocked and the latch is pulled	O