

6.2.4.2. GetSetupPINResponse Command

This message is sent in response to the GetSetupPIN command, and contains the Setup PIN, or null when the account identified in the request does not match the active account of the running Content App.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	SetupPIN	string	desc			M

6.2.4.2.1. SetupPIN Field

This field SHALL provide the Setup PIN as a text string at least 8 characters in length or empty string to indicate that the accounts do not match.

NOTE	Newer cluster clients should be aware that AccountLogin cluster version 1 specified an 11 digit minimum length.
------	---

6.2.4.3. Login Command

The purpose of this command is to allow the Content App to assume the user account of a given Commissionee by leveraging the Setup PIN input by the user during the commissioning process.

For example, a Video Player with a Content App Platform may invoke this command on one of its Content App endpoints after the commissioning has completed of a Phone App made by the same vendor as the Content App. The Content App may determine whether the Temporary Account Identifier maps to an account with a corresponding Setup PIN and, if so, it may automatically login to the account for the corresponding user. The end result is that a user performs commissioning of a Phone App to a Video Player by inputting the Setup PIN for the Phone App into the Video Player UX. Once commissioning has completed, the Video Player invokes this command to allow the corresponding Content App to assume the same user account as the Phone App.

The verification of Setup PIN for the given Temporary Account Identifier is determined by the Content App using a method which is outside the scope of this specification and will typically involve a central service which is in communication with both the Content App and the Commissionee. Implementations of such a service should impose aggressive time outs for any mapping of Temporary Account Identifier to Setup PIN in order to prevent accidental login due to delayed invocation.

Upon receipt, the Content App checks if the account associated with the client’s Temp Account Identifier has a current active Setup PIN with the given value. If the Setup PIN is valid for the user account associated with the Temp Account Identifier, then the Content App MAY make that user account active.

The Temporary Account Identifier for a Commissionee may be populated with the Rotating ID field of the client’s commissionable node advertisement encoded as an octet string where the octets of the Rotating Device Identifier are encoded as 2-character sequences by representing each octet’s value as a 2-digit hexadecimal number, using uppercase letters.

The Setup PIN for a Commissionee may be populated with the Manual Pairing Code encoded as a