

9.3.8.15. NextChargeTargetSoC Attribute

This attribute SHALL indicate the target SoC the EVSE is going to attempt to reach when the vehicle is next charged.

A null value indicates that there is no scheduled charging (for example, the EVSE Mode is set to use Manual mode tag), or that the vehicle is not plugged in with the SupplyState indicating that charging is enabled, or that the next [ChargingTargetStruct](#) is using the AddedEnergy value to charge the vehicle.

If the SOC feature is not supported, only the values null and 100% are supported.

9.3.8.16. ApproximateEVEfficiency Attribute

This attribute SHALL indicate the vehicle efficiency rating for a connected vehicle.

This can be used to help indicate to the user *approximately* how many miles or km of range will be added. It allows user interfaces to display to the user simpler terms that they can relate to compared to kWh.

This value is stored in km per kWh multiplied by a scaling factor of 1000.

A null value indicates that the EV efficiency is unknown and the [NextChargeRequiredEnergy](#) attribute cannot be converted from Wh to miles or km.

To convert from Wh into Range:

$$\begin{aligned}\text{AddedRange (km)} &= \text{AddedEnergy (Wh)} \times \text{ApproxEVEfficiency (km/kWh} \times 1000) \\ \text{AddedRange (Miles)} &= \text{AddedEnergy (Wh)} \times \text{ApproxEVEfficiency (km/kWh} \times 1000) \times \\ &0.6213\end{aligned}$$

Example:

$$\begin{aligned}\text{ApproxEVEfficiency (km/kWh} \times 1000): &4800 \text{ (i.e. } 4.8\text{km/kWh} \times 1000) \\ \text{AddedEnergy (Wh):} &10,000\end{aligned}$$

$$\begin{aligned}\text{AddedRange (km)} &= 10,000 \times 4800 / 1,000,000 = 48 \text{ km} \\ \text{AddedRange (Miles)} &= \text{AddedEnergy (Wh)} \times \text{ApproxEVEfficiency (km/kWh} \times 1000) \times \\ &0.6213 \\ &= 29.82 \text{ Miles}\end{aligned}$$

9.3.8.17. StateOfCharge Attribute

This attribute SHALL indicate the state of charge of the EV battery in steps of 1%. The values are in the 0-100%. This attribute is only available on EVSEs which can read the state of charge from the vehicle and that support the **SOC** feature. If the StateOfCharge cannot be read from the vehicle it