

Mode Tag Value	Name
0x0002	Quiet
0x0003	LowNoise
0x0004	LowEnergy
0x0005	Vacation
0x0006	Min
0x0007	Max
0x0008	Night
0x0009	Day
0x4000	Off
0x4001	Manual
0x4002	Timed

9.6.7.1.1. Off Tag

While in modes with this tag, the device will not attempt to keep the water warm.

9.6.7.1.2. Manual Tag

While in modes with this tag, the device will attempt to keep the water warm based on the OccupiedHeatingSetpoint attribute of the associated Thermostat cluster.

9.6.7.1.3. Timed Tag

While in modes with this tag, the device will attempt to keep the water warm based on the Schedules attribute of the associated Thermostat cluster.

9.6.8. Mode Examples

A few examples of Water Heater modes and their mode tags are provided below.

- For the "Off" mode, tags: 0x4000 (Off)
- For the "Manual" mode, tags: 0x4001 (Manual)
- For the "Timed" mode, tags: 0x4002 (Timed)

9.7. Energy Preference Cluster

This cluster provides an interface to specify preferences for how devices should consume energy.

NOTE Support for Energy Preference cluster is provisional.