

- Respond with the status code SUCCESS.

11.3.7.5. MPTZRemovePreset Command

This command SHALL remove a preset entry from the PresetMptzTable. The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PresetID	uint8	1 to MaxPresets			M

11.3.7.5.1. PresetID Field

This field SHALL indicate the ID of an entry in [MptzPresets](#).

11.3.7.5.2. Effect on Receipt

The process below SHALL be followed by the camera when receiving this command:

- If the PresetID does not exist in [MptzPresets](#):
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
- Remove the entry for the provided PresetID from [MptzPresets](#).
- Respond with the status code SUCCESS

11.3.7.6. DPTZSetViewport Command

This command allows for setting the digital viewport for a specific Video Stream. This command is a per-stream version of the [Viewport Attribute](#). The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	VideoStreamID	VideoStreamIDType	all			M
1	Viewport	ViewportStruct				M

11.3.7.6.1. VideoStreamID Field

This field SHALL be a [VideoStreamIDType](#) representing the video stream to modify.

11.3.7.6.2. Viewport Field

This field SHALL be a [ViewportStruct](#) representing the new viewport to apply to the requested stream. The aspect ratio of the viewport SHALL match the aspect ratio of the stream requested.