

```
avahi-publish-service --subtype=_S3._sub._matterc._udp
--subtype=_L840._sub._matterc._udp DD200C20D25AE5F7 --subtype=_CM._sub._matterc._udp
_matterc._udp 11111 D=840 CM=2
```

- Short discriminator is filterable through **_S3** subtype and algorithmically through **D=840** TXT key.
- Long discriminator is filterable through **_L840** subtype and directly through **D=840** TXT key.
- The Commissionee is currently in Commissioning Mode after an Administrator having opened a commissioning window (see [Section 4.3.1.7, “TXT key for commissioning mode \(CM\)”](#)), as shown by **CM=2** TXT key and availability by browsing the **_CM** subtype.
 - Had the Commissionee been discoverable for initial commissioning rather than subsequent additional commissioning, a **CM=1** TXT key would have been published instead.
 - Had the Commissionee been in Commissioning Mode due to the [OpenJointCommissioning-Window](#) command, a **CM=3** TXT key would have been published instead.

Avahi only sends a single AAAA record. To force the link-local address to be used, use avahi-publish-address. For example:

```
avahi-publish-address B75AFB458ECD.local fe80::f515:576f:9783:3f30
```

The DNS-SD service registration commands shown above results in the creation of the following Multicast DNS records:

_matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_S3._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_L840._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
_CM._sub._matterc._udp.local.	PTR	DD200C20D25AE5F7._matterc._udp.local.
DD200C20D25AE5F7._matterc._udp.local.	SRV	0 0 11111 B75AFB458ECD.local.
DD200C20D25AE5F7._matterc._udp.local.	TXT	"D=840" "CM=2"
B75AFB458ECD.local.	AAAA	fe80::f515:576f:9783:3f30

Consider a device on Wi-Fi using the 48-bit device MAC address of B75AFB458ECD as its host name. DNS-SD records for it can be set up as follows, when it is in Commissionable Node Discovery.

```
dns-sd -R DD200C20D25AE5F7 _matterc._udp,_S3,_L840,_V123,_CM,_T81 . 11111 D=840
VP=123+456 CM=2 DT=266 DN="Kitchen Plug" PH=256 PI=5
```

or

```
avahi-publish-service --subtype=_S3._sub._matterc._udp
--subtype=_L840._sub._matterc._udp --subtype=_V123._sub._matterc._udp
--subtype=_CM._sub._matterc._udp --subtype=_T81._sub._matterc._udp DD200C20D25AE5F7
_matterc._udp 11111 D=840 VP=123+456 CM=2 DT=81 DN="Kitchen Plug" PH=256 PI=5
```