

Protocol Opcode	Protocol Command Name	Description
0x33	CASE Sigma2_Resume	The second resumption message of the CASE protocol.
0x40	StatusReport	The Status Report message encodes the result of an operation in the Secure Channel as well as other protocols.
0x50	ICD Check-In message	The Check-in message notifies a client that the ICD is available for communication.

4.11.1.1. Session Establishment - Out of Resources

After a successful session establishment using [CASE](#) or [PASE](#), a responder may not have enough resources to save all of the [session context information](#). To free resources, a responder SHALL evict an existing session using the following procedure:

1. Use the [SessionTimestamp](#) to determine the least-recently used session.
2. Determine the session that was least-recently used then:
 - a. Send a [status report](#): `StatusReport(GeneralCode: SUCCESS, ProtocolId: SECURE_CHANNEL, ProtocolCode: CLOSE_SESSION)` message to the peer node
 - b. Remove all state associated with the session (see [Section 4.13.3.1, “Secure Session Context”](#)). The Node MAY save state necessary to perform [Session Resumption](#), see [Section 4.14.2.2.1, “Session Resumption State”](#) for more details.
3. Respond to the initiator with the appropriate session establishment message

4.11.1.2. Status Report

The Status Report message is sent from protocol handlers to convey the status of an operation using a common format as defined in [Appendix D, Status Report Messages](#). The *StatusReport* message is a part of the Secure Channel protocol, but embeds an additional context-specific ProtocolID field in its message-specific payload. In this way, the *StatusReport* can convey status for any protocol handler.

4.11.1.3. Secure Channel Status Report Messages

Status Reports specific to the Secure Channel are designated by embedding the [PROTOCOL_ID_SECURE_CHANNEL](#) in the ProtocolId field of the *StatusReport* body. All Secure Channel Status Report Messages SHALL use the [PROTOCOL_ID_SECURE_CHANNEL](#) protocol id. For example, a failure to find a common root of trust may be written in the specification as follows: `StatusReport(GeneralCode: FAILURE, ProtocolId: SECURE_CHANNEL, ProtocolCode: NO_SHARED_TRUST_ROOTS)`.

There are several cases for which the secure channel layer may emit a status report:

1. To indicate successful session establishment
2. In response to errors during session establishment
3. In response to errors after session establishment
4. To indicate that a Node is terminating a session