

Vendors are encouraged to use Matter-common elements where applicable.

Table 63. Matter-common Reserved Tags

Tag	Value	Description	Type(s)
<i>kTag_Serial-Number</i>	0x00	Device Serial #	UTF-8 String (length = 1..32 bytes) Unsigned Integer, up to 8-byte value (has room to represent a 19-digit decimal number)
<i>PBKDFIterations</i> *	0x01	PBKDFParameterSet Iterations	Unsigned Integer (range = CRYPTO_PBKDF_ITERATIONS_MIN.. CRYPTO_PBKDF_ITERATIONS_MAX)
<i>PBKDFSalt</i> *	0x02	PBKDFParameterSet Salt	Octet String (length = 16..32 bytes)
<i>kTag_NumberOfDevices</i>	0x03	Number of devices that are expected to be commissioned using this payload when using the Enhanced Commissioning Method	Unsigned Integer, range 1 to 255
<i>kTag_CommissioningTime-out</i>	0x04	Time, in seconds, during which the device(s) are expected to be commissionable using the Enhanced Commissioning Method	Unsigned Integer, see Section 5.4.2.3, “Announcement Duration”
reserved	0x05..0x7F	reserved for future use	

* If the PBKDF parameters are to be included in the TLV section, both the **PBKDFSalt** and **PBKDFIterations** SHALL be encoded.

5.1.5.3. TLV Examples

Manufacturer-specific and Matter-common elements

```
{
  vendorTag01 (0x81) = "Vendor",
  kTag_SerialNumber(0) = "1234567890"
}
```

The above notation encodes to the following bytes:

```
0x15 0x2C 0x81 0x06 0x56 0x65 0x6E 0x64 0x6F 0x72 0x2C 0x00 0x0A 0x31 0x32 0x33
0x34 0x35 0x36 0x37 0x38 0x39 0x30 0x18
```