

Parameter Name	Feature	Description
PairingHint	Bypass Commissionable Node Discovery	The pairing hint as described in the mdns TXT records (see Section 4.3.1.11 , “TXT key for pairing hint (PH)”).
RotatingDeviceId	Bypass Commissionable Node Discovery	The Rotating Device Identifier as described in the mdns txt records (see Section 4.3.1.10 , “TXT key for rotating device identifier (RI)”).
Port	Bypass Commissionable Node Discovery	The service port for PASE as found in the SRV record of the DNS-SD Commissionable Node Discovery response.
TargetAppList	Target Content Application	The set of content app Vendor IDs (and optionally, Product IDs) that can be used for authentication.
TargetApp	Target Content Application	An entry in the TargetAppList which contains a TargetVendorId and an optional TargetProductId.
AppVendorId	Target Content Application	The content app Vendor IDs that can be used for authentication.
AppProductId	Target Content Application	The content app Product ID associated with the specified Vendor ID that can be used for authentication.
NoPasscode	Target Content Application	Flag to instruct the Commissioner not to display a Passcode input dialog, and instead send a CommissionerDeclaration message if a commissioning Passcode is needed.
CdUponPasscodeDialog	Coordinate Passcode Dialogs	Flag to instruct the Commissioner to send a CommissionerDeclaration message when the Passcode input dialog on the Commissioner has been shown to the user.
Commissioner-Passcode	Commissioner-Generated Passcode	Flag to instruct the Commissioner to use the Commissioner-generated Passcode for commissioning.
Commissioner-PasscodeReady	Commissioner-Generated Passcode	Flag to indicate whether or not the Commissionee has obtained the Commissioner Passcode from the user and is therefore ready for commissioning.
CancelPasscode	Coordinate Passcode Dialogs	Flag to indicate when the Commissionee user has decided to exit the commissioning process.