

| ID | Name             | Type                                   | Constraint | Quality | Fallback | Conformance |
|----|------------------|----------------------------------------|------------|---------|----------|-------------|
| 0  | <b>ErrorCode</b> | <a href="#">CommissioningErrorEnum</a> |            |         | OK       | M           |
| 1  | <b>DebugText</b> | string                                 | max 128    |         | ""       | M           |

#### ErrorCode Field

This field SHALL contain the result of the operation, based on the behavior specified in the functional description of the ArmFailSafe command.

#### DebugText Field

See [Section 11.10.7.1, “Common fields in General Commissioning cluster responses”](#).

### 11.10.7.4. SetRegulatoryConfig Command

This command is used to set the regulatory configuration for the device.

This SHALL add or update the regulatory configuration in [the RegulatoryConfig Attribute](#) to the value provided in the NewRegulatoryConfig field.

| ID | Name                       | Type                                       | Constraint | Quality | Fallback | Conformance |
|----|----------------------------|--------------------------------------------|------------|---------|----------|-------------|
| 0  | <b>NewRegulatoryConfig</b> | <a href="#">RegulatoryLocationTypeEnum</a> |            |         |          | M           |
| 1  | <b>CountryCode</b>         | <a href="#">string</a>                     | 2          |         |          | M           |
| 2  | <b>Breadcrumb</b>          | uint64                                     |            |         |          | M           |

Success or failure of this command SHALL be communicated by the [SetRegulatoryConfigResponse](#) command, unless some data model validations caused a failure status code to be issued during the processing of the command.

The CountryCode field SHALL conform to ISO 3166-1 alpha-2 and SHALL be used to set the [Location](#) attribute reflected by the [Basic Information Cluster](#).

If the server limits some of the values (e.g. locked to a particular country, with no regulatory data for others), then setting regulatory information outside a valid country or location SHALL still set the [Location](#) attribute reflected by the [Basic Information Cluster](#) configuration, but the SetRegulatoryConfigResponse replied SHALL have the ErrorCode field set to [ValueOutsideRange](#) error.

If the [LocationCapability](#) attribute is not Indoor/Outdoor and the NewRegulatoryConfig value received does not match either the Indoor or Outdoor fixed value in LocationCapability, then the SetRegulatoryConfigResponse replied SHALL have the ErrorCode field set to [ValueOutsideRange](#)