

Value	Name	Summary	Conformance
3	SsidNotFound	The specified SSID could not be found.	M

11.15.5.4. ConnectionStatusEnum Type

This data type is derived from [enum8](#).

Value	Name	Summary	Conformance
0	Connected	Indicate the node is connected	M
1	NotConnected	Indicate the node is not connected	M

11.15.6. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	BSSID	octstr	6	X	null	R V	M
0x0001	Security-Type	Security-TypeEnum	all	X	null	R V	M
0x0002	WiFiVersion	WiFiVersionEnum	all	X	null	R V	M
0x0003	Channel-Number	uint16	all	X	null	R V	M
0x0004	RSSI	int8	-120 to 0	C X	null	R V	M
0x0005	Beacon-LostCount	uint32	all	C X	0	R V	ERRCNT
0x0006	BeaconRx-Count	uint32	all	C X	0	R V	PKTCNT
0x0007	Packet-MulticastRxCount	uint32	all	C X	0	R V	PKTCNT
0x0008	Packet-Multicast-TxCount	uint32	all	C X	0	R V	PKTCNT
0x0009	PacketUnicastRx-Count	uint32	all	C X	0	R V	PKTCNT
0x000A	PacketUnicastTx-Count	uint32	all	C X	0	R V	PKTCNT