

1.13.5. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	NumberOfPositions	uint8	min 2	F		R V	M
0x0001	CurrentPosition	uint8	max (NumberOfPositions - 1)	N		R V	M
0x0002	MultiPressMax	uint8	min 2	F		R V	MSM

1.13.5.1. NumberOfPositions Attribute

This attribute SHALL indicate the maximum number of positions the switch has. Any kind of switch has a minimum of 2 positions. Also see [Section 1.13.10, “Multi Position Details”](#) for the case NumberOfPositions>2.

1.13.5.2. CurrentPosition Attribute

This attribute SHALL indicate the position of the switch.

The valid range is zero to NumberOfPositions - 1.

CurrentPosition value 0 SHALL be assigned to the default position of the switch: for example the "open" state of a rocker switch, or the "idle" state of a push button switch.

1.13.5.3. MultiPressMax Attribute

This attribute SHALL indicate how many consecutive presses can be detected and reported by a momentary switch which supports multi-press (MSM feature flag set).

For example, a momentary switch supporting single press, double press and triple press, but not quad press and beyond, would return the value 3.

When more than MultiPressMax presses are detected within a multi-press sequence:

- The server for cluster revision < 2 SHOULD generate a MultiPressComplete event with the TotalNumberOfPressesCounted field set to the value of the MultiPressMax attribute, and avoid generating any further InitialPress and MultiPressOngoing events until the switch has become fully idle (i.e. no longer in the process of counting presses within the multipress).
- The server for cluster revision >= 2 SHALL generate a MultiPressComplete event with the TotalNumberOfPressesCounted field set to zero (indicating an aborted sequence), and SHALL NOT generate any further InitialPress and MultiPressOngoing events until the switch has become fully idle (i.e. no longer in the process of counting presses within the multipress).

This approach avoids unintentionally causing intermediate actions where there is a very long