

2.14.7.1.2. Effect on Receipt

The following process SHALL be followed when the server receives this command:

- If the current number of UserDefined Zones within **Zones** equals **MaxUserDefinedZones**:
 - Fail the command with the status code RESOURCE_EXHAUSTED, and end processing with no other side effects.
- If the **Use** field of the passed in **Zone** is **Focus Value** and the device does not support **FocusZones**:
 - Fail the command with the status code CONSTRAINT_ERROR, and end processing with no other side effects.
- If any **X** or **Y** points, in the **Vertices** field, of the **TwoDCartesianZone** field, of the passed in **Zone**, are greater than the corresponding point values in **TwoDCartesianMax**:
 - Fail the command with the status code DYNAMIC_CONSTRAINT_ERROR, and end processing with no other side effects.
- If the **Vertices** and **Use** fields, of the **TwoDCartesianZone** field, of the passed in **Zone**, exactly match the corresponding fields of any entry in the **Zones** attribute:
 - Fail the command with the status code ALREADY_EXISTS, and end processing with no other side effects.
- If the resulting shape of the **Vertices** field, of the **TwoDCartesianZone** field, of the passed in **Zone**, results in any self-intersecting lines:
 - Fail the command with the status code DYNAMIC_CONSTRAINT_ERROR, and end processing with no other side effects.
- Create a new ZoneID as described in **ZoneID** within **Zones**
- Create a new **ZoneInformationStruct** setting **ZoneID** to the new ZoneID, **ZoneSource** to **User**, the passed in **Zone** as **TwoDCartesianZone**, and **ZoneType** to **TwoDCARTZone**.
- Add that **ZoneInformationStruct** as a new entry in **Zones**.
- Return the new ZoneID in the corresponding **CreateTwoDCartesianZoneResponse** command.

2.14.7.2. CreateTwoDCartesianZoneResponse Command

This command SHALL be generated in response to a CreateTwoDCartesianZone command.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ZoneID	ZoneID				M

2.14.7.2.1. ZoneID Field

The ZoneID field SHALL be an unsigned 16 bit integer representing the unique ZoneID.

2.14.7.3. UpdateTwoDCartesianZone Command

The UpdateTwoDCartesianZone SHALL update a stored **TwoD Cartesian Zone**.