

maintain product operational safety, etc.

When the value of the [FanMode](#) attribute is AUTO, the value of this attribute MAY vary across the range over time.

See [Section 4.4.6.6.1, “Speed Rules”](#) for more details.

4.4.6.8. RockSupport Attribute

This attribute is a bitmap that indicates the rocking motions that are supported by the server.

If this attribute is supported by the server, at least one bit SHALL be set in this attribute.

4.4.6.9. RockSetting Attribute

This attribute is a bitmap that indicates the currently active fan rocking motion setting. Each bit SHALL only be set to 1, if the corresponding bit in the RockSupport attribute is set to 1, otherwise a status code of CONSTRAINT_ERROR SHALL be returned.

If a combination of supported bits is set by a client, and the server does not support the combination, the lowest supported single bit in the combination SHALL be set and active, and all other bits SHALL indicate zero.

For example: If RockUpDown and RockRound are both set, but this combination is not possible, then only RockUpDown becomes active.

4.4.6.10. WindSupport Attribute

This attribute is a bitmap that indicates what wind modes are supported by the server.

If this attribute is supported by the server, at least one bit SHALL be set in this attribute.

4.4.6.11. WindSetting Attribute

This attribute is a bitmap that indicates the current active fan wind feature settings. Each bit SHALL only be set to 1, if the corresponding bit in the WindSupport attribute is set to 1, otherwise a status code of CONSTRAINT_ERROR SHALL be returned.

If a combination of supported bits is set by a client, and the server does not support the combination, the lowest supported single bit in the combination SHALL be set and active, and all other bits SHALL indicate zero.

For example: If Sleep Wind and Natural Wind are set, but this combination is not possible, then only Sleep Wind becomes active.

4.4.6.12. AirflowDirection Attribute

This attribute SHALL indicate the current airflow direction of the fan. This attribute MAY be writ-